6. Audio version

Prompt 2 was run on the final corrected text in three tools. All three said every number, exponent and unit correctly, so explicit "spell it out in words" rules worked well for audio.

6.1 Audio script comparison

Criterion	Gemini	ChatGPT	NotebookLM
Numbers and exponents	All correct	All correct	All correct
Added content	Greeting; "capital letter C/A"	Signposting; defines I, Q, t	"Tiny"; greeting and goodbye
Listening structure	Good	Best (section transitions)	Good
Precision	Good	Good	Recap point 1 slightly imprecise (said "charge flowing through a circuit")
Length	About 420 words	About 400 words	About 380 words
Cleanup needed	Remove opening filler	Remove title line	Remove tool offer, emoji, filler
Attempts	1	1	2 (first reply was a feature offer, not a script)

6.2 Final audio script (merged)

Let us learn about electric current and circuits.

Electric current is the flow of electric charge through a conductor. A metallic wire is an example of a conductor.

A continuous, closed path for electric current is an electric circuit. A switch joins the cell and the bulb. If the circuit breaks anywhere, the current stops. Then the bulb does not glow.

Now, how is current measured? Current is the amount of charge flowing through an area in unit time. Suppose a net charge Q flows across a cross-section in time t. Then the current I equals Q divided by t. Here, I is current, Q is charge, and t is time.

Next, the direction of current. In metal wires, electrons carry negative charge. Electrons were not known when electricity was first studied. So people thought positive charges were flowing. By convention, current flows opposite to the flow of electrons. It flows from the positive terminal of the cell to the negative terminal.

Now, the units. The SI unit of charge is the coulomb. One coulomb is the charge of nearly six times ten to the power eighteen electrons. One electron has a negative charge of one point six times ten to the power minus nineteen coulombs.

The SI unit of current is the ampere. It is named after Andre-Marie Ampere. One ampere equals one coulomb per second. Small currents use smaller units. One milliampere equals ten to the

power minus three amperes. One microampere equals ten to the power minus six amperes.

An ammeter measures electric current. It is always connected in series.

Let us solve one example from the book. The current is zero point five amperes. The time is ten minutes, which is six hundred seconds. Charge equals current times time. So charge equals zero point five amperes times six hundred seconds. The charge is three hundred coulombs.

Here is a quick recap. First, an electric circuit is a continuous, closed path for current. Second, current is the rate of flow of charge. Current I equals charge Q divided by time t. Its SI unit is the ampere. Third, current flows opposite to the flow of electrons, from the positive terminal to the negative terminal.

6.3 Audio file

Item	Detail
Tool and settings	ElevenLabs (free tier), model elevenlabs-v4, style "warmly", generated 19 October 2026
File	MP3, 128 kbps, 44.1 kHz, mono, about 2.4 MB
Length	149.9 seconds (about 2 min 30 s), within the 2-3 minute target
Listening check	Listened in full by the student: no misread numbers, exponents or names; no fixes needed
Label	AI-generated voice (ElevenLabs)