



MSGEQ7 support parts are the datasheet Typical Application: 22k + 0.01uF into IN, 0.1uF on VDD (CD) and on pin 6 (CG), 200k from CKIN up to VDD and 33pF from CKIN down to GND (165 kHz clock).



J3 Eurorack 10-pin bus: +5V and GND only. Confirm which pins carry them on your bus board before wiring.

J4 External 5 V supply (screw terminal).

The LEDs are the load that matters: 145 LEDs (5 x 29) draw several amps at full white, far beyond a Eurorack 5 V rail. Big case: external supply on J4 feeds both the board and the LEDs. Small case (3 x 29): same rule.

Strip layout is set in the web UI (strips x LEDs per strip), chained on one data line with alternate strips reversed.

diydoohickeys.com
Audio-reactive lighting controller for a modular synth case
DIY Doohickeys

Sheet: /
File: rackglow.kicad_sch

Title: Rackglow

Size: A4	Date:
KiCad E.D.A. 10.0.4	

Rev:
Id: 1/1