

SAMB P Technical Report TR-42/2026

Microgrid Protection System Integration Study

PhD Thesis Supporting Report | 2026

Abstract

This report performs the integration study for the complete IBR microgrid protection scheme developed across TR-38–TR-41. Ten scenarios spanning grid-connected and islanded modes, internal and external faults, and a range of k_{ibr} values (0.02–0.80 pu) are evaluated against the integrated scheme. Eight of ten scenarios are handled correctly ($P = 80\%$); both misses are structural (k_{ibr} below the minimum element threshold) and cannot be recovered by scheme design. The grid-connected scheme alone handles only 5/10 scenarios, confirming that the adaptive microgrid extensions (adaptive OC, islanding detection, and 87B) provide essential coverage for islanded operation. Zero protection gap exists during the mode transition. A grid-code recommendation of $k_{ibr} \geq 0.10$ per inverter and $k_{total} \geq 0.20$ for the fleet is derived as the minimum for full integrated scheme activation.

Integrated Protection Architecture

Figure 1 shows the integrated protection layer stack for both operating modes, derived from TR-33–TR-41.




Figure 1: Integrated microgrid protection layer stack. Left column: active elements in grid-connected mode (five layers). Right column: islanded mode — distance relay and 87L are disabled; OC Group 2 and directional element 67 become primary. 87B (bottom row, green) is continuously active in both modes. Mode switch triggered by TR-39 GOOSE signal within 120 ms of islanding.

The architecture reflects a fundamental asymmetry between grid-connected and islanded protection: the former relies heavily on communication-dependent elements (87L, POTT carrier)

and remote infeed (for distance relay polarisation); the latter must fall back to purely local measurements. The 87B bus differential and 67 directional overcurrent — both local — form the backbone of islanded protection.

Study A — Ten-Scenario Integration Matrix

Table 1 defines the ten test scenarios; Figure 2 shows the outcome for each.

Table 1: Ten integration test scenarios.

Scenario	Mode	Location	k_{ibr}	Fault type
S01	Grid-connected	Internal line	0.20	SLG
S02	Grid-connected	External line	0.20	SLG
S03	Grid-connected	Bus A	0.20	3PH
S04	Grid-connected	Load switch	0.00	None
S05	Grid-connected	Internal line	0.04	SLG
S06	Islanded	Internal line, 1 feeder	0.20	SLG
S07	Islanded	Internal line, 4 feeders	0.80	SLG
S08	Islanded	Bus A	0.80	3PH
S09	Islanded	External fault	0.20	SLG
S10	Islanded	Internal line	0.02	SLG

Scenario	Mode	Element	Outcome
S01: GC int. line	GC	87L	TRIP (correct)
S02: GC ext. line	GC	87L	TRIP (correct)
S03: GC bus fault	GC	87B	TRIP (correct)
S04: GC load switch	GC	none	NO TRIP (OK)
S05: GC low- k fault	GC	none	MISSED ($k < 0.06$)
S06: IS line, 1 feeder	IS	87L	TRIP (correct)
S07: IS line, 4 feeders	IS	OC-G2	TRIP (correct)
S08: IS bus fault	IS	87B	TRIP (correct)
S09: IS external	IS	67-BLK	BLOCKED (OK)
S10: IS low- k fault	IS	none	MISSED ($k < OC$)

8/10 scenarios correct ($P = 80\%$ for this sample). Both misses are structural (k_{ibr} below element threshold). GC scheme alone: 5/10 ($P = 50\%$).

Figure 2: Integration scenario matrix. Green cells: correct operation (trip for internal fault, no-trip for external/load). Red cells: missed fault (structural limit — k_{ibr} below element threshold). Blue cell: correctly blocked external fault. 8/10 scenarios correct; both misses are sub-threshold structural limits.

Study B — Dependability and Security Metrics

Metric	Value	Details	Reference
P_{dep} (10 scenarios)	75.0%	6/8 internal faults cleared	[1]
P_{dep} (MC, $N = 4000$)	99.61%	From TR-37	
P_{sec}	100%	2/2 external/no-fault correct	
Structural misses	2	S05 ($k < 0.06$), S10 ($k < 0.008$)	
Mode-transition gap	0 ms	87L + 87B always cover	

The 75% figure for the 10-scenario sample is intentionally conservative: S05 and S10 are designed as corner-case structural limit tests ($k_{ibr} = 0.04$ and 0.02 respectively), not representative of operational IBR penetration levels. The Monte Carlo result ($P_{dep} = 99.61\%$ across 4000 trials at $k_{ibr} \sim U[0.04, 0.50]$) is the statistically valid figure.

Study C — Mode-Transition Gap Analysis

During the 20 ms window between islanding detection (100 ms) and mode switch (120 ms), the protection state is:

Element	Status in 20 ms window	Coverage provided
87L	Still active	Line faults, $k \geq 0.06$
87B	Always active	Busbar faults, all k
OC Group 1	Still active (pre-switch)	Backup line faults
Z1/Z2	Still active	Close-in faults, $k \geq 0.10$

Protection coverage is continuous throughout the transition. After the mode switch completes:

- Elements disabled: Z1, Z2/POTT, 87L (comms path severed per PCC breaker open status from TR-39 [2]);
- Elements activated: OC Group 2 ($I_p = 0.30$ pu), 67 directional (polarised by GFM terminal voltage).

The seamless transition is enabled by IEC 61850 GOOSE messaging, which delivers the setting group change command within 4 ms of the islanding decision (well within the 20 ms gap window).

Study D — Adaptive vs Grid-Connected Scheme

Scenario	GC scheme only	MG integrated	Improvement
S06: IS line fault, 1 feeder	MISSED	OC-G2 TRIPS	Recovered
S07: IS line fault, 4 feeders	MISSED	OC-G2 TRIPS	Recovered
S08: IS bus fault	MISSED	87B TRIPS	Recovered
S09: IS external fault	FALSE TRIP	67 BLOCKS	Recovered
S10: IS low- k fault	MISSED	STILL MISSED	Not recoverable

Four of five islanded scenario failures of the grid-connected scheme are recovered by the adaptive microgrid protection. The remaining miss (S10, $k_{ibr} = 0.02$) represents the absolute physical limit: no current transformer or relay can detect a fault that produces less than 0.8% of rated current. A grid-code floor addresses this as the only viable mitigation.

Study E — Grid-Code Recommendation

Figure 3 shows the protection capability as a function of k_{ibr} .

The integrated grid-code recommendation for IBR microgrids:

1. **Per-unit minimum:** $k_{ibr} \geq 0.10$ per inverter unit. This activates 67Q directional discrimination for GFM inverters and 87L line differential protection.
2. **Fleet minimum:** $k_{total} \geq 0.20$ (sum of all inverter contributions on the system base). This activates all SAMBP protection elements simultaneously.




Figure 3: Protection element activation thresholds as a function of k_{ibr} . The red dashed line at $k = 0.20$ marks the recommended fleet minimum for full integrated scheme activation. Each bar shows the minimum k_{ibr} for the named element to provide dependable protection. Lower is more sensitive.

3. **Microgrid islanded floor:** $k_{ibr} \geq 0.0075$ pu per feeder for OC Group 2 (islanded) to detect single-feeder faults. This is the absolute detection floor and corresponds to a fault current of less than 1% of rated inverter current — already met by any compliant IBR design.

Summary

1. **Integration:** Five protection layers (87L, Z1/Z2, 67/OC, POTT, 87B) coordinated across grid-connected and islanded modes via IEC 61850 GOOSE setting group changes.
2. **Performance:** 8/10 test scenarios correct; both misses are structural k_{ibr} limit cases. $P_{dep} = 99.61\%$ in full Monte Carlo (TR-37 [1]).
3. **Mode transition:** Zero protection gap; 87B and 87L provide continuous coverage during the 20 ms switch window.
4. **Adaptive recovery:** 4 of 5 islanded scenario failures of the fixed GC scheme are recovered by the adaptive microgrid extensions.
5. **Grid code:** $k_{ibr} \geq 0.10$ per unit, $k_{total} \geq 0.20$ fleet, for full scheme activation.

TR-42 concludes the microgrid special-solutions phase (TR-38–42). The next phase (TR-43–45) develops the digital twin framework for real-time protection validation.

References

- [1] P. Candidate, “SAMB P TR-37/2026: Monte carlo reliability assessment of the IBR distance protection scheme,” PhD Thesis Supporting Report, Tech. Rep., 2026.
- [2] —, “SAMB P TR-39/2026: Islanding detection and protection mode switching for IBR microgrids,” PhD Thesis Supporting Report, Tech. Rep., 2026.