

SAMBP TR-20/2026

Frequency-Adaptive 87L Charging-Current Correction for Inverter-Dominated Microgrids

PhD Candidate

Smart Adaptive Multi-Bus Protection Research

April 2026

Contents

1	Background and Motivation	1
2	Frequency-Adaptive Correction Algorithm	2
2.1	Correction Formula	2
2.2	Processing Pipeline	2
3	Frequency Estimator	3
3.1	Zero-Crossing Method	3
3.2	Accuracy and Fallback	3
3.3	DFT Alternative	4
4	Study Results	4
4.1	Study A: No-Fault Residual Charging Error	4
4.2	Study B: Internal Fault Detection	4
4.3	Study C: Security (External Fault)	5
4.4	Selectivity Summary	5
5	Sensitivity to Line Parameters	6
5.1	Critical B_C at which Fixed Correction Causes False Trips	6
5.2	ROCOF Transient Considerations	6
6	Integration with SAMBP Suite	6
7	Conclusions	7
7.1	Future Work	7

1 Background and Motivation

TR-15 [Candidate \[2026\]](#) introduced pi-section charging-current correction for the SAMBP 87L line differential relay. The correction computes the expected charging differential as:

$$\hat{i}_C(t) = B_C \cdot \text{Im}\{H[v_{\text{avg}}(t)]\} \quad (1)$$

where $B_C = \omega_0 C_{\text{total}}$ is the total line susceptance evaluated at the *nominal* frequency $\omega_0 = 2\pi f_0$, and $H[\cdot]$ is the Hilbert transform (wideband 90° phase shift).

In inverter-dominated microgrids the system frequency deviates from 50 Hz due to droop control. ENTSO-E RfG [ENTSO-E \[2016\]](#) specifies a normal operating range of 47.5–51.5 Hz; IEC 60255-181 [IEC \[2019\]](#) requires protection to remain operable down to 47 Hz. Under islanded operation, frequency can transiently reach the extremes of the 47–53 Hz ROCOF corridor.

The actual pi-section charging current at frequency f_{actual} is:

$$i_{C,\text{actual}}(t) = C_{\text{total}} \frac{dv_{\text{avg}}}{dt} = \frac{B_C}{\omega_0} \cdot 2\pi f_{\text{actual}} \cdot \text{Im}\{H[v_{\text{avg}}(t)]\} = B_C \cdot \frac{f_{\text{actual}}}{f_0} \cdot \text{Im}\{H[v_{\text{avg}}(t)]\} \quad (2)$$

Equation (1) omits the factor (f_{actual}/f_0) , leaving a residual charging error of:

$$\varepsilon_C = B_C \left| 1 - \frac{f_{\text{actual}}}{f_0} \right| V_{\text{avg,rms}} \quad (3)$$

For the study network ($B_C = 0.079$ pu, $V = 1$ pu) at $f = 47$ Hz:

$$\varepsilon_C(47 \text{ Hz}) = 0.079 \times 0.06 \times 1.0 = 0.0047 \text{ pu} \quad (4)$$

This error is well below the 87L threshold of 0.12 pu and therefore does *not* cause false trips in the present study network. However, for longer or higher-voltage lines with larger B_C , or for tighter threshold settings approaching the sensitivity floor, the residual can become significant. This report characterises the frequency dependence, demonstrates the frequency-adaptive correction, and establishes the safe operating envelope.

2 Frequency-Adaptive Correction Algorithm

2.1 Correction Formula

The TR-20 adaptive correction replaces the fixed B_C in (1) with a frequency-scaled version:

$$\hat{i}_{C,\text{adapt}}(t) = B_C \cdot \frac{\hat{f}}{f_0} \cdot \text{Im}\{H[v_{\text{avg}}(t)]\} \quad (5)$$

where $\hat{f}$ is the estimated actual frequency. The residual error after adaptive correction is:

$$\varepsilon_{C,\text{adapt}} = B_C \left| \frac{\hat{f}}{f_0} - \frac{f_{\text{actual}}}{f_0} \right| V_{\text{avg,rms}} = \frac{B_C}{f_0} \left| \hat{f} - f_{\text{actual}} \right| V_{\text{avg,rms}} \quad (6)$$

For a frequency estimator with accuracy $\delta f \leq 0.05$ Hz (achievable with a 2-cycle zero-crossing estimator; see Section 3):

$$\varepsilon_{C,\text{adapt}} \leq \frac{0.079}{50} \times 0.05 \times 1.0 = 7.9 \times 10^{-5} \text{ pu} \quad (7)$$

This is two orders of magnitude below the no-load noise floor of 0.003 pu reported in TR-15 and completely negligible.

2.2 Processing Pipeline

Figure 1 shows the TR-20 pipeline. The new frequency estimator block feeds the adaptive B_C scaling; all other stages are unchanged from TR-15/TR-17.




Figure 1: Frequency-adaptive 87L processing pipeline. The highlighted (green) block — the adaptive B_C scaler — is the only change from TR-15. Input: both-end voltage and current waveforms; output: trip / hold decision.

3 Frequency Estimator

3.1 Zero-Crossing Method

The estimator uses positive-going zero-crossings of phase A voltage (pre-fault window, 2 cycles). Sub-sample interpolation is applied at each crossing:

$$t_{\text{cross},k} = k + \frac{-v[k]}{v[k+1] - v[k]} \quad (\text{samples}) \quad (8)$$

The period is estimated as the median inter-crossing interval:

$$\hat{T} = \text{median} \{t_{\text{cross},k+1} - t_{\text{cross},k}\} \quad \hat{f} = 1/\hat{T} \quad (9)$$

Median is used in preference to mean to be robust against noise spikes or partial-cycle windows at the start of the waveform.

3.2 Accuracy and Fallback

Table 1 shows the estimator accuracy for the study network (4000 Sa/s, 4-cycle window, $V = 1$ pu balanced 3-phase).

Table 1: Zero-crossing frequency estimator performance ($f_s = 4000$ Sa/s, 4-cycle window). $\delta f = |\hat{f} - f_{\text{actual}}|$.

f_{actual} [Hz]	$\hat{f}$ [Hz]	δf [Hz]	$\varepsilon_{C,\text{adapt}}$ [pu]	Status
47	47.00	< 0.01	$< 1 \times 10^{-5}$	✓
48	48.00	< 0.01	$< 1 \times 10^{-5}$	✓
49	49.00	< 0.01	$< 1 \times 10^{-5}$	✓
50	50.00	< 0.01	$< 1 \times 10^{-5}$	✓
51	51.00	< 0.01	$< 1 \times 10^{-5}$	✓
52	52.00	< 0.01	$< 1 \times 10^{-5}$	✓
53	53.00	< 0.01	$< 1 \times 10^{-5}$	✓

If the estimator returns fewer than three zero-crossings (e.g., during a DC offset transient or very short pre-fault window), the algorithm falls back to $\hat{f} = f_0 = 50$ Hz, equivalent to the TR-15 fixed correction. The fallback frequency range is clamped to $[47, 53]$ Hz to prevent runaway corrections from corrupted measurements IEC [2019].

3.3 DFT Alternative

An alternative DFT-peak estimator with parabolic sub-bin interpolation is implemented in `line_freq_adaptive.py` for comparison. For the 4-cycle window at 4000 Sa/s the DFT gives $\delta f < 0.1$ Hz across the full 47–53 Hz range. The zero-crossing estimator is preferred in this implementation for its lower latency (≈ 0.5 cycle vs. 2 cycles for DFT accumulation) Schweitzer et al. [2010].

4 Study Results

4.1 Study A: No-Fault Residual Charging Error

Figure 2 and Table 2 show the residual charging error for fixed (TR-15) vs. adaptive (TR-20) correction across $f = 47$ –53 Hz.




Figure 2: Residual charging error ε_C vs. frequency, no-fault condition. Fixed correction (TR-15) reaches 0.0033 pu at $f = 47$ Hz. Adaptive correction (TR-20) is $< 10^{-5}$ pu at all frequencies.

Table 2: No-fault residual charging error and normalised α_{50} . $I_{\text{nom}} = 1.0$ pu; 87L threshold = 0.12 pu; TR-17 α_{50} target ≤ 0.030 .

f [Hz]	$\varepsilon_{C,\text{fixed}}$ [pu]	$\varepsilon_{C,\text{adapt}}$ [pu]	$\alpha_{50,\text{fix}}$	$\alpha_{50,\text{adp}}$	$\leq 0.030?$	Improv.
47	0.00331	$< 10^{-5}$	0.00331	$< 10^{-5}$	✓	$> 1000\times$
48	0.00221	$< 10^{-5}$	0.00221	$< 10^{-5}$	✓	$> 1000\times$
49	0.00111	$< 10^{-5}$	0.00111	$< 10^{-5}$	✓	$> 1000\times$
50	0.00000	0.00000	0.00000	0.00000	✓	—
51	0.00111	$< 10^{-5}$	0.00111	$< 10^{-5}$	✓	$> 1000\times$
52	0.00221	$< 10^{-5}$	0.00221	$< 10^{-5}$	✓	$> 1000\times$
53	0.00331	$< 10^{-5}$	0.00331	$< 10^{-5}$	✓	$> 1000\times$

Both methods satisfy $\alpha_{50} \leq 0.030$ for the study network ($B_C = 0.079$ pu). The adaptive method provides a margin that is $> 1000\times$ larger, enabling future tighter thresholds or larger B_C lines.

4.2 Study B: Internal Fault Detection

Table 3 shows the peak corrected differential for a 0.15 pu internal fault (above the 0.12 pu threshold) across all test frequencies.

Table 3: Internal fault (0.15 pu) peak corrected differential and trip decision. Threshold = 0.12 pu.

f [Hz]	Peak _{fixed} [pu]	Peak _{adapt} [pu]	Trip _{fixed}	Trip _{adapt}	Correct
47	0.152	0.150	✓	✓	✓
48	0.151	0.150	✓	✓	✓
49	0.150	0.150	✓	✓	✓
50	0.150	0.150	✓	✓	✓
51	0.150	0.150	✓	✓	✓
52	0.151	0.150	✓	✓	✓
53	0.151	0.150	✓	✓	✓

Both methods detect the fault at all frequencies. The slight elevation in Peak_{fixed} at 47/53 Hz occurs because the fixed-frequency residual (0.003 pu) adds in-phase with the fault current, marginally increasing the measured differential. This is a *conservative* effect (increases sensitivity) but confirms that the fixed correction does not cause missed trips for the study parameters.

4.3 Study C: Security (External Fault)

For an external fault (no true differential), the adaptive correction achieves zero residual at all frequencies, while the fixed correction leaves a 0.003–0.010 pu peak residual at the extremes of the frequency range. Both methods remain well below the 0.12 pu threshold, giving no false trips.

4.4 Selectivity Summary

21/21 scenarios correct (100%)

Three scenarios $\times$ seven frequencies = 21 total. Both fixed and adaptive methods achieve 21/21. The adaptive method additionally eliminates the residual error completely, extending safe operation to larger B_C values.

Figure 3 shows α_{50} vs. frequency for both methods.




Figure 3: Normalised false-trip metric α_{50} vs. frequency. Fixed correction (TR-15) shows a V-shaped error centred at 50 Hz; adaptive correction (TR-20) is flat at zero. Both are far below the TR-17 target of 0.030 for this study network.

5 Sensitivity to Line Parameters

5.1 Critical B_C at which Fixed Correction Causes False Trips

From Eq. (3), the fixed correction produces a false trip if:

$$\varepsilon_C = B_C \left| 1 - \frac{f}{f_0} \right| V_{\text{rms}} \geq I_{\text{threshold}} = 0.12 \text{ pu} \quad (10)$$

At $f = 47 \text{ Hz}$ (worst case, $|1 - 47/50| = 0.06$):

$$B_{C,\text{crit}} = \frac{0.12}{0.06 \times 1.0} = 2.0 \text{ pu} \quad (11)$$

The study network has $B_C = 0.079 \text{ pu}$, a factor of $25\times$ below the critical value. Lines up to $B_C \approx 2.0 \text{ pu}$ (corresponding to a $\approx 500 \text{ km}$, 400 kV EHV circuit) would remain safe even with the fixed correction. Nevertheless, the adaptive correction is recommended as a robust default because:

1. It has zero additional computation cost once the frequency estimate is available (single multiply).
2. It eliminates any frequency-dependent false-trip risk for all foreseeable line lengths.
3. It allows the 87L threshold to be reduced toward the noise floor (benefit from TR-15 and TR-17) without concern about off-nominal frequency operation.

5.2 ROCOF Transient Considerations

During a rate-of-change-of-frequency (ROCOF) event, f changes continuously. The zero-crossing estimator provides a new $\hat{f}$ every cycle. For a worst-case ROCOF of 2 Hz/s (IEC 60255-181 test criterion), the frequency changes by only $2 \times 0.02 = 0.04 \text{ Hz}$ per power cycle. The correction lag error is therefore:

$$\varepsilon_{C,\text{ROCOF}} \approx \frac{B_C}{f_0} \times 0.04 \times 1.0 = \frac{0.079}{50} \times 0.04 = 6.3 \times 10^{-5} \text{ pu} \quad (12)$$

Negligible.

6 Integration with SAMBP Suite

The TR-20 adaptive correction is implemented in `sambp_line_diff/adaptation/line_freq_adaptive.py` and integrates with the existing SAMBP stack as follows:

Table 4: TR-20 module interactions within the SAMBP 87L chain.

Module	Role	Interaction
<code>line_freq_adaptive</code> (TR-20, new)	Frequency estimation; adaptive B_C scaling	Replaces <code>compute_charge</code>
<code>line_pi_section_model</code> (TR-15)	Fixed pi-section correction (reference)	Retained for 50-Hz grids;
<code>line_adaptive_threshold</code> (TR-17)	$I_{\text{thresh}} = \max(I_{\text{base}}, k_s I_{\text{rest}})$	Unchanged; receives corre
<code>line_confidence_gate</code> (TR-12)	Magnitude override for HIF sensitivity	Unchanged

The frequency estimate $\hat{f}$ is computed once per protection cycle (20 ms window at 50 Hz) from the pre-fault voltage and cached for use by the adaptive correction. No changes to the LM estimator or trip logic are required [IEE \[2015\]](#).

7 Conclusions

1. **21/21 scenarios correct (100%)** across seven frequencies (47–53 Hz) and three scenario types (no-fault, internal fault, external fault), for both fixed and adaptive correction.
2. **Residual error is eliminated** by the adaptive correction: $\varepsilon_{C,\text{adapt}} < 10^{-5}$ pu vs. $\varepsilon_{C,\text{fixed}} = 0.0033$ pu at $f = 47$ Hz.
3. **The fixed correction (TR-15) is safe** for the study network ($B_C = 0.079$ pu) across the full 47–53 Hz range; the critical B_C for false trips is 2.0 pu at $f = 47$ Hz.
4. **Adaptive correction is recommended** as it costs one multiply per cycle, extends safety to all line lengths, and enables future threshold reductions without frequency sensitivity.
5. **Zero-crossing estimator accuracy:** $\delta f < 0.01$ Hz for a 4-cycle, 4000 Sa/s window — sufficient for 10^{-4} pu correction accuracy.
6. **ROCOF robustness:** worst-case 2 Hz/s ROCOF adds $< 10^{-4}$ pu additional error per cycle — negligible.

7.1 Future Work

1. **TR-21: DC-offset compensation** — inverter faults sometimes inject significant DC offsets into the differential waveform. Extend the LM estimator to include a DC term.
2. **TR-22: Negative-sequence 87L for asymmetric IBR faults** — inverter current-limiting reduces positive-sequence contribution during single-phase faults; validate that negative-sequence differential (87LN) maintains sensitivity.
3. **Hardware-in-the-loop at variable frequency:** sweep 47–53 Hz using a real-time digital simulator feeding a physical 87L IED to validate the frequency estimator latency.
4. **Unbalanced ROCOF:** validate estimator performance during asymmetric disturbances where phase-A, -B, -C frequencies diverge transiently.

References

- IEEE std c37.243-2015: Guide for application of digital line current differential relays using digital communication, 2015.
- IEC 60255-181:2019: Measuring relays and protection equipment — part 181: Functional requirements for frequency protection, 2019.
- PhD Candidate. SAMBP TR-15/2026: 87L pi-section charging-current correction. Technical report, PhD Thesis Supporting Report, 2026.
- ENTSO-E. Commission regulation (EU) 2016/631 of 14 april 2016 establishing a network code on requirements for grid connection of generators. Technical report, European Network of Transmission System Operators for Electricity, 2016.
- E. O. Schweitzer, D. A. Kiefer, and R. Yinger. Frequency measurement for power system management. *Proceedings of the 37th Annual Western Protective Relay Conference*, 2010.