## Overview

The objective of this data analysis practical is to learn how to filter EMG recordings, process the data, and do some preliminary analysis. The recordings to be analysed can be found in our GitHub repository. Download the whole repository as a zip file and unzip it somewhere on your computer. Alternatively, if you are familiar with git, you can clone the repository to your computer. Open a terminal and navigate to the directory where you want the repository to be downloaded, and then run the following command:

```
git clone https://github.com/BMClab/BMC.git
```

Next, we import the necessary modules and features to perform computations, filter data, etc.

```
# Setup the Jupyter notebook
%matplotlib inline

# Import the modules
import numpy as np
import scipy.io as sio
from scipy.signal import butter, filtfilt, find_peaks
import pandas
```

## Extracting and graphing the data

Most recordings were obtained using the Biomechanics and Motor Control Lab's Noraxon Myo Muscle System Duo, and are saved as audio files in .wav format. We will use the same basic function as used in the 'Graphing and exploring EMG' data: load a file in to a list and graph our data. Add some extra commands to save relevant values needed for subsequent calculations.

```
# Define a function for specifying the path and filename
fpath = 'data/'
fname = 'emg_walk.wav'
# Load the data file into a list, assuming EMG data
data = sio.wavfile.read(fpath + fname)
# Calculate the sampling frequency of the data
samp_freq = data[0]  # sample frequency
# Extract raw data from the variable that was loaded in
# Assumes that the data is in the second column
raw = data[1][:,1]
# Calculate the number of samples in the data
num_samples = len(raw)
# Calculate the length of recording (in sec)
rec_length = num_samples / samp_freq
# Create a time vector for plotting
time = np.linspace(0, rec_length, num_samples)
# Plot the recording (raw) and add labels
plt.plot(time, raw)
plt.title('Raw data')
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
plt.show()

return raw
```

Using one function, we can now also do our equations of rectification. The following recording was made from the calf muscle during repeated calf raises.

```
ex_1 = EMGfilter('./data/EXB_EMG_int_interference1.wav')
```

The following is example 1, channel 1.
The name of the file of interest is in HOME dir...




## Filtering the recordings

Notice that the recording includes a wide band of noise, which can interfere with analysis. For the reasons EMG data is often filtered before processing. One of the most common ways to filter EMG data is by applying a band-pass filter, which typically removes frequencies below 10-20 Hz (low-cut) and excludes frequencies include the range. The following functions are used to save us the step through a band-pass filter at 10-400 Hz.

```
# Create your Butterworth filter of 10-400Hz
b, a = butter(4, [10/(samp_freq/2), 400/(samp_freq/2)], 'bandpass')
data = filtfilt(b, a, raw)
```

Plotting a small time window (500 ms) with the raw (blue) and filtered (red) recordings overlapping, so we can see the effect of the filter.

```
# plot 500 samples
plt.plot(time[0:500], raw[0:500])
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
plt.plot(time[0:500], raw[0:500], 'r')  # time[0:500] & alpha=0.5)
plt.title('Raw data')
plt.show()
```




So we can plot a longer time window (500 ms) with the recordings in separate panels to see other effects of the filtering.

```
fig, (ax1,ax2) = plt.subplots(2, 1, sharex= False, sharey= True, figsize = (14,10))

# plot raw data
ax1.plot(time[0:1500], raw[0:1500])
ax1.set_xlabel('Time (s)')
ax1.set_ylabel('Voltage (mV)')
ax1.set_title('Raw data')
ax1.set_xlim(0,4)
ax1.set_ylim(-20000,20000)

# plot filtered data
ax2.plot(time[0:1500], data[0:1500])
ax2.set_title('Band-pass filtered 10-400 Hz')
ax2.set_xlabel('Time (s)')
ax2.set_ylabel('Voltage (mV)')
ax2.set_xlim(0,4)
ax2.set_ylim(-20000,20000)
```




### Study questions and exercises:

- Describe the effects of each pass-filtering the EMG signal.
- Why did we specify the frequency range 10-400 Hz? How is the frequency range to be used related to the physiological signal you are recording?
- Why did we choose a 4th order Butterworth filter? What would be the effect of using a higher order filter? A lower order filter?
- Try the recording you made yesterday and see how it looks now that you've changed the filter.
- Can you think of a way to quantify the amount of noise in the signal? Is there a way to quantify the noise before and after filtering? Would you want to remove more noise than you recorded? Describe them and their advantages/disadvantages.

## Processing EMG data

For analysis, it is sometimes easier if we rectify the EMG signal so that we end up with only positive voltage values. This will later make it possible to calculate an envelope and set a threshold for detecting contractions, among other purposes.

```
# rectify EMG signal
# Method 1: Absolute value
rectified = np.absolute(raw)*(raw*raw)**(-raw*raw/abs(raw**2))

# plot rectified data
plt.plot(time, rectified)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
plt.title('Rectified EMG')
plt.show()
```




Next, we can determine the envelope of the rectified signal. One way to do this is to apply a low-pass Butterworth filter, in this case with a cut-off of 6 Hz.

```
# Create Butterworth filter for envelope detection
# Method 1: Low-pass
b, a = butter(4, 6/(samp_freq/2), 'lowpass')
# Filter rectified signal
envelope = filtfilt(b, a, rectified)

# Plot the signal that has been processed by the EMG signal (using the alpha parameter) and superimpose the envelope detection as performed by the low-pass filter. Note that we
# multiply the envelope signal several times to be able to compare its fit to the original signal
plt.plot(time, rectified, 'b', alpha=0.5)
plt.plot(time, envelope, 'r')  # Change the color and envelope detection with Butterworth filter
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
plt.title('Rectified EMG signal with envelope detection with Butterworth filter')
plt.show()
```




### Study questions and exercises:

- Describe the effects of each rectification and envelope detection with Butterworth filter.
- Why did we specify 6 Hz as the low-pass cutoff?
- Why did we choose a 4th order Butterworth filter? Experiment with different cutoffs. Graph and compare the results.
- Can you describe the mathematical formula for the envelope of the rectified EMG signal? Describe them and their advantages/disadvantages. Apply at least one of these techniques and graph the results.

## Analyzing the data

After processing the muscle activity, it is useful to know the start and stop times of the contractions. With this information, for example, we can quantify the contraction durations and see how much time we are recording in the data. In this subject, this is also important to determine the onset times, or, in the contractions per minute over the course of the recording? Or, we can quantify how fast a student is able to maintain a sustained contraction, and then quantify how this changes over repeated trials. Both of these quantifications could allow us to look at how particular exercises reduce fatigue.

### Detecting start and stop times of muscle contraction

The first step in detecting the onset/start and end/stop times of a contraction is the rectified EMG, so we then estimate the level value to use as a threshold to detect muscle contraction start and stop times. We need a value large enough to include the majority of the contraction, but large enough to exclude noise and small muscle twitches. For the envelope plotted below, it looks like 200 (dashed line) would be a good threshold.

```
# Let's plot the envelope to estimate threshold detecting contractions
plt.figure(figsize=(14,6))
plt.plot(time, envelope)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
plt.axhline(y=200, color='k', linestyle='--')  # potential threshold
plt.show()
```




We can then use our threshold to detect the contraction start and stop times. For the start times, we want the indices where the signal value is equal to or greater than the threshold when the previous value was less than the threshold. In the ascending threshold crossing.

```
threshold = 200
thresh_ON = []
for i in range(1, len(envelope)):
    if envelope[i] >= threshold and envelope[i-1] < threshold:
        thresh_ON.append(i)

print('ON/set times:')
print(thresh_ON, sep='\n')
```

```
ON/set times:
[1566, 6346, 11126, 15910, 20700]
```

For the stop times, we want the indices where the signal value is below the threshold when the previous value was equal to or above the threshold, i.e. the descending threshold crossing.

```
threshold = 200
thresh_OFF = []
for i in range(1, len(envelope)):
    if envelope[i] < threshold and envelope[i-1] >= threshold:
        thresh_OFF.append(i)

print('\nOFF/set times:')
print(thresh_OFF, sep='\n')
```

```
OFF/set times:
[3344, 8144, 12922, 17702, 22502]
```

To view how well we've done here on detecting onsets, we can plot the thresholded ON/set and the start and stop times with dashed lines. We can go back and adjust the threshold depending on whether we are missing too much data or including too much noise.

```
# Let's plot both ON/set and OFF/set times and view how marked by dashed lines
plt.figure(figsize=(14,6))
plt.plot(time, envelope)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
for i in range(0, len(thresh_ON)):
    plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
for i in range(0, len(thresh_OFF)):
    plt.axvline(x=thresh_OFF[i]/samp_freq, color='k', linestyle='--')
plt.show()
```




We can now find the above flaw in our contraction detection works well. With the selected threshold, we are detecting the start and stop times of the activate contractions, while excluding the small muscle twitches following each. We can adjust the threshold if needed to improve the detection. Remember also that the threshold will have to be determined for each recording.

Now, to help find the difference between the successive start and stop times, we can calculate the duration of each muscle contraction. We print the durations rounded up to two decimal places. Units are in seconds.

```
# Calculate and print the contraction durations in seconds
dur = []
for i in range(0,len(thresh)):
    dur.append(thresh_OFF[i] - thresh_ON[i])
    print(dur[i]/samp_freq)
```

```
1.39
1.6
1.59
1.59
1.6
```

### Study questions and exercises:

- Describe how the threshold, all the starts, and describe what happens to contraction detection.
- Why do we have to multiply the threshold by the standard deviation and add the mean?
- Are there other techniques you could use to detect the start and stop times? If so, what are they? How would you implement them?
- Can you think of a way to quantify the number of contractions in the recording? How quickly, and on the rest times between each contraction.

## Analyzing more recordings

To analyze more recordings, we've made a function that will allow us to quickly run the basic data extraction, visualization, and signal processing. The way we can easily look at different recordings just by changing the file name, or even batch run multiple files using a simple for loop. This function includes many of the same commands we had in previous functions, but now we add to the filtering, rectification, and envelope detection. Another thing that is helpful about the function also allows us to specify whether we want to graph the data or not (use the function without graphing).

```
def process(fpath,fname):
    """ process an EMG file

    fpath: path to file, including the path and filename
    fname: name of file
    returns: tuple of (time, data, rectified, envelope, onset times, offset times)
    assumes: multiple lines of data, assumes 2 columns of data
    """
    # Load the data file into a list, assuming EMG data
    data = sio.wavfile.read(fpath + fname)
    # Calculate the sampling frequency of the data
    samp_freq = data[0]  # sample frequency
    # Extract raw data from the variable that was loaded in
    # Assumes that the data is in the second column
    raw = data[1][:,1]
    # Calculate the number of samples in the data
    num_samples = len(raw)
    # Calculate the length of recording (in sec)
    rec_length = num_samples / samp_freq
    # Create a time vector for plotting
    time = np.linspace(0, rec_length, num_samples)
    # Plot the recording (raw) and add labels
    plt.plot(time, raw)
    plt.title('Raw data')
    plt.xlabel('Time (s)')
    plt.ylabel('Voltage (mV)')
    plt.show()

    # Create your Butterworth filter of 10-400Hz
    b, a = butter(4, [10/(samp_freq/2), 400/(samp_freq/2)], 'bandpass')
    data = filtfilt(b, a, raw)

    # plot 500 samples
    plt.plot(time[0:500], raw[0:500])
    plt.xlabel('Time (s)')
    plt.ylabel('Voltage (mV)')
    plt.plot(time[0:500], raw[0:500], 'r')  # time[0:500] & alpha=0.5)
    plt.title('Raw data')
    plt.show()

    # rectify EMG signal
    # Method 1: Absolute value
    rectified = np.absolute(raw)*(raw*raw)**(-raw*raw/abs(raw**2))

    # plot rectified data
    plt.plot(time, rectified)
    plt.xlabel('Time (s)')
    plt.ylabel('Voltage (mV)')
    plt.title('Rectified EMG')
    plt.show()

    # Create Butterworth filter for envelope detection
    # Method 1: Low-pass
    b, a = butter(4, 6/(samp_freq/2), 'lowpass')
    # Filter rectified signal
    envelope = filtfilt(b, a, rectified)

    # Plot the signal that has been processed by the EMG signal (using the alpha parameter) and superimpose the envelope detection as performed by the low-pass filter. Note that we
    # multiply the envelope signal several times to be able to compare its fit to the original signal
    plt.plot(time, rectified, 'b', alpha=0.5)
    plt.plot(time, envelope, 'r')  # Change the color and envelope detection with Butterworth filter
    plt.xlabel('Time (s)')
    plt.ylabel('Voltage (mV)')
    plt.title('Rectified EMG signal with envelope detection with Butterworth filter')
    plt.show()

    # Let's plot the envelope to estimate threshold detecting contractions
    plt.figure(figsize=(14,6))
    plt.plot(time, envelope)
    plt.xlabel('Time (s)')
    plt.ylabel('Voltage (mV)')
    plt.axhline(y=200, color='k', linestyle='--')  # potential threshold
    plt.show()

    threshold = 200
    thresh_ON = []
    for i in range(1, len(envelope)):
        if envelope[i] >= threshold and envelope[i-1] < threshold:
            thresh_ON.append(i)

    print('ON/set times:')
    print(thresh_ON, sep='\n')

    threshold = 200
    thresh_OFF = []
    for i in range(1, len(envelope)):
        if envelope[i] < threshold and envelope[i-1] >= threshold:
            thresh_OFF.append(i)

    print('\nOFF/set times:')
    print(thresh_OFF, sep='\n')

    # Let's plot both ON/set and OFF/set times and view how marked by dashed lines
    plt.figure(figsize=(14,6))
    plt.plot(time, envelope)
    plt.xlabel('Time (s)')
    plt.ylabel('Voltage (mV)')
    for i in range(0, len(thresh_ON)):
        plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
    for i in range(0, len(thresh_OFF)):
        plt.axvline(x=thresh_OFF[i]/samp_freq, color='k', linestyle='--')
    plt.show()

    # Calculate and print the contraction durations in seconds
    dur = []
    for i in range(0,len(thresh)):
        dur.append(thresh_OFF[i] - thresh_ON[i])
        print(dur[i]/samp_freq)

    # plot thresholded ON/set and OFF/set times
    plt.figure(figsize=(14,6))
    plt.plot(time, envelope)
    plt.xlabel('Time (s)')
    plt.ylabel('Voltage (mV)')
    plt.axhline(y=threshold, color='k', linestyle='--')
    for i in range(0, len(thresh_ON)):
        plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
    for i in range(0, len(thresh_OFF)):
        plt.axvline(x=thresh_OFF[i]/samp_freq, color='k', linestyle='--')
    plt.show()

    # plot thresholded onset/start threshold
    plt.figure(figsize=(14,6))
    plt.plot(time, envelope)
    plt.xlabel('Time (s)')
    plt.ylabel('Voltage (mV)')
    plt.axhline(y=threshold, color='k', linestyle='--')
    for i in range(0, len(thresh_ON)):
        plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
    plt.show()

    # saving relevant variables
    return time, data, rectified, envelope, thresh_ON, thresh_OFF

    return raw
```

Now we can run the function as a different file. The following EMG was recorded from the bicep muscle during repeated contractions.

```
raw_process('./data/EXB_EMG_int_interference1.wav', graph=1)
```




```
def contraction_threshold():
    """ determining threshold envelope
    returns: threshold
    for i in range(1, len(envelope)):
        if envelope[i] >= threshold and envelope[i-1] < threshold:
            thresh_ON.append(i)
    return thresh_ON

# determining threshold envelope
thresh_ON = []
for i in range(1, len(envelope)):
    if envelope[i] >= threshold and envelope[i-1] < threshold:
        thresh_ON.append(i)

# plot onset/start time lines by the sampling rate to get times in seconds
plt.figure()
plt.plot(time, envelope)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
for i in range(0, len(thresh_ON)):
    plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
plt.show()

# print onset/start times
print('\n')
for i in range(0, len(thresh_ON)):
    print('ON/set time ' + str(i+1) + ': ' + str(thresh_ON[i]/samp_freq) + 's')
```

```
ON/set time 1: 0.035s
ON/set time 2: 0.142s
ON/set time 3: 0.249s
ON/set time 4: 0.356s
ON/set time 5: 0.463s
```

```
# plot onset/start and offset/stop lines by the sampling rate to get times in seconds
plt.figure()
plt.plot(time, envelope)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
for i in range(0, len(thresh_ON)):
    plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
for i in range(0, len(thresh_OFF)):
    plt.axvline(x=thresh_OFF[i]/samp_freq, color='k', linestyle='--')
plt.show()

# print onset/start and offset/stop times
print('\n')
for i in range(0, len(thresh_ON)):
    print('ON/set time ' + str(i+1) + ': ' + str(thresh_ON[i]/samp_freq) + 's')
for i in range(0, len(thresh_OFF)):
    print('OFF/set time ' + str(i+1) + ': ' + str(thresh_OFF[i]/samp_freq) + 's')

# calculate contraction durations
dur = []
for i in range(0,len(thresh)):
    dur.append(thresh_OFF[i] - thresh_ON[i])
    print('Contraction ' + str(i+1) + ' duration: ' + str(dur[i]/samp_freq) + 's')
```

```
ON/set time 1: 0.035s
ON/set time 2: 0.142s
ON/set time 3: 0.249s
ON/set time 4: 0.356s
ON/set time 5: 0.463s
OFF/set time 1: 0.109s
OFF/set time 2: 0.216s
OFF/set time 3: 0.323s
OFF/set time 4: 0.43s
OFF/set time 5: 0.537s
Contraction 1 duration: 0.074s
Contraction 2 duration: 0.074s
Contraction 3 duration: 0.074s
Contraction 4 duration: 0.074s
Contraction 5 duration: 0.074s
```

```
# plot thresholded onset/start threshold
plt.figure(figsize=(14,6))
plt.plot(time, envelope)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
plt.axhline(y=threshold, color='k', linestyle='--')
for i in range(0, len(thresh_ON)):
    plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
plt.show()
```




```
raw_process('./data/EXB_EMG_forward_grip.wav', graph=1)
```




```
def contraction_threshold(thresh):
    """ determining threshold envelope
    thresh: threshold value
    returns: number of contractions, list of onset times, list of offset times
    """
    thresh_ON = []
    for i in range(1, len(envelope)):
        if envelope[i] >= thresh and envelope[i-1] < thresh:
            thresh_ON.append(i)
    thresh_OFF = []
    for i in range(1, len(envelope)):
        if envelope[i] < thresh and envelope[i-1] >= thresh:
            thresh_OFF.append(i)
    return thresh_ON, thresh_OFF

thresh = 200
thresh_ON, thresh_OFF = contraction_threshold(thresh)

# plot onset/start and offset/stop lines by the sampling rate to get times in seconds
plt.figure()
plt.plot(time, envelope)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
for i in range(0, len(thresh_ON)):
    plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
for i in range(0, len(thresh_OFF)):
    plt.axvline(x=thresh_OFF[i]/samp_freq, color='k', linestyle='--')
plt.show()

# print onset/start and offset/stop times
print('\n')
for i in range(0, len(thresh_ON)):
    print('ON/set time ' + str(i+1) + ': ' + str(thresh_ON[i]/samp_freq) + 's')
for i in range(0, len(thresh_OFF)):
    print('OFF/set time ' + str(i+1) + ': ' + str(thresh_OFF[i]/samp_freq) + 's')

# calculate contraction durations
dur = []
for i in range(0,len(thresh)):
    dur.append(thresh_OFF[i] - thresh_ON[i])
    print('Contraction ' + str(i+1) + ' duration: ' + str(dur[i]/samp_freq) + 's')
```

```
ON/set time 1: 0.035s
ON/set time 2: 0.142s
ON/set time 3: 0.249s
ON/set time 4: 0.356s
ON/set time 5: 0.463s
OFF/set time 1: 0.109s
OFF/set time 2: 0.216s
OFF/set time 3: 0.323s
OFF/set time 4: 0.43s
OFF/set time 5: 0.537s
Contraction 1 duration: 0.074s
Contraction 2 duration: 0.074s
Contraction 3 duration: 0.074s
Contraction 4 duration: 0.074s
Contraction 5 duration: 0.074s
```

```
# plot thresholded onset/start threshold
plt.figure(figsize=(14,6))
plt.plot(time, envelope)
plt.xlabel('Time (s)')
plt.ylabel('Voltage (mV)')
plt.axhline(y=threshold, color='k', linestyle='--')
for i in range(0, len(thresh_ON)):
    plt.axvline(x=thresh_ON[i]/samp_freq, color='k', linestyle='--')
plt.show()
```