WooCommerce Email Checklist

A customer pays. No confirmation email.

WooCommerce emails not sending: what to check, in order. The first three checks need no code.

Faisal Alvi · Senior WooCommerce Engineer

Check 1

Did the order reach the right status?

An order on Pending payment has not triggered the Processing email. If orders stay pending after payment, the gateway confirmation is failing. Order notes show timestamps.

Check 2

Is that email enabled?

Open WooCommerce > Settings > Emails. A disabled email fails silently, with no error. Plugins can also switch it off with a filter, even when the box is ticked.

Check 3

Is there a valid recipient?

Customer emails go to the billing email. WooCommerce drops any address that fails is_email(). If none remain, nothing is sent. Check for typos and bad separators.

Check 4

Look at the sender address.

An empty or invalid From address falls back to wordpress@ plus your domain, which some hosts block. Use a real mailbox on your own domain.

Check 5

Read the real error from wp_mail.

Log the wp_mail_failed error with a temporary mu-plugin on staging. One logged error beats guessing. No error does not guarantee delivery.

Check 6

Sent, but never received?

Set the SPF and DKIM records your provider gives you, then add DMARC. Test several inbox providers and check spam before assuming loss.

Rule

Get one error, then change one thing.

Run the plugin conflict test on staging. Do not stack two SMTP plugins. Black Friday is about four weeks out: test every payment method now.

Full guide

Faisal Alvi

Senior WooCommerce Engineer

Full guide, step by step

https://faisalalvi.com/blog/woocommerce-emails-not-sending/

faisalalvi.com