

軟體測試與資安檢測

教師：王凡

授課時間：每週三 9：10—12：00

博理館 113

課程代號：EE 5170

識別碼：921 U9550

民國 110 年春季班

QUIZ (2021/3/17)

Open-book, open-internet, no discussion

Name: _____ Department : _____ Student ID: _____

1. Please draw the control-flow graph (CFG) of the following program code.

```
x = y
while x < 100:
    if x < y:
        x += 1
    if x > 5:
        y += 1
    else:
        y += 2
print (x, y)
```

2. Please write down a set of test paths for 100% node coverage and explain its correctness.

3. Please write down a set of test paths for 100% edge-pair coverage and explain its correctness.

4. Please write down a set of test paths for 100% prime path coverage and explain its correctness.