

# Tune Up

Specific Operating Power Range:

GSM850 Band:

Power Class 1;

Power Control Level 5 +33dBm +0.3dB/-0.3dB

Power Control Level 6 +31dBm +2.0dB/-2.0dB

Power Control Level 7 +29dBm +2.0dB/-2.0dB

Power Control Level 8 +27dBm +2.0dB/-2.0dB

Power Control Level 9 +25dBm +2.0dB/-2.0dB

Power Control Level 10 +23dBm +2.0dB/-2.0dB

Power Control Level 11 +21dBm +2.0dB/-2.0dB

Power Control Level 12 +19dBm +2.0dB/-2.0dB

Power Control Level 13 +17dBm +2.0dB/-2.0dB

Power Control Level 14 +15dBm +2.0dB/-2.0dB

Power Control Level 15 +13dBm +2.0dB/-2.0dB

Power Control Level 16 +11dBm +2.0dB/-2.0dB

Power Control Level 17 +9dBm +2.0dB/-2.0dB

Power Control Level 18 +7dBm +2.0dB/-2.0dB

Power Control Level 19 +5dBm +2.0dB/-2.0dB

GSM1900 Band:

Power Class 1;

Power Control Level 0 +30dBm +2.0dB/-2.0dB

Power Control Level 1 +28dBm +3.0dB/-3.0dB

Power Control Level 2 +26dBm +3.0dB/-3.0dB

Power Control Level 3 +24dBm +3.0dB/-3.0dB

Power Control Level 4 +22dBm +3.0dB/-3.0dB

Power Control Level 5 +20dBm +3.0dB/-3.0dB

Power Control Level 6 +18dBm +3.0dB/-3.0dB

Power Control Level 7 +16dBm +3.0dB/-3.0dB

Power Control Level 8 +14dBm +3.0dB/-3.0dB

Power Control Level 9 +12dBm +4.0dB/-4.0dB

Power Control Level 10 +10dBm +4.0dB/-4.0dB

Power Control Level 11 +8dBm +4.0dB/-4.0dB

Power Control Level 12 +6dBm +4.0dB/-4.0dB

Power Control Level 13 +4dBm +4.0dB/-4.0dB

Power Control Level 14 +2dBm +5.0dB/-5.0dB

Power Control Level 15 +0dBm +5.0dB/-5.0dB

Note; Effective radiation efficiency is -3.7dB




Figure 1

### 1 Adjustment of RF Output Power:

(1) The equipment setup as shown in Figure 1.

(2) Operation of PC adjusts equipment.

(3) Use RF Engineering Tools at PC side.

Select GSM850 Band:

- 1) Set GSM850 Band.
- 2) Set ARFCN: 190
- 3) TX ON.
- 4) Adjust the power to 32.4dBm (+1.0dB/-1.0dB, Power control level: PCL=5) by PA DAC value.
- 5) Repeat 4) for 15 times, and adjust the power level to 30.5, 28.8, 27, 25, 23, 21, 19, 17, 15, 13, 11, 9, 7, 5.
- 6) Make 16 Ramp-Up/Ramp-Down data from the adjustment value of (5) and (6).

7) Data of 5) and 6) is written to flash memory.

Select PCS1900 Band:

- 1) Set PCS Band.
- 2) Set ARFCN: 661.
- 3) TX ON.
- 4) Adjust the power to 29.0 dBm (+2.0dB/-2.0dB, Power control level: PCL=0) by PA DAC value.
- 5) Repeat 4) for 15 times, and adjust the power level to 27.5, 26, 24, 22, 20, 18, 16, 14, 12, 10, 8, 6, 4, 2, 0.
- 6) Make 16 Ramp-Up/Ramp-Down data from the adjustment value of (5) and (6).
- 7) Data of 5) and 6) is written to flash memory.

## **2 Adjustment of oscillation frequency of VCXO:**

(1) The equipment setup as shown in Figure 1.

(2) Use Crystal AFC Control Tools to Set CapID and AFC DAC value.

(3) Set Band=GSM850, Set ARFCN=190, Set PCL=12.

- 1) Set AFC DAC=4096, fixed. (Check that  $V_{afc}=1.4V$ ).
- 2) Set CapID=0, and verify that frequency error  $>>10KHz$ .
- 3) Set CapID=63, and verify that frequency error  $<<-10KHz$ .
- 4) If the above 3 items are verified, then change CapID value to make frequency error be closed to 0 Hz as possible, record this CapID value.
- 5) Set CapID value got from step 4), then change AFC DAC value to make frequency error be closed to 0 Hz as possible, record this AFC DAC value.
- 6) Download the CapID value and AFC DAC value to flash memory.

## **3 Adjustment of RX Sensitivity:**

(1) Select GSM850 Band:

- 1) Set BCCH level: -85dBm; ARFCN: 128.
- 2) Test sample make a call to connect RF Tester..
- 3) Set TCH level: -106dBm.
- 4) Measure BER II error at TCH ARFCN: 128, 190, 251.
- 5) Tune up the RX matching circuit to make sure  $BER II < 2\%$  at each ARFCN.

(2) Select PCS Band:

- 1) Set BCCH level:-85dBm;ARFCN:512.
- 2) Test sample make a call to connect RF Tester..
- 3) Set TCH level:-106dBm.
- 4) Measure BER II error at TCH ARFCN:512, 661, 810.
- 5) Tune up the RX matching circuit to make sure BER II < 2% at each ARFCN.