


Q7, Q8 : cascode circuit  
 Q9, Q11 : current mirror circuit  
 R23, R17, C2 : DC servo  
 Q12 : temperature compensation

Do not power on the board without opamp.



0.25, 0.50W resistor : Vishay CCF07 or MRS25

Q1, Q13 : IRF610

Q2, Q10 : KSA992

Q4, Q14 : IRF9610

Q3, Q7 : KSC1845

Q5 : FQP3P20

Q6 : FQP3N30

Q8 : ZVN4206AV or 2N7000 (not TA)

Q12 : BD139

Q9, Q11 : ZVP2106A or BS250P (Diodes Inc)

Q15, Q17 : FQA46N15

Q16, Q18 : FQA36P15

U1 : OPA1641

C0 : CDE 1uF 100v 930C1W1K-F

1W resistor : Vishay PR01

C15, C16 : Vishay 256 PMG-SI

C18, C19 : Wima MKS4C043303G

100nF : Wima MKS2

D1, D4 : LED RED 2V

D2, D3 : 1N5248B

D5, D6 : 1N5245

C4, C5 : 100nF COG KEMET C322C104K3G5TA

D7 : Onsemi 1N5819RLG

C3, C6 : ELNA Silmic II RFS 100uF 16V

C3, C5, C13, C14, C21, C23, C26, C28 : Panasonic FC

R26, R27, R28 : try to use non inductive 1W resistor (Vishay Dale or Ohmite).

R36, R37, R38, R39 : Noble RGC5 or KOA BPR58 0.1R 5W (white sugar)

C7 : use MKP capacitor (MKP1F041005100JYSD or MKP4D041005D00JSSD).

C17 : use MKP capacitor (MKP1F031004B00K100 or FKP3C031004C00JSSD).

C2 : use 100uF/16V BP Michicon Muse

C1, C10 : use Mica CDE CD15 or Polystyrene capacitor.

J2 and J3: FASTON 250 PCB connector (TE Connectivity 63849-1)

To try: New D7 and R23 = 8K6

C21, C23, C26, C28 with Silmic II 47uF/63v  
 New R40 and R41

For 0.750v input sensibility R17 = 3K3.

Exicon laterals : R11 and R12 = 10R 2W

Q17 a QUAD405 audiophile approach

Modified by Stef for the Q17-P2 project  
 by eng. Tiberiu Nicol

Sheet: /  
 File: Q17-P2.kicad\_sch

**Title: Q17-P2 Amplifier**

Size: A4 Date: 2022-01-01

KiCad E.D.A. kicad (6.99.0)

Rev: 1.1.7

Id: 1/1