HOORVIA - AWG TO MM WIRE GAUGE CHART: PRINTABLE CONVERSION

Quick Reference Cheat Sheet · US Letter Printable

Crafting & DIY · Sheet #1

AWG	Diameter (mm)	Cross-section (mm²)	Ampacity (60°C)	Common Use
18 AWG	1.02	0.82	7 A (low voltage)	Doorbell, thermostat wire
16 AWG	1.29	1.31	10 A (low voltage)	Speakers, landscape lighting
14 AWG	1.63	2.08	15 A	Lighting, bedroom circuits
12 AWG	2.05	3.31	20 A	Kitchen, bathroom, laundry
10 AWG	2.59	5.26	30 A	Dryers, water heaters
8 AWG	3.26	8.37	40 A	Ranges, subpanels
6 AWG	4.12	13.30	55 A	EV chargers, subpanel feeders
4 AWG	5.19	21.15	70 A	100A subpanel feeders
2 AWG	6.54	33.62	95 A	Main service entrance
1 AWG	7.35	42.41	110 A	Large subpanels, service
1/0 AWG	8.25	53.49	125 A	Service entrance
2/0 AWG	9.27	67.43	145 A	200A service entrance

PRO TIP: Bigger AWG number means thinner wire: AWG is backwards: 18 AWG is thin, 2 AWG is thick. When in doubt, check the diameter in millimeters - it never lies.