AI UNLEASHES CHAOS

Lorenz attractor -- circuit by Paul Horowitz

PCB by Jason Gallicchio and Claude Opus 5 Max 2026-09-15 rev A



x and z on a scope in X–Y draw this

$$\frac{dx}{dt} = s\,(y - x)$$

$$\frac{dy}{dt} = r\,x - y - x\,z$$

$$\frac{dz}{dt} = x\,y - b\,z$$

s = 10 r = 28 b = 8/3

Every term weighs 1 MEG / R: R1 = R2 = 100k is s, R3 = 35.7k is r, R7 = 374k is b. The MPY634s form A*B/10 and take their minus signs from swapped inputs. 0.1 V per unit; time scale tau = 1 MEG x C.

this project, and how it was made

Paul's original circuit seti.harvard.edu

Sheet: File: lorenz.kicad_pcb		
Title:		
Size: A4	Date:	**Rev:**
KiCad E.D.A. 10.0.6		Id: 1/1