

```
// L298N motor driver
const int ENA = 5;
const int IN1 = 7;
const int IN2 = 8;

void setup() {
  pinMode(ENA, OUTPUT);
  pinMode(IN1, OUTPUT);
  pinMode(IN2, OUTPUT);
}

void loop() {
  // Forward
  digitalWrite(IN1, HIGH);
  digitalWrite(IN2, LOW);
  analogWrite(ENA, 200);
  delay(3000);

  // Stop
  analogWrite(ENA, 0);
  delay(1000);

  // Reverse
  digitalWrite(IN1, LOW);
  digitalWrite(IN2, HIGH);
  analogWrite(ENA, 200);
  delay(3000);

  // Stop
  analogWrite(ENA, 0);
  delay(1000);
}
```

### PCB connections

- Arduino **D5** → **ENA**
- Arduino **D7** → **IN1**
- Arduino **D8** → **IN2**