

Uno R4 Minima → DFRobot DFR0669 3.5" TFT wiring

DFRobot DFR0669 (ILI9488, 480x320, 3.3-5.5 V) · GT911 capacitive touch over I2C

AA-30.ZERO: UART1 TX → R4 D0 (Serial1 RX) · UART1 RX → R4 D1 (Serial1 TX) · GND common.

Module runs at 3.3-5.5 V, so SPI logic needs NO level shifter (earlier 2.4" ILI9341 + LEVEL-8P + HU1-HU8 are removed). Backlight (BL) is on by default.

Display uses SPI D8-D13; touch uses I2C A4/A5; AA-30 uses D0/D1 — no overlap. Touch INT and SDCS are not used.

DFR0669 pins: VCC GND SCLK MOSI MISO CS RES DC BL · touch: SCL SDA INT · SD: SDCS. MISO may be left unconnected.

