

User Guide for `circuitmacro.sty`

Luca Giaccone

August 12, 2025

Contents

1	Introduction	2
2	Commands list	2
3	Commands Overview and Examples	3
3.1	Resistor: <code>\R</code>	3
3.2	Inductor: <code>\L</code>	3
3.3	Capacitor: <code>\C</code>	4
3.4	Generic bipole (e.g. impedance): <code>\B</code>	4
3.5	Switch open: <code>\SwOpen</code>	4
3.6	Switch closed: <code>\SwClosed</code>	5
3.7	Short circuit (e.g. connection): <code>\Short</code>	5
3.8	Open circuit: <code>\Open</code>	6
3.9	Independent voltage source: <code>\Vs</code>	6
3.10	Independent current source: <code>\Is</code>	7
3.11	Controlled voltage source: <code>\cVs</code>	7
3.12	Controlled current source: <code>\cIs</code>	7
3.13	Voltage: <code>\V</code>	8
3.14	Current: <code>\I</code>	8
3.15	Nodes: <code>\Nodes</code>	9
3.16	Terminal: <code>\Terminal</code>	10
3.17	Label: <code>\Label</code>	10
3.18	Power load (single phase or three phase): <code>\PLoad</code>	10
3.19	Star connected load: <code>\YLoad</code>	11
3.20	Triangle connected load: <code>\DLoad</code>	11
3.21	Three phase line: <code>\triLine</code>	12
3.22	Three phase connection: <code>\triShort</code>	12
3.23	Three phase generator: <code>\triGen</code>	13
4	Example Circuits	15
4.1	Example 1: first order circuit	15
4.2	Example 2: AC Circuit	16
4.3	Example 3: Three-Phase Circuit	17

1 Introduction

This document provides a complete user guide for the `circuitmacro.sty` package, authored by Luca Giaccone. The package extends `circuitikz` by introducing macros that simplify the drawing of common DC, AC, and three-phase circuit components.

The only external dependencies are:

- `circuitikz`
- `xstring`

Put the file either in project directory or in the `TEXHOME` tree. These are the correct path for different operating systems:

macOS:	/Users/<username>/Library/texmf/tex/latex/circuitmacro/
Linux:	/home/<username>/texmf/tex/latex/circuitmacro/

2 Commands list

<code>\R* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\L* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\C* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\B* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\SwOpen* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\SwClosed* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\Short [<circuitikz options>]{<start coords>}{<end coords>}</code>
<code>\Open [<circuitikz options>]{<start coords>}{<end coords>}</code>
<code>\Vs* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\Is* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\cVs* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\cIs* [<circuitikz options>]{<start coords>}{<end coords>}{<label>}</code>
<code>\V*{<start coords>}{<end coords>}{<label>}</code>
<code>\I*{<start coords>}{<end coords>}{<label>}</code>
<code>\Nodes*{<coords>} ...</code>
<code>\Terminal{<start coords>}{<end coords>}{<label>}</code>
<code>\Label[<tikz node options>]{<coords>}{<text>}</code>
<code>\PLoad[<top label>][<bottom label>]{<width>}{<height>}{<center coords>}</code>
<code>\YLoad* [<length scale>] [<component type>]{<coord1>}{<coord2>}{<offset>} ...</code> <code>{<label phase 1>}{<label phase 2>}{<label phase 2>}</code>
<code>\DLoad* [<length scale>] [<component type>]{<coord1>}{<coord2>}{<offset>} ...</code> <code>{<label branch 1>}{<label branch 2>}{<label branch 3>}</code>
<code>\triGen* [<length scale>] [V I]{<coord1>}{<coord2>}{<offset>} ...</code> <code>{<label phase A>}{<label phase B>}{<label phase C>}</code>
<code>\triLine* [<length scale>] [<component type>]{<coord1>}{<coord2>}{<offset>} ...</code> <code>{<label phase A>}{<label phase B>}{<label phase C>}</code>
<code>\triShort* [<circuitikz options>][<gap>]{<coord1>}{<coord2>}{<offset>}</code>

Notes on the optionals (based on your definitions):

- Starred forms (`\Cmd*`) flip label/side.
- `<length scale>` defaults to 1 where present.
- `<component type>` defaults to *B* (generic) where present.
- `\triGen` source type defaults to *V* (voltage); *I* selects current sources.

3 Commands Overview and Examples


3.1 Resistor: `\R`

Signature:

`\R[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```
\begin{circuitikz}
  \R{0,0}{0,3}{R_1}
  \R*{3,0}{3,3}{R_2}
  \R[i=$I_3$]{4,0}{7,3}{R_3}
  \R[v=$V_4$, i^<=$I_4$, *-*]{7,0}{10,3}{R_4}
\end{circuitikz}
```




3.2 Inductor: `\L`

Signature:

`\L[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```
\begin{circuitikz}
  \L{0,0}{0,3}{L_1}
  \L*{3,0}{3,3}{L_2}
  \L[i=$I_3$]{4,0}{7,3}{L_3}
  \L[v=$V_4$, i^<=$I_4$, *-*]{7,0}{10,3}{L_4}
\end{circuitikz}
```




3.3 Capacitor: `\C`

Signature:

`\C[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```
\begin{circuitikz}
  \C{0,0}{0,3}{C_1}
  \C*{3,0}{3,3}{C_2}
  \C[i=$I_3$]{4,0}{7,3}{C_3}
  \C[v=$V_4$, i^<=$I_4$, *-*]{7,0}{10,3}{C_4}
\end{circuitikz}
```




3.4 Generic bipole (e.g. impedance): `\B`

Signature:

`\B[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```
\begin{circuitikz}
  \B{0,0}{0,3}{\bar{Z}_1}
  \B*{3,0}{3,3}{\bar{Z}_2}
  \B[i=$I_3$]{4,0}{7,3}{\bar{Z}_3}
  \B[v=$V_4$, i^<=$I_4$, *-*]{7,0}{10,3}{\bar{Z}_4}
\end{circuitikz}
```



3.5 Switch open: `\SwOpen`

Signature:


`\SwOpen[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```

\begin{circuitikz}
  \SwOpen{0,0}{0,3}{t=0}
  \SwOpen*{3,0}{3,3}{t=0}
  \SwOpen{4,0}{7,3}{t=0}
  \SwOpen[v=$v_s(t)$, *-]{7,0}{10,3}{t=0}
\end{circuitikz}

```



3.6 Switch closed: `\SwClosed`

Signature:


```
\SwClosed[<circuitikz options>]{<start>}{<end>}{<label>}
```

Example:

```

\begin{circuitikz}
  \SwClosed{0,0}{0,3}{t=0}
  \SwClosed*{3,0}{3,3}{t=0}
  \SwClosed{4,0}{7,3}{t=0}
  \SwClosed[v=$v_s(t)$, *-]{7,0}{10,3}{t=0}
\end{circuitikz}

```



3.7 Short circuit (e.g. connection): `\Short`

Signature:


```
\Short[<circuitikz options>]{<start>}{<end>}
```

Example:

```

\begin{circuitikz}[scale=1]
  \Short{0,0}{0,3}
  \Short[i<=$I_{cc2}$, *-]{2.5,0}{2.5,3}
  \Short[i_=$I_{cc3}$, o-o]{4,0}{7,3}
  \Short[i_<=$I_{cc4}$]{7,0}{10,3}
\end{circuitikz}

```




3.8 Open circuit: `\Open`

Signature:

`\Open[<circuitikz options>]{<start>}{<end>}`

Example:

```
\begin{circuitikz}[scale=1]
  \Open[v=$V_{oc1}$, *-]{0,0}{0,3}
  \Open[v_=$V_{oc2}$, o-o]{2.5,0}{2.5,3}
  \Open[v<=$V_{oc3}$, *-]{4,0}{7,3}
  \Open[v_<=$V_{oc4}$, o-o]{7,0}{10,3}
\end{circuitikz}
```




3.9 Independent voltage source: `\Vs`

Signature:

`\Vs[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```
\begin{circuitikz}
  \Vs[i=$I_1$]{0,3}{0,0}{E_1}
  \Vs*{3,3}{3,0}{E_2}
  \Vs{4,0}{7,3}{}
  \Vs*[i=$I_4$, *-]{7,0}{10,3}{E_4}
\end{circuitikz}
```




3.10 Independent current source: `\Is`

Signature:

`\Is[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```
\begin{circuitikz}
  \Is[v>=$V_1$]{0,0}{0,3}{A_1}
  \Is*{3,0}{3,3}{A_2}
  \Is{7,3}{4,0}{A_3}
  \Is*[v>=$V_4$, *-*]{10,3}{7,0}{A_4}
\end{circuitikz}
```




3.11 Controlled voltage source: `\cVs`

Signature:

`\cVs[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```
\begin{circuitikz}
  \cVs[i=$I_1$]{0,3}{0,0}{E_1}
  \cVs*{3,3}{3,0}{E_2}
  \cVs{4,0}{7,3}{}
  \cVs*[i=$I_4$, *-*]{7,0}{10,3}{E_4}
\end{circuitikz}
```



3.12 Controlled current source: `\cIs`

Signature:


`\cIs[<circuitikz options>]{<start>}{<end>}{<label>}`

Example:

```

\begin{circuitikz}
  \cIs[v>=$V_1$]{0,0}{0,3}{A_1}
  \cIs*{3,0}{3,3}{A_2}
  \cIs{7,3}{4,0}{A_3}
  \cIs*[v^>=$V_4$, *-*]{10,3}{7,0}{A_4}
\end{circuitikz}

```



3.13 Voltage: `\V`

Signature:


`\V{<start>}{<end>}{<label>}`

Example:

```

\begin{circuitikz}[scale=1]
  \V{0,0}{0,3}{V_1}
  \V*{3,0}{3,3}{V_2}
  \V{4,0}{7,3}{V_3}
  \V{10,3}{7,0}{V_4}
\end{circuitikz}

```



3.14 Current: `\I`

Signature:


`\I{<start>}{<end>}{<label>}`

Example:

```

\begin{circuitikz}
  \I{0,0}{0,1}{I_1}
  \I*{2,0}{2,1}{I_2}
  \I{4,0}{5,1}{I_3}
  \I{8,1}{7,0}{I_4}
\end{circuitikz}

```

3.15 Nodes: `\Nodes`

Signature:

`\Nodes{coordinates1}{coordinates1} ... {coordinatesn}`

Example:

```
\begin{circuitikz}
  \Nodes{0,0}{1,1}
  \Nodes*{4,0}{5,0}{5,1}{4,1}
\end{circuitikz}
```




3.16 Terminal: `\Terminal`

`\Terminal{from}{to}{label}`

Example:

```
\begin{circuitikz}
  % some resistors
  \R[*-]{1,1}{1,3}{R_1}
  \R{1,3}{3,3}{R_2}
  \R[*-]{3,3}{3,1}{R_3}
  \R{1,1}{3,1}{R_4}

  % terminals
  \Terminal{0,0}{1,1}{A}
  \Terminal{0,4}{1,3}{B}
  \Terminal{4,4}{3,3}{C}
  \Terminal{4,0}{3,1}{D}
\end{circuitikz}
```



3.17 Label: `\Label`

I'm above the node
I'm below the node


$B \bullet D$

3.18 Power load (single phase or three phase): `\PLoad`

`\PLoad[labe1][label2]{dx}{dy}{origin}`

Example:

```
\begin{circuitikz}
  \PLoad[P][Q]{2}{4}{0,0}
  \PLoad[Q_c][Q]{3}{1}{7,0}
\end{circuitikz}
```




3.19 Star connected load: `\YLoad`

Signature:

`\YLoad[scale] [B|R|L|C] {start}{end}{gap}{label1}{label2}{label3}`

Example:

```
\begin{circuitikz}
  \YLoad{0,0}{3,0}{2}{\bar{Z}}{}{}
  \YLoad[0.8] [R] {7,-1}{8.5,1}{1.5}{R_1}{R_2}{R_3}
  \YLoad*[0.5] [C] {13,0}{11,0}{1}{C}{}{}
\end{circuitikz}
```




3.20 Triangle connected load: `\DLoad`

Signature:

`\DLoad[scale] [B|R|L|C] {start}{end}{gap}{label1}{label2}{label3}`

Example:

```
\begin{circuitikz}
  \DLoad{0,0}{3,0}{2}{\bar{Z}_1}{\bar{Z}_2}{\bar{Z}_3}
  \DLoad[0.5] {7,0}{10,0}{2}{\bar{Z}_1}{\bar{Z}_2}{\bar{Z}_3}
  \DLoad[0.5] [R] {5,-4}{6,-3}{1}{R}{}{}
\end{circuitikz}
```




3.21 Three phase line: `\triLine`

Signature:

`\triLine[scale] [B|R|L|C]{start}{end}{gap}{label1}{label2}{label3}`

Example:

```
\begin{circuitikz}
  \triLine{0,0}{3,0}{2}{\bar{Z}}{}{}
  \triLine[0.8][R]{7,-1}{8.5,1}{1.5}{R_1}{R_2}{R_3}
  \triLine*[0.5][C]{13,0}{11,0}{1}{C}{}{}
\end{circuitikz}
```



3.22 Three phase connection: `\triShort`

Signature:


`\triShort[<circuitikz options>] [<cut>]{start}{end}{gap}`

Example:

```

\begin{circuitikz}
  \triShort{0,0}{3,0}{2}
  \triShort*[*-][1]{7,2}{7,-3}{1}
  \triShort*[*-][1]{12,2}{12,-2}{1}
\end{circuitikz}

```



3.23 Three phase generator: `\triGen`

Signature:

```

\triGen[V|I][scale]{start}{end}{gap}{label1}{label2}{label3}

```


(N.B. `scale` does not work perfectly here. It is included for future development and it is suggested to leave it to the default value (i.e. 1). In this version labels, plus sign for voltage generators and arrows for current generators do not scale according to `scale` parameters.)

Example:

```

\begin{circuitikz}
  \triGen{0,0}{3,0}{2}{\bar{E}_1}{\bar{E}_2}{\bar{E}_3}
  \triGen*{8,-2}{11,1}{2}{\bar{E}_1}{\bar{E}_2}{\bar{E}_3}
  \triGen[1][I]{5,-3}{5,-6}{2}{\bar{A}_1}{\bar{A}_2}{\bar{A}_3}
\end{circuitikz}


```



4 Example Circuits


4.1 Example 1: first order circuit

```
\begin{circuitikz}
  \Vs{0,3}{0,0}{E_1}
  \R{0,3}{3,3}{R_1}
  \R{0,0}{3,0}{R_2}
  \Is[*-]{3,0}{3,3}{A_1}
  \R[-*]{3,3}{6,0}{R_3}
  \R[-*]{3,3}{6,3}{R_4}
  \SwOpen{6,3}{9,3}{t=0}
  \C[v<=$v(t)$]{9,3}{9,0}{C_1}
  \Short{3,0}{9,0}
  \Short{6,0}{6,3}
\end{circuitikz}
```



4.2 Example 2: AC Circuit

```
\begin{circuitikz}
  \Vs{0,6}{0,0}{\bar{E}_1}
  \Is[*-]{3,3}{6,3}{\bar{A}_1}
  \B[*-, v<=\bar{V}_1]{3,6}{3,3}{\bar{Z}_1}
  \B[-*, i=\bar{I}_2]{3,3}{3,0}{\bar{Z}_2}
  \B[i^<=\bar{I}_3]{6,6}{6,3}{\bar{Z}_3}
  \B[v<=\bar{V}_4]{6,3}{6,0}{\bar{Z}_4}
  \Short{0,0}{6,0}
  \Short{0,6}{6,6}
\end{circuitikz}
```



4.3 Example 3: Three-Phase Circuit

```
\begin{circuitikz}
% generator and line
\triGen{0,4}{2,4}{1.8}{\bar{E}_1}{\bar{E}_2}{\bar{E}_3}
\triLine{2,4}{4.5,4}{1.8}{\bar{Z}_L}{}{}

% load A
\triShort{4.5, 4}{9, 4}{1.8}
\PLoad[P_A][Q_A]{2}{4.5}{9,4}

% load B
\triShort[*-]{1.8}{6.5, 5.8}{6.5, 1}{1.8}
\PLoad[P_B][Q_B]{4.5}{2}{6.5,1}

% current and voltages
\I{8,5.8}{8.5,5.8}{\bar{I}_A}
\I{4.7,3.5}{4.7,3}{\bar{I}_B}
\V*{2,4}{2,5.8}{\bar{V}_g}
\V{8.5,4}{8.5,5.8}{\bar{V}}
\end{circuitikz}
```

