

EMERGENCY RESPONSE GUIDE

Blue Bird Vision Electric Bus 2026 to Present



BLUE BIRD®

SHUTDOWN PROCEDURE

1. Chock wheels, then apply the parking brake.
2. Shutdown procedure Methods in preferred order:

METHOD A: Ignition key is accessible

- Turn OFF ignition and remove key.
- Turn OFF 12 Volt battery disconnect switch in battery box.

METHOD B: Ignition key not accessible

- Turn OFF 12 Volt battery disconnect switch in battery box.
- OR
- Turn OFF the 12 Volt battery using the remote disconnect switch.

IF VEHICLE IS SUBMERGED:

There is NOT a risk of electric shock from contacting the vehicle's body or frame in or out of the water. Perform the system shutdown procedure and continue with standard first responder procedures.


VEHICLE FIRE:

IMPORTANT NOTE: Use copious amounts of water to control a lithium battery fire. Perform the system shutdown procedure and continue with standard first responder procedures.

12 Volt Battery Disconnect Switch

The 12 Volt disconnect switch is mounted on the rear wall of the 12 Volt battery compartment which is located on the driver's side of the bus below the driver's window.

Rotate knob to the LOCK OFF position. Center of knob should pop up when 12V is disconnected.



- OR -

Remote Disconnect Switch

A lighted Remote Disconnect Switch may be mounted on the rear side of the air compressor box or on the frame rail under the skirt behind the rear axle on the curbside of the bus.

If ON side is lit, slide cover up to expose the OFF side of switch and push to turn off 12V disconnect.

