Z80 is the sole SRAM address/write master. Pico injects instructions with SRAM reads inhibited. RESET_N directly joins Pico and Z80 at 3.3V.

J2: 3.3V signals only.
Pin 1 / GP8 reserved for SRAM bank select.
GP22/GP26 available for software/PIO I2C.

BANK SELECT: Pico physical pin 11 / GP8 -> U4.17.
R24: 10k from Pico pin 11 to GND (3.3V side).
U4.3 -> U2.2 / A16 (5V side); LOW selects bank 0.
Remove the former U4.17 and U2.2 ground straps.

A2: external Stage 10 0.91in SSD1315 128x32 status OLED, no PCB footprint.
Module 38.00 x 12.00 mm; 4-pin 2.54 mm header.
Header order GND, VCC, SCK, SDA: not VCC first.
SDA = J2.2 / GP22; SCK (I2C SCL) = J2.3 / GP26.
VCC = J2.4 / 3V3; GND = J2.5 / GND.
I2C pull-ups to 3.3V only, never 5V.
DMA-fed PIO I2C on core 1; address 0x3C.
Shows IP, port 8088, uptime, heartbeat.

-ups. R17–R20: 3V3 pull-ups. R21–R23: GPIO pull-downs. Both data paths default disabled; no PLD/programmer required.

Native KiCad 10 schematic generated from the verified README pin map
Z80ROMlessSBC
Sheet: /
File: z80_romless_sbc.kicad_sch
Title: Z80ROMlessSBC — Exact Breadboard Electrical Schematic
Size: A0
Date: 2026-10-26
Rev: 2
KiCad E.D.A. 10.0.7
Id: 1/1