Raspberry Pi Pico

+3.3V
R1 220
3V1 green
GND

R10 220k
+BATT
GND
+3.3V
J1
5V
NT5 NetTie_2
NT6 NetTie_2
NT7 NetTie_2
NT8 NetTie_2

P1
rpi pico 1
2648-SC0915CT-ND
tht

1.8-5.5v
5V
D1 D_Schottky
+3.3V
VBUS
VSYS
3V3_OUT
ADC_VREF
3V3_EN
RUN
GP0
GP1
GP2
GP3
GP4
GP5
GP6
GP7
GP8
GP9
GP10
GP11
GP12
GP13
GP14
GP15
GP16
GP17
GP18
GP19
GP20
GP21
GP22
GP26
GP27
GP28
AGND
GND
GND_1
GND_2
GND_3
GND_4
GND_5
GND_6
bt1
bt2
bt3
bt4
sda
scl
R2 220
D13 blue
GND
right_2
right_1
right_en
left_2
left_en
left_1
+3.3V
J3 joystick
GND
+3.3V
J4 speed knob
GND
GND

left motor

U1
DRV8245HQPWPRQ
LVL6, in independent mode that means faults are retried
SR
DIAG
PH/IN2
EN/IN1
DRVOFF
VM
OUT1
OUT2
GND
EPAD
ITRIP
MODE
NFAULT
IPROPI
NSLEEP
left_2
left_1
+BATT
GND
C1 0.1uF
8.2k +-10% LVL2 INDEPENDENT
8.2k R7
GND
left_ipropi
left_en
+BATT
HSL1 Heatsink
J100 0197054001
J101 0197054001
optionally replace J7 to be weelye compatible
ML+
ML-
J7 1017491
GND

U2
DRV8245HQPWPRQ
right_1
right_2
+BATT
GND
C2 0.1uF
8.2k +-10% LVL2 INDEPENDENT
8.2k R6
GND
right_ipropi
right_en
+BATT
HSR1 Heatsink
MR-
MR+
J8 1017491
optionally replace J8 to make the PCB weelye compatible
wellye style J104
wellye RX25 style J105
GND

ADC (for measuring battery voltage and motor current)

+3.3V NT1
NetTie_3
GND
TP0 TestPoint
U4
TLA2024IRUGR
+3.3V
VDD
ADDR
SCL
SDA
AIN0
AIN1
AIN2
AIN3
NC
GND
scl
sda
right_ipropi
left_ipropi
C4 0.1uF
GND
+BATT
R13 100k
R14 13.7k
GND
TP1 TestPoint
left_ipropi
TP2 TestPoint
right_ipropi
R11 604
R12 604
GND
GND
+3.3V
R20 EXB34V182JV
pullup resistors
1.8k
sda
scl

qwiic I2C plug
GND
+3.3V
sda
scl
J2 Conn_01x04
MP

weelye compatible header
J11
+BATT
switch
D2 D_Schottky
+BATT
bat-
GND
Conn_01x10_Pin

3.5mm audio jacks for if you want to connect buttons as an alternative to the joystick
B1 ASJ-200-B-HT
B2 ASJ-200-B-HT
B3 ASJ-200-B-HT
B4 ASJ-200-B-HT
bt1
bt2
bt3
bt4
GND

alternative voltage regulator
Instead of the voltage regulator circuit, you could get a single THT module that outputs 5V.
Make sure the pinout matches.
Make sure the min and max input voltage are compatible with your battery.
U5
D78B05T, RBT05W24S05, pololu5593
+BATT
IN
GND
OUT
5V
GND

voltage regulator circuit https://webench.ti.com/appinfo/webench/scripts/SDP.cgi?ID=F7F7D983B50C08E2
+BATT
R5 100k
U3
TPS54202HDDCR
EN
FB
VIN
BOOT
SW
GND
C6 0.1uF
L1 12uH
C7 56pF
R8 100k
R9 13.7k
C8 47uF
5V
C3 10uF
GND

battery power circuit
J102 0197054001
optionally replace J5 to be weelye compatible
J103 0197054001
J5 TB005-762-02BE
bat-
R3 8.2k
18V zener D3
SW1 screw terminal
C5 33uf
GND
R4 100k
switch
+BATT
J6
PSMN1R2-25YLDX NMOS Q1 reverse polarity protection
PSMN1R2-25YLDX Q2 on/off switch
GND

3mm diameter bolt holes
3.35in x 2.2in
85.09mm x 55.88mm
H1 M3
H2 M3
H3 M3
H4 M3

https://github.com/gobabygocarswithjoysticks gobabygocarswithjoysticks@gmail.com
Sheet: /
File: gbg-pcb.kicad_sch
Title:
Size: A3 | Date: | Rev:
KiCad E.D.A. 10.0.1 | Id: 1/1