Below is the pin description of the G4801S magnetic module (2×1000BASE-T). Each port consists of 4 differential pairs with transformer center taps on PHY and line sides.

1 — P1_CT1 — center tap transformer pair 1 port 1
2 — P1_DI1+ — differential input positive pair 1 port 1
3 — P1_DI1- — differential input negative pair 1 port 1

4 — P1_CT2 — center tap transformer pair 2 port 1
5 — P1_DI2+ — differential input positive pair 2 port 1
6 — P1_DI2- — differential input negative pair 2 port 1

7 — P1_CT3 — center tap transformer pair 3 port 1
8 — P1_DI3+ — differential input positive pair 3 port 1
9 — P1_DI3- — differential input negative pair 3 port 1

10 — P1_CT4 — center tap transformer pair 4 port 1
11 — P1_DI4+ — differential input positive pair 4 port 1
12 — P1_DI4- — differential input negative pair 4 port 1

13 — P2_CT1 — center tap transformer pair 1 port 2
14 — P2_DI1+ — differential input positive pair 1 port 2
15 — P2_DI1- — differential input negative pair 1 port 2

16 — P2_CT2 — center tap transformer pair 2 port 2
17 — P2_DI2+ — differential input positive pair 2 port 2
18 — P2_DI2- — differential input negative pair 2 port 2

19 — P2_CT3 — center tap transformer pair 3 port 2
20 — P2_DI3+ — differential input positive pair 3 port 2
21 — P2_DI3- — differential input negative pair 3 port 2

22 — P2_CT4 — center tap transformer pair 4 port 2
23 — P2_DI4+ — differential input positive pair 4 port 2
24 — P2_DI4- — differential input negative pair 4 port 2

25 — P1_CT4_L — center tap line pair 4 port 1
26 — P1_DO4+ — differential output positive pair 4 port 1
27 — P1_DO4- — differential output negative pair 4 port 1

28 — P1_CT3_L — center tap line pair 3 port 1
29 — P1_DO3+ — differential output positive pair 3 port 1
30 — P1_DO3- — differential output negative pair 3 port 1

31 — P1_CT2_L — center tap line pair 2 port 1
32 — P1_DO2+ — differential output positive pair 2 port 1
33 — P1_DO2- — differential output negative pair 2 port 1

34 — P1_CT1_L — center tap line pair 1 port 1
35 — P1_DO1+ — differential output positive pair 1 port 1
36 — P1_DO1- — differential output negative pair 1 port 1

37 — P2_CT4_L — center tap line pair 4 port 2
38 — P2_DO4+ — differential output positive pair 4 port 2

39 — P2_DO4- — differential output negative pair 4 port 2

40 — P2_CT3_L — center tap line pair 3 port 2
41 — P2_DO3+ — differential output positive pair 3 port 2
42 — P2_DO3- — differential output negative pair 3 port 2

43 — P2_CT2_L — center tap line pair 2 port 2
44 — P2_DO2+ — differential output positive pair 2 port 2
45 — P2_DO2- — differential output negative pair 2 port 2

46 — P2_CT1_L — center tap line pair 1 port 2
47 — P2_DO1+ — differential output positive pair 1 port 2
48 — P2_DO1- — differential output negative pair 1 port 2