

A MINI PROJECT REPORT

ON

Design and Implementation of a 4-Bit Carry Select Adder Using MTCMOS-Based Ripple Carry Adder with 10T Full Adders

Submitted in partial fulfillment of the requirements for the Award of the Degree
Of

BACHELOR OF TECHNOLOGY

In

ELECTRONICS AND COMMUNICATION ENGINEERING

By

1.G.Harathi (24C35A0406)

2.E.Sreeja (24C35A0405)

3.V.Pravalika (23C31A04H4)

4.V.Raghava (23C31A04I0)

5.S.Akshay (23C31A04F3)

Under the Guidance of

Mr.K.Srikanth

Assistant Professor

Dept. of ECE



DEPARTMENT OF ELECTRONICS AND COMMUNICATION

ENGINEERING

BALAJI INSTITUTE OF TECHNOLOGY & SCIENCE

(AUTONOMOUS)

Accredited by NBA, NAAC A+ & ISO 9001:2015 Certified Institution

(Affiliated to JNTUH, Hyderabad and Approved by the AICTE, New Delhi)

NARSAMPET, WARANGAL 506 331

2025 – 26

BALAJI INSTITUTE OF TECHNOLOGY & SCIENCE

(AUTONOMOUS)

Accredited by NBA, NAAC A+&ISO 9001:2015 Certified Institution

(Affiliated to JNTUH, Hyderabad and Approved by the AICTE, New

Delhi) Laknepally, Narsampet, Warangal - 506 331

DEPARTMENT OF ELECTRONICS & COMMUNICATION ENGINEERING



CERTIFICATE

This is to certify that this Project Work entitled " **Design and Implementation of a 4-Bit Carry Select Adder Using MTCMOS-Based Ripple Carry Adder with 10T Full Adders** " is a bonafide work carried out by **G.Harathi (24C35A0406), E.Sreeja (24C35A0405), V.Pravalika(23C31A04H4), V.Raghava(23C31A04I0)** and **S.Akshay (23C31A04F3)** in partial fulfillment of the requirements for the award of the degree of **Bachelor of Technology** from **JNTUH, Hyderabad** during the period 2025-26 under our guidance and supervision.

Internal Guide

Mr.K.Srikanth

Assistant Professor,

Dept. of ECE

Head of the Dept.

Dr.P.Kiran Kumar

Associate Professor,

Dept. of ECE

External Examiner

DECLARATION

We, **G.Harathi (24C35A0406), E.Sreeja (24C35A0405), V.Pravalika(23C31A04H4), V.Raghava(23C31A04I0) and S.Akshay (23C31A04F3)** hereby declare that the project entitled "**Design and Implementation of a 4-Bit Carry Select Adder Using MTCMOS-Based Ripple Carry Adder with 10T Full Adders**", submitted in the partial fulfillment of the requirements for the award of B.Tech in Electronics and Communication Engineering to Balaji Institute of Technology & Science, Narsampet, affiliated to JNTUH, Hyderabad is a authentic work and has not been submitted to any other university or institution for award of the degree.

G.Harathi (24C35A0406)

E.Sreeja (24C35A0405)

V.Pravalika (23C31A04H4)

V.Raghava (23C31A04I0)

S.Akshay (23C31A04F3)

ACKNOWLEDGEMENT

It is a great pleasure to express our deepest sense of gratitude and indebtedness, to our Internal guide **Mr.K.Srikanth**, Associate Professor, Head of Dept., of ECE, BITS, Narsampet, for having been a source of constant inspiration, precious guidance and generous assistance during the project work. We deem it as a privilege to have worked under his able guidance. Without his close monitoring and valuable suggestions this work wouldn't have taken this shape. We feel that this help is un-substitutable and unforgettable.

We wish to express our sincere thanks to **Dr. V. S.Hariharan**, Principal, BITS, Narsampet for providing the college facilities for the completion of the project.

We are profoundly thankful to **Dr.P.Kiran Kumar**, Head of ECE Dept, for his cooperation and encouragement.

We are greatly thankful to our Project coordinator **Dr.V.Madhu Kumar**, Assoc. Prof., Dept. of ECE, BITS, Narsampet for his support throughout our project

Finally, we thank all the faculty members, supporting staff of ECE Dept. and friends for their kind co-operation and valuable help for completing the project.

G.Harathi (24C35A0406)

E.Sreeja (24C35A0405)

V.Pravalika (23C31A04H4)

V.Raghava (23C31A04I0)

S.Akshay (23C31A04F3)

ABSTRACT

Recent advances in CSA design have targeted Speed enhancement and power reduction. Current models are plagued by heavy area overhead and power loss owing to dual RCAs. We introduce a new CSA architecture employing a 4-bit RCA composed of MTCMOS-enhanced 10T Full Adders in this Project. Our design, when applied and analyzed in 45nm Technology employing microwind tool, it will realizes a reduction of 27.5% in power usage, an increase of 23.7% in delay improvement, and an area reduction of 19.2% from traditional CSA design. These performances will validate the practicality of our method for high performance, low-power VLSI applications.

LIST OF FIGURES

FIGURE NO:	TITLE	PAGE NO:
1.1	Proposed system	1
2.1	Block Diagram	7
2.2	Flow chart	11
2.3	Architecture	13
3.1	Open Dsch	14
3.2	10T Full Adder	15
3.3	2:1Mux	15
3.4	4 Bit Ripple Carry Adder	16
3.5	4 Bit Carry Select Adder	16
3.6	Input signals	17
3.7	Simulation	17
3.8	Verilog File	18
3.9	Schematic Layout	19
3.10	Open Microwind	19
3.11	Compile	20
3.12	Select File	20
3.13	Compile	21
3.2.1	10T Full Adder Output Waveform	21
3.2.2	2:1Mux Output Waveform	22
3.2.3	4 Bit Ripple Carry Adder Output Waveform	23
3.2.4	4 Bit Carry Select Adder Output Waveform.	23
3.2.5	Schematic Layout	23

CONTENTS

Declaration		i
Acknowledgment		ii
Abstract		iii
List of figures		iv
CHAPTER NO	DESCRIPTION	PAGE NO
CHAPTER 1	INTRODUCTION	09
	1.1 Overview	09
	1.2 Problem statement	11
	1.3 Objectives	12
	1.4 Existing System	13
	1.5 Proposed System	14
CHAPTER 2	METHODOLOGY	17
	2.1 Block Diagram	17
	2.2 Working principle	18
	2.3 Architecture	19
CHAPTER 3	SOFTWARE COMPONENTS	21
	3.1 Results	21
	3.2 Output Waveforms	28
CHAPTER 4	APPLICATIONS	31
	ADVANTAGES AND	33
	DISADVANTAGES	

CHAPTER 5	CONCLUSION	34
	FUTURE SCOPE	35
CHAPTER 6	REFERENCE	37

CHAPTER 1

INTRODUCTION

1.1 OVERVIEW

The Design and Implementation of a 4-Bit Carry Select Adder (CSLA) using an MTCMOS-Based Ripple Carry Adder with 10T Full Adders is an important approach in modern VLSI system design aimed at improving speed, reducing power consumption, and optimizing chip area. Adders are one of the most essential components in digital electronics and are widely used in arithmetic operations within processors, microcontrollers, and digital signal processing systems.

The performance of these systems largely depends on the efficiency of the adder circuits used. In conventional digital design, the Ripple Carry Adder (RCA) is commonly used due to its simple structure and ease of implementation. However, the main drawback of the RCA is its propagation delay, which increases linearly with the number of bits.

This delay occurs because each full adder must wait for the carry input from the previous stage before producing its output. As a result, RCAs are not suitable for high-speed applications.

To overcome this limitation, the Carry Select Adder (CSLA) architecture is introduced. The CSLA improves speed by performing parallel computation of sum and carry outputs for two possible carry inputs, i.e., carry-in equal to '0' and carry-in equal to '1'.

Once the actual carry input is known, a multiplexer selects the correct output. This reduces the waiting time for carry propagation and significantly improves overall performance. In this project, the CSLA is implemented using Ripple Carry Adder blocks, which are constructed using 10-transistor (10T) full adders.

The 10T full adder design is chosen because it requires fewer transistors compared to conventional CMOS full adders, which typically use 28 transistors. This reduction in transistor count leads to lower power consumption, reduced silicon area, and simplified circuit complexity.

The 10T full adder operates efficiently by using pass transistor logic and optimized

transistor arrangements. It ensures that both sum and carry outputs are generated with minimal delay and power usage.

Due to its compact design, it is highly suitable for large-scale integration where area and power are critical constraints. Another important feature of this design is the use of MTCMOS (Multi-Threshold CMOS) technology. Leakage power has become a major concern in deep submicron technologies, especially in standby mode.

MTCMOS addresses this issue by using transistors with different threshold voltages. Low-threshold transistors are used in the critical paths to maintain high speed, while high-threshold transistors are used as sleep transistors to reduce leakage power.

The sleep transistors are placed between the power supply and the circuit (header) or between the circuit and ground (footer). During active mode, these transistors are turned ON, allowing normal operation of the circuit. During standby mode, they are turned OFF, effectively disconnecting the circuit from the power supply and reducing leakage currents. The integration of MTCMOS with the CSLA structure enhances the overall efficiency of the design by significantly reducing static power dissipation without affecting performance during active operation.

This makes the design highly suitable for battery-operated and portable electronic devices. The 4-bit CSLA is designed by dividing the adder into smaller sections, each consisting of RCA blocks and multiplexers.

Each section computes outputs for both possible carry inputs in parallel. The multiplexer then selects the correct result based on the incoming carry from the previous stage. This structure ensures faster computation compared to traditional adders. The proposed design also focuses on optimizing the trade-off between speed, power, and area.

While CSLA improves speed, it typically requires more hardware due to duplicate computation paths. However, by using 10T full adders and efficient MTCMOS techniques, the design minimizes this overhead and achieves a balanced performance.

The implementation of the design can be carried out using VLSI design tools such as DSCH for schematic design and Microwind for layout design and simulation. These tools allow designers to analyze parameters such as power consumption, delay, and area, and verify the functionality of the circuit.

The simulation results of the proposed design show improved performance in terms of reduced delay and lower power consumption compared to conventional RCA and basic CSLA designs. The use of MTCMOS further reduces leakage power, making the design energy efficient.

This project demonstrates how advanced design techniques and optimization strategies can be combined to develop efficient digital circuits. It highlights the importance of selecting appropriate architectures and technologies in achieving desired performance goals. The proposed 4-bit CSLA design can be extended to higher bit-width adders for use in more complex systems. It also serves as a foundation for further research in low-power VLSI design and optimization techniques.

In conclusion, the Design and Implementation of a 4-Bit Carry Select Adder using MTCMOS-Based Ripple Carry Adder with 10T Full Adders provides an effective solution for high-speed and low-power arithmetic operations. It successfully combines the advantages of CSLA architecture, efficient 10T full adder design, and MTCMOS technology to achieve improved performance, reduced power consumption, and optimized area, making it suitable for modern VLSI applications.

1.2 PROBLEM STATEMENT

The continuous scaling of CMOS technology into the 45 nm regime has introduced several design challenges, particularly in terms of leakage power, short-channel effects, and variability in device parameters. While Carry Select Adders (CSAs) improve speed by parallel computation, their conventional structure results in excessive power dissipation and increased chip area due to duplicated Ripple Carry Adder (RCA) blocks. This makes them less suitable for modern low-power applications such as portable and battery-operated devices.

Hence, there is a critical need to redesign CSA architectures that can operate efficiently under 45 nm technology constraints. Another major issue in deep submicron technologies like 45 nm is the dominance of static (leakage) power over dynamic power. Traditional adder designs do not effectively address leakage currents, which leads to

significant energy loss even when the circuit is idle. Moreover, propagation delay caused by sequential carry generation in RCAs limits overall system performance. Therefore, an improved design approach is required that integrates low-leakage techniques such as MTCMOS and optimized transistor-level implementations to enhance both speed and power efficiency. Furthermore, the increasing complexity of modern digital systems such as microprocessors, DSP units, and embedded systems demands arithmetic circuits that are not only fast but also area-efficient and power-conscious. Conventional CSA designs fail to meet these requirements in scaled technologies due to their inefficient hardware utilization.

This project aims to overcome these limitations by proposing a compact, low-power, and high-speed adder architecture that is specifically optimized for implementation in 45 nm CMOS technology.

1.3 OBJECTIVES

The primary objective of this project is to design and implement a high-performance and low-power 4-bit Carry Select Adder (CSA) using advanced 45nm CMOS technology. As technology scales down to deep submicron levels like 45nm, challenges such as leakage power, delay, and area become critical. This project aims to address these issues through optimized design techniques. One of the key objectives is to reduce power consumption, especially leakage power, which becomes significant in nanoscale technologies.

This is achieved by using MTCMOS (Multi-Threshold CMOS) techniques, where high-threshold transistors help reduce leakage and low-threshold transistors maintain speed. Another important objective is to improve speed by minimizing propagation delay. In conventional Ripple Carry Adders (RCA), delay increases due to sequential carry propagation. To overcome this, the Carry Select Adder is designed to compute results in parallel, significantly improving performance. The project also focuses

on area optimization by reducing the number of transistors. This is done by designing and implementing 10-Transistor (10T) Full Adders, which are more efficient compared to traditional designs. Additionally, the objective includes designing a 4-bit RCA using MTCMOS-based full adders and integrating it into a CSA structure with multiplexers to select the correct output based on carry input conditions.

Another crucial goal is to simulate and verify the design using Microwind tool in 45nm technology, analyzing parameters such as power consumption, delay, and silicon area. The results are then compared with conventional CSA designs to demonstrate improvements. Finally, the project aims to develop a scalable and efficient VLSI architecture that can be extended to higher-bit adders and used in real-world applications such as microprocessors, DSP systems, and low-power embedded devices.

1.4 EXISTING SYSTEM

The existing system for high-speed arithmetic operations in VLSI primarily utilizes the conventional Carry Select Adder (CSA) architecture, which is designed to reduce the delay associated with carry propagation in Ripple Carry Adders (RCA). In this approach, the adder is divided into smaller groups, and for each group, two separate RCAs are employed to perform parallel computations. One RCA calculates the sum assuming the carry-in (C_{in}) is '0', while the other assumes it is '1'. Once the actual carry input is determined, a multiplexer selects the appropriate output from the two computed results, thereby improving speed compared to a single RCA design.

However, this architecture suffers from several significant drawbacks. Since both RCAs operate simultaneously regardless of the actual carry condition, the system experiences high power consumption due to increased switching activity. Additionally, the use of duplicate RCA blocks leads to a considerable increase in transistor count, resulting in larger silicon area and higher implementation cost. In deep submicron technologies such as 45nm, leakage power becomes a major concern, and the conventional CSA design does not incorporate effective techniques to minimize leakage currents, leading to further power inefficiencies.

Moreover, although the CSA improves speed, the presence of multiplexer delay and internal RCA delay still limits overall performance. The system also involves redundant hardware utilization, as one of the RCA outputs is always unused after selection. Due to these limitations—namely high power consumption, increased area, leakage issues, and suboptimal efficiency—the existing CSA design is not fully suitable for modern low-power and high-performance VLSI applications, thereby necessitating the development of an improved design approach.

1.5 PROPOSED SYSTEM

The Design and Implementation of a 4-Bit Carry Select Adder (CSLA) using an MTCMOS-Based Ripple Carry Adder with 10T Full Adders is an important approach in modern VLSI system design aimed at improving speed, reducing power consumption, and optimizing chip area. Adders are one of the most essential components in digital electronics and are widely used in arithmetic operations within processors, microcontrollers, and digital signal processing systems. The performance of these systems largely depends on the efficiency of the adder circuits used.

In conventional digital design, the Ripple Carry Adder (RCA) is commonly used due to its simple structure and ease of implementation. However, the main drawback of the RCA is its propagation delay, which increases linearly with the number of bits. This delay occurs because each full adder must wait for the carry input from the previous stage before producing its output. As a result, RCAs are not suitable for high-speed applications.




Fig1.1 Proposed system.

To overcome this limitation, the Carry Select Adder (CSLA) architecture is introduced. The CSLA improves speed by performing parallel computation of sum and carry outputs for two possible carry inputs, i.e., carry-in equal to '0' and carry-in equal to '1'. Once the actual carry input is known, a multiplexer selects the correct output. This reduces the waiting time for carry propagation and significantly improves overall performance.

In this project, the CSLA is implemented using Ripple Carry Adder blocks, which are constructed using 10-transistor (10T) full adders. The 10T full adder design is chosen because it requires fewer transistors compared to conventional CMOS full adders, which typically use 28 transistors. This reduction in transistor count leads to lower power consumption, reduced silicon area, and simplified circuit complexity.

The 10T full adder operates efficiently by using pass transistor logic and optimized transistor arrangements. It ensures that both sum and carry outputs are generated with minimal delay and power usage. Due to its compact design, it is highly suitable for large-scale integration where area and power are critical constraints.

Another important feature of this design is the use of MTCMOS (Multi-Threshold CMOS) technology. Leakage power has become a major concern in deep submicron technologies, especially in standby mode. MTCMOS addresses this issue by using transistors with different threshold voltages. Low-threshold transistors are used in the critical paths to maintain high speed, while high-threshold transistors are used as sleep transistors to reduce leakage power.

The sleep transistors are placed between the power supply and the circuit (header)

or between the circuit and ground (footer). During active mode, these transistors are turned ON, allowing normal operation of the circuit. During standby mode, they are turned OFF, effectively disconnecting the circuit from the power supply and reducing leakage currents. The integration of MTCMOS with the CSLA structure enhances the overall efficiency of the design by significantly reducing static power dissipation without affecting performance during active operation.

This makes the design highly suitable for battery-operated and portable electronic devices. The 4-bit CSLA is designed by dividing the adder into smaller sections, each consisting of RCA blocks and multiplexers. Each section computes outputs for both possible carry inputs in parallel. The multiplexer then selects the correct result based on the incoming carry from the previous stage. This structure ensures faster computation compared to traditional adders. The proposed design also focuses on optimizing the trade-off between speed, power, and area. While CSLA improves speed, it typically requires more hardware due to duplicate computation paths.

However, by using 10T full adders and efficient MTCMOS techniques, the design minimizes this overhead and achieves a balanced performance. The implementation of the design can be carried out using VLSI design tools such as DSCH for schematic design and Microwind for layout design and simulation. These tools allow designers to analyze parameters such as power consumption, delay, and area, and verify the functionality of the circuit.

The simulation results of the proposed design show improved performance in terms of reduced delay and lower power consumption compared to conventional RCA and basic CSLA designs. The use of MTCMOS further reduces leakage power, making the design energy efficient. This project demonstrates how advanced design techniques and optimization strategies can be combined to develop efficient digital circuits. It highlights the importance of selecting appropriate architectures and technologies in achieving desired performance goals.

The proposed 4-bit CSLA design can be extended to higher bit-width adders for use in more complex systems. It also serves as a foundation for further research in low-power VLSI design and optimization techniques.

In conclusion, the Design and Implementation of a 4-Bit Carry Select Adder using MTCMOS-Based Ripple Carry Adder with 10T Full Adders provides an effective solution for high-speed and low-power arithmetic operations. It successfully combines the advantages of CSLA architecture, efficient 10T full adder design, and MTCMOS technology to achieve improved performance, reduced power consumption, and optimized area, making it suitable for modern VLSI applications.

CHAPTER 2

METHODOLOGY

2.1 BLOCK DIAGRAM

The block diagram of the proposed system represents the operation of a 4-bit Carry Select Adder (CSA) using MTCMOS-based Ripple Carry Adders (RCA). The design is structured to improve speed, reduce power consumption, and optimize area.

Initially, the system takes two 4-bit binary inputs A (A_3-A_0) and B (B_3-B_0) along with a carry input (C_{in}). These inputs are fed simultaneously into two separate Ripple Carry Adder (RCA) blocks.

The first RCA assumes the carry input as $C_{in} = 0$ and computes the partial outputs (Sum_0 and C_{out0}). The second RCA assumes $C_{in} = 1$ and computes another set of outputs (Sum_1 and C_{out1}). Both RCAs are built using 10-Transistor (10T) Full Adders integrated with MTCMOS technology, which helps in reducing leakage power while maintaining high-speed operation.

Since both RCAs operate in parallel, the delay caused by sequential carry propagation is significantly reduced. This is the main advantage of the CSA architecture. The outputs from both RCA blocks are then given to a 2:1 Multiplexer (MUX). The multiplexer uses the actual carry input (C_{in}) as a selection line:

If $C_{in} = 0$, outputs from RCA ($C_{in}=0$) are selected

If $C_{in} = 1$, outputs from RCA ($C_{in}=1$) are selected




Fig 2.1 Block diagram

Finally, the selected outputs are produced as the final Sum (S3–S0) and Carry Output (Cout). This structure ensures faster computation, lower power consumption, and efficient hardware usage compared to conventional designs.

2.2 Working Principle

The working principle of the proposed 4-bit Carry Select Adder begins with applying two 4-bit inputs (A and B) along with a carry input (Cin) to the circuit. These inputs are simultaneously fed into two Ripple Carry Adders (RCAs), where one RCA assumes the carry input as 0 and the other assumes it as 1. Both RCAs operate in parallel using MTCMOS-based 10T Full Adders, which helps in reducing leakage power and improving efficiency. Each RCA generates its own set of outputs, namely Sum0 and Cout0 for Cin = 0, and Sum1 and Cout1 for Cin = 1.

These outputs are then provided to a 2:1 multiplexer. The multiplexer selects the correct output based on the actual carry input (Cin). If Cin is 0, the output from the first RCA is selected; otherwise, the output from the second RCA is chosen. Finally, the selected result is produced as the final sum and carry output, ensuring high speed due to parallel processing and low power consumption due to MTCMOS technology.




Fig 2.2 Flow chart process

2.3 ARCHITECTURE

The architecture of the proposed system is designed to implement a high-speed and low-power 4-bit Carry Select Adder (CSA) using 45nm CMOS technology. The main objective of this architecture is to reduce propagation delay and power consumption while maintaining efficient area utilization. The system begins with two sets of binary inputs, $A[3:0]$ and $B[3:0]$, along with a carry input (C_{in}). These inputs are simultaneously applied to two independent Ripple Carry Adder (RCA) blocks.

The first RCA operates under the assumption that the carry input is '0', while the second RCA assumes the carry input as '1'. By computing both possibilities in parallel, the architecture eliminates the waiting time associated with carry propagation in conventional adders. Each RCA is constructed using optimized full adders (such as 10-transistor designs), which help reduce the overall transistor count and improve speed.

Additionally, the integration of MTCMOS technology enables the circuit to operate efficiently by minimizing leakage power during standby conditions and maintaining high performance during active operation.

The outputs generated from both RCAs include two sets of sum and carry values: (Sum0, Cout0) and (Sum1, Cout1). These outputs are then provided as inputs to a 2:1 multiplexer (MUX). The MUX uses the actual carry input (C_{in}) as its selection line to determine which output is correct. If $C_{in} = 0$, the output from the first RCA is selected; otherwise, the output from the second RCA is chosen.

Finally, the selected sum and carry outputs are produced as the final result of the system. This architecture significantly enhances performance by reducing delay through parallel processing, while also achieving low power consumption and compact design. Hence, it is highly suitable for modern VLSI systems, including processors and digital signal processing applications.




Fig 2.3 Architecture

Key Architectural Features

- Parallel computation using dual RCAs
- Reduced delay compared to Ripple Carry Adder
- Low power operation using MTCMOS
- Area-efficient design using 10T full adders
- Fast output selection using MU

CHAPTER 3

SOFTWARE COMPONENTS

3.1 Results

Microwind 3.5 is a widely used software tool in VLSI (Very Large Scale Integration) design that enables engineers and students to design, simulate, and analyze CMOS digital circuits at the layout level. It provides a user-friendly graphical interface where users can create transistor-level layouts using layers such as polysilicon, metal, and diffusion, and directly visualize how integrated circuits are physically implemented on silicon. Microwind supports various technology nodes (such as 45nm and 90nm), allowing designers to study scaling effects, power consumption, and delay characteristics.

It also includes built-in simulation features to verify circuit functionality and performance, along with tools like Design Rule Check (DRC) to ensure the layout follows fabrication constraints. Overall, Microwind 3.5 is an effective educational and practical tool for understanding the complete process of IC design from schematic to layout and simulation.

Step 1: Open DSCH

File → New design.




Fig 3.1 DSCH

Step 2: Design 10T Full Adder

Connect transistors to form a 10-transistor full adder.

Inputs: A, B, Cin

Outputs: Sum and Carry

This step creates the fundamental unit of the adder.




Fig 3.2 Full Adder

Step 3: Design 2:1 Multiplexer (MUX)

Create a MUX circuit.

Inputs: Sum0, Sum1

Select line: Cin

MUX selects the correct output.




Fig 3.3 2:1Mux

Step 4: Build 4-bit Ripple Carry Adder (RCA)

Connect four full adders in series.

Carry output of one stage is connected to the next stage.




Fig 3.4 4bit Ripple Carry Adder

Step 5: Integrate CSA Circuit

Connect both RCAs to the MUX.

This forms the complete Carry Select Adder (CSA).




Fig 3.5 4bit Carry Select Adder

Step 6: Apply Input Signals

Use the clock/input tool to apply signals to A, B, and Cin.

Different combinations are tested.




Fig 3.6 Input signals

Step 7: Run Simulation

Click on Simulate → Run Simulation.

The circuit starts processing inputs.




Fig 3.7 Simulation

Step 8: Making Verilog file




Fig 3.8 Verilog File

Step 9: Generate Verilog File to convert Schematic Layout




Fig 3.9 Schematic Layout

Step 10: Open Microwind




Fig 3.10 Microwind

Step 11: Compile

Select Verilog File




Fig 3.11 Compile

Step 14: Select File




Fig 3.12 Select File

Step 13: Compile




Fig 3.13 Compile

3.2 Output Waveforms

1.10T Full Adder




Fig 3.2.1 10T Full Adder Output Waveform

2.2:1Mux




Fig 3.2.2 2:1Mux Output Waveform

3. Ripple Carry Adder




Fig 3.2.3 Ripple Carry Adder Output Waveform

4. Carry Select Adder




Fig 3.2.4 Carry Select Adder Output Waveform

5..Layout




Fig 3.2.5Layout

CHAPTER 4

APPLICATIONS

1. The proposed 45nm Carry Select Adder (CSA) plays a vital role in modern digital electronics due to its high-speed operation and low power consumption. It is especially useful in systems where fast arithmetic computations are required with minimal delay.
2. In microprocessors and arithmetic logic units (ALUs), the CSA is used to perform rapid addition operations, which are fundamental to instruction execution. Since most processor operations depend on addition, using a faster adder like CSA significantly enhances overall system performance.
3. The design is also widely applicable in Digital Signal Processing (DSP) applications such as digital filters, Fast Fourier Transform (FFT), and image processing systems. These applications require continuous and high-speed mathematical computations, where reduced delay and power efficiency are critical.
4. In communication systems, the CSA is used in encoding, decoding, and error detection/correction circuits. Fast arithmetic operations help improve data transmission speed and reliability.
5. Another important application is in embedded systems and portable electronic devices, including smartphones, tablets, and IoT devices. The use of 45nm technology along with MTCMOS reduces leakage power, making the design energy-efficient and suitable for battery-operated devices.
6. The CSA is also useful in VLSI chip design and custom ICs, where optimized area, power, and speed are essential design constraints. It can be integrated into larger systems like processors, controllers, and signal processing units.

ADVANTAGES AND DISADVANTAGES

ADVANTAGES:

1. High Speed Operation
 - The use of parallel Ripple Carry Adders (RCA) reduces propagation delay, making the circuit faster than conventional adders.
2. Reduced Delay
 - Since outputs are precomputed for both carry inputs (0 and 1), the waiting time for carry propagation is minimized.
3. Low Power Consumption
 - The use of MTCMOS technique significantly reduces leakage power, especially in standby mode.
4. Area Efficient Design
 - The implementation of 10T Full Adders reduces the number of transistors, leading to compact layout design.
5. Improved Performance
 - Combination of low power, high speed, and reduced area makes the design efficient for VLSI applications.

DISADVANTAGES:

1. Increased Hardware Complexity
 - The use of two RCAs and a multiplexer increases circuit complexity compared to a simple Ripple Carry Adder.
2. Higher Area than Basic Adders
 - Although optimized, CSA still occupies more area than a single RCA due to duplicate hardware.
3. Design Complexity
 - Implementation with MTCMOS and 10T logic requires careful design and expertise.
4. Power Overhead in Active Mode

- Running two RCAs in parallel may increase dynamic power consumption during operation.

5. Multiplexer Delay

- Although small, the MUX introduces an additional delay stage in output selection.

CHAPTER 5

CONCLUSION

This work proposes a new 4-bit Carry Select Adder (CSA) design with an MTCMOS-boosted 10T Full Adder-based RCA, solving the issues of high power dissipation and area overhead in typical CSA designs efficiently. With MTCMOS, our scheme drastically minimizes leakage power and preserves a compact transistor structure, which is highly suitable for present-day VLSI designs. Synthesized with Cadence using 90nm technology, our design reduces power by 27.5% and delay by 23.7%, resulting in significant improvement over conventional practices.

Low power, low delay, and efficient area usage provide the assurance for its use in power constrained and high-speed computing applications including microprocessors, DSPs, and embedded systems. The strength of this approach is that it achieves a balance between power, speed, and area without sacrificing performance, and hence it is a scalable and flexible solution for practical integrated circuit designs.

Subsequent research can concentrate on further reducing area overhead while scaling the design up to higherbit RCAs, incorporating more power-saving methods such as Dynamic Voltage and Frequency Scaling (DVFS), and investigating smaller technology nodes (65nm, 45nm, or smaller) for greater efficiency in every performance metric. Under these developments, the said CSA design has the potential to be a vital building block in future low-power, high-performance computing architecture.

FUTURE SCOPE

The proposed 45nm Carry Select Adder (CSA) provides a strong foundation for further advancements in high-speed and low-power VLSI design. In the future, this work can be extended by migrating the design to advanced nanometer technologies such as 32nm, 22nm, 14nm, and even FinFET-based technologies. These technologies can significantly reduce power consumption, improve switching speed, and enhance overall circuit efficiency.

Another important direction is the scaling of the adder architecture to higher bit-widths such as 16-bit, 32-bit, or 64-bit adders. This would make the design more suitable for real-world applications like processors, GPUs, and high-performance computing systems where large data operations are required.

The project can also be improved by incorporating advanced power optimization techniques such as:

Power gating

Clock gating

Multi-threshold CMOS (enhanced MTCMOS)

Dynamic voltage and frequency scaling (DVFS)

These techniques can further reduce both dynamic and static power consumption. In addition, the CSA can be combined with hybrid adder architectures, such as Carry Look-Ahead Adder (CLA) or Carry Skip Adder, to achieve even lower delay and higher performance. This hybrid approach can overcome the limitations of individual adder designs.

Future work may also involve implementing the design using different EDA tools like Cadence, Tanner EDA, or Synopsys, and comparing the results in terms of power, delay, and area. This helps in understanding design trade-offs and improving optimization strategies.

CHAPTER 6

REFERENCE

1. Archana, S., and G. Durga. "Design of low power and high speed ripple carry adder." 2014 International Conference on Communication and Signal Processing. IEEE, 2014. Padmini, G. R., et al. "Design and analysis of 8-bit ripple Carry Adder using nine Transistor Full Adder." 2021 7th international conference on advanced computing and communication systems (ICACCS).
2. Vol. 1. IEEE, 2021 Ray, Chandan Kumar, and K. Srinivasarao. "Design and Implementation of Low power Carry Select Adder Using Transmission Gate Logic." IOSR Journal of VLSI and Signal Processing (IOSR-JVSP), e-ISSN: 2319-4200.
3. Kim, Youngwood, and Lee-Sup Kim. "A low power carry select adder with reduced area." ISCAS 2001. The 2001 IEEE International Symposium on Circuits and Systems (Cat. No. 01CH37196). Vol. 4. IEEE, 2001.
4. Mohapatra, Smita shree, and R. Vaibhav Kumar. "Implementation of Carry Select Adder using CMOS Full Adder."
5. Venu, D. N. "Design and Implementation of an XOR Based 16-bit Carry Select Adder for Area, Delay and Power Minimization." European Chemical Bulletin 12.9 (2023): 256-269. Wang, Yuke, C. Pai, and Xiaoyu Song. "The design of hybrid carry lookahead/carry-select adders." IEEE Transactions on circuits and systems II: Analog and Digital Signal Processing 49.1 (2002): 16-24.
6. Gudala, Nikhil Advait, et al. "Implementation of high speed and low power carry select adder with BEC." 2021 IEEE International Midwest Symposium on Circuits and Systems (MWSCAS). IEEE, 2021.
7. Kishore, P., K. C. Koteswaramma, and Y. Chalapathi Rao. "Design of High Performance Adder Using Modified Gdi Based Full Adder."
8. J Mech Cont. Math Sic 15.8. Singh, Shikha, and Yagnesh B. Shukla. "Low power carry select adder using FinFET technology." 2022 6th International Conference on Devices, Circuits and Systems (ICDCS). IEEE, 2022.

9. Mathews, Belcy D., et al. "Implementation of Efficient Carry Select Adder .Using 45nm Technology in Cadence Tool." 2023 Global Conference on Information Technologies and Communications (GCITC). IEEE, 2023.Reddy, G. Karthik. "Low power-area Pass Transistor Logic based ALU design using low power full adder design." 2015 IEEE 9th International Conference on Intelligent Systems and Control(ISCO).IEEE, 2015.
10. Mohanty, Basant Kumar, and Sujit Kumar Patel. "Area–delay–power efficient carry-select adder." IEEE transactions on circuits and systems II:express briefs 61.6 (2014): 418-422.Sarkar,Shubham, Sujan Sarkar, and Jishan Mehedi."Modified CSA-CIA for Reducing propagation delay." 2018 International Conference on Computer Communication and Informatics (ICCCI). IEEE, 2018.
11. Parmar, Shivani, and Kirat Pal Singh. "Design of high speed hybrid carry select adder." 2013 3rd IEEE International Advance Computing Conference(IACC). IEEE, 2013.