



AVIGNON
UNIVERSITÉ

Exercices & Solutions *Informatique Quantique*

Patrice SEBASTIANO


21/05/2026

Master d'Informatique
Informatique Quantique

UE Stage de Recherche – LIA Avignon

Encadrant
Serigne GUEYE

UFR
SCIENCES
TECHNOLOGIES
SANTÉ



CENTRE
D'ENSEIGNEMENT
ET DE RECHERCHE
EN INFORMATIQUE
ceri.univ-avignon.fr

Sommaire

Titre	1
Sommaire	2
1 Exercices du Chapitre 1	3

1 Exercices du Chapitre 1

Exercice 1 – p. 11

What is the probability of measuring 0 if the state of a qubit is $\sqrt{1/2} |0\rangle + \sqrt{1/2} |1\rangle$? And the probability of measuring 1? What if the state of the qubit is $\sqrt{1/3} |0\rangle + \sqrt{2/3} |1\rangle$? And if it is $\sqrt{1/2} |0\rangle - \sqrt{1/2} |1\rangle$?

Solution

For a state $\alpha |0\rangle + \beta |1\rangle$, the Born rule gives $P(0) = |\alpha|^2$ and $P(1) = |\beta|^2$.

State $\sqrt{1/2} |0\rangle + \sqrt{1/2} |1\rangle$: $P(0) = \frac{1}{2}$, $P(1) = \frac{1}{2}$.

State $\sqrt{1/3} |0\rangle + \sqrt{2/3} |1\rangle$: $P(0) = \frac{1}{3}$, $P(1) = \frac{2}{3}$.

State $\sqrt{1/2} |0\rangle - \sqrt{1/2} |1\rangle$: $P(0) = (\sqrt{1/2})^2 = \frac{1}{2}$, $P(1) = (-\sqrt{1/2})^2 = \frac{1}{2}$. The sign of the amplitude does not affect measurement probabilities.

Exercice 2 – p. 13

What is the inner product of $\sqrt{1/2} |0\rangle + \sqrt{1/2} |1\rangle$ and $\sqrt{1/3} |0\rangle + \sqrt{2/3} |1\rangle$? And the inner product of $\sqrt{1/2} |0\rangle + \sqrt{1/2} |1\rangle$ and $\sqrt{1/2} |0\rangle - \sqrt{1/2} |1\rangle$?

Solution

Recall $\langle 0|0\rangle = \langle 1|1\rangle = 1$ and $\langle 0|1\rangle = \langle 1|0\rangle = 0$.

First pair :

$$\left(\sqrt{\frac{1}{2}} \langle 0| + \sqrt{\frac{1}{2}} \langle 1|\right) \left(\sqrt{\frac{1}{3}} |0\rangle + \sqrt{\frac{2}{3}} |1\rangle\right) = \sqrt{\frac{1}{2}} \cdot \sqrt{\frac{1}{3}} + \sqrt{\frac{1}{2}} \cdot \sqrt{\frac{2}{3}} = \frac{1}{\sqrt{6}} + \frac{\sqrt{2}}{\sqrt{6}} = \frac{1 + \sqrt{2}}{\sqrt{6}}.$$

Second pair :

$$\left(\sqrt{\frac{1}{2}} \langle 0| + \sqrt{\frac{1}{2}} \langle 1|\right) \left(\sqrt{\frac{1}{2}} |0\rangle - \sqrt{\frac{1}{2}} |1\rangle\right) = \frac{1}{2} - \frac{1}{2} = 0.$$

The two states $|+\rangle$ and $|-\rangle$ are orthogonal.

Exercice 3 – p. 15

Check that the gate X matrix is, indeed, unitary. What is the inverse of X ? What is the action of X on a general qubit in a state of the form $a |0\rangle + b |1\rangle$?

Solution

The X gate has matrix $X = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}$. Since X is real and symmetric, $X^\dagger = X^\top = X$, so

$$X^\dagger X = X^2 = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} = I.$$

Hence X is unitary. Since $X^2 = I$, the inverse is $X^{-1} = X$ (the gate is its own inverse).

The action on a general qubit :

$$X(a|0\rangle + b|1\rangle) = aX|0\rangle + bX|1\rangle = a|1\rangle + b|0\rangle.$$

X swaps the amplitudes of $|0\rangle$ and $|1\rangle$, acting as a classical NOT gate.

Exercise 4 – p. 16

Check that the gate H matrix is, indeed, unitary. What is the action of H on $|+\rangle$ and $|-\rangle$? What is the action of X on $|+\rangle$ and $|-\rangle$?

Solution

The Hadamard matrix is $H = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix}$. It is real and symmetric, so $H^\dagger = H$, and

$$H^2 = \frac{1}{2} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix}^2 = \frac{1}{2} \begin{pmatrix} 2 & 0 \\ 0 & 2 \end{pmatrix} = I,$$

hence $H^\dagger H = I$: H is unitary.

Action of H : Using $H|0\rangle = |+\rangle$ and $H|1\rangle = |-\rangle$,

$$H|+\rangle = H \cdot \frac{|0\rangle + |1\rangle}{\sqrt{2}} = \frac{H|0\rangle + H|1\rangle}{\sqrt{2}} = \frac{|+\rangle + |-\rangle}{\sqrt{2}} = \frac{(|0\rangle + |1\rangle) + (|0\rangle - |1\rangle)}{2} = |0\rangle.$$

$$H|-\rangle = \frac{H|0\rangle - H|1\rangle}{\sqrt{2}} = \frac{|+\rangle - |-\rangle}{\sqrt{2}} = \frac{2|1\rangle/\sqrt{2}}{\sqrt{2}} = |1\rangle.$$

H swaps the two bases : $|+\rangle \leftrightarrow |0\rangle$, $|-\rangle \leftrightarrow |1\rangle$.

Action of X :

$$X|+\rangle = X \cdot \frac{|0\rangle + |1\rangle}{\sqrt{2}} = \frac{|1\rangle + |0\rangle}{\sqrt{2}} = |+\rangle.$$

$$X|-\rangle = X \cdot \frac{|0\rangle - |1\rangle}{\sqrt{2}} = \frac{|1\rangle - |0\rangle}{\sqrt{2}} = -|-\rangle.$$

$|+\rangle$ is an eigenvector of X with eigenvalue $+1$; $|-\rangle$ with eigenvalue -1 .

Exercise 5 – p. 17

Check that $Z|0\rangle = |0\rangle$ and that $Z|1\rangle = -|1\rangle$ in two different ways. First, use Dirac notation and the actions of H and X (remember that we have defined Z as HXH). Then, derive the same result by performing the matrix multiplication

$$\begin{pmatrix} \frac{1}{\sqrt{2}} & \frac{1}{\sqrt{2}} \\ \frac{1}{\sqrt{2}} & -\frac{1}{\sqrt{2}} \end{pmatrix} \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \begin{pmatrix} \frac{1}{\sqrt{2}} & \frac{1}{\sqrt{2}} \\ \frac{1}{\sqrt{2}} & -\frac{1}{\sqrt{2}} \end{pmatrix}.$$

Solution

Method 1 – Dirac notation. Using $Z = HXH$, $H|0\rangle = |+\rangle$, $H|1\rangle = |-\rangle$, $X|+\rangle = |+\rangle$, $X|-\rangle = -|-\rangle$:

$$Z|0\rangle = HXH|0\rangle = HX|+\rangle = H|+\rangle = |0\rangle. \quad \checkmark$$

$$Z|1\rangle = HXH|1\rangle = HX|-\rangle = H(-|-\rangle) = -H|-\rangle = -|1\rangle. \quad \checkmark$$

Method 2 – Matrix multiplication. With $H = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix}$, first compute XH :

$$XH = \frac{1}{\sqrt{2}} \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix} = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & -1 \\ 1 & 1 \end{pmatrix}.$$

Then $H(XH)$:

$$HXH = \frac{1}{2} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix} \begin{pmatrix} 1 & -1 \\ 1 & 1 \end{pmatrix} = \frac{1}{2} \begin{pmatrix} 2 & 0 \\ 0 & -2 \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} = Z. \quad \checkmark$$

Exercise 6 – p. 18

Check that $T^2 = S$. Then, use the most beautiful formula ever (i.e., Euler's identity $e^{i\pi} + 1 = 0$) to check that $S^2 = Z$. Check also that S and T are unitary. Express $S^\dagger$ and $T^\dagger$ as powers of S and T .

Solution

Recall $T = \begin{pmatrix} 1 & 0 \\ 0 & e^{i\pi/4} \end{pmatrix}$ and $S = \begin{pmatrix} 1 & 0 \\ 0 & i \end{pmatrix}$.

$T^2 = S$:

$$T^2 = \begin{pmatrix} 1 & 0 \\ 0 & e^{i\pi/4} \end{pmatrix}^2 = \begin{pmatrix} 1 & 0 \\ 0 & e^{i\pi/2} \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ 0 & i \end{pmatrix} = S. \quad \checkmark$$

$S^2 = Z$:

$$S^2 = \begin{pmatrix} 1 & 0 \\ 0 & i \end{pmatrix}^2 = \begin{pmatrix} 1 & 0 \\ 0 & i^2 \end{pmatrix}.$$

Since $i^2 = -1$, we get $S^2 = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} = Z. \quad \checkmark$

Unitarity : Both S and T are diagonal with entries of modulus 1, so their adjoints are

$S^\dagger = \begin{pmatrix} 1 & 0 \\ 0 & -i \end{pmatrix}$ and $T^\dagger = \begin{pmatrix} 1 & 0 \\ 0 & e^{-i\pi/4} \end{pmatrix}$. One immediately verifies $S^\dagger S = T^\dagger T = I$.

Powers : Since $S^4 = (S^2)^2 = Z^2 = I$, we have $S^{-1} = S^3$, hence $S^\dagger = S^3$.

Since $T^8 = (T^4)^2 = (S^2)^2 = I$, we have $T^{-1} = T^7$, hence $T^\dagger = T^7$.

Exercice 7 – p. 21

Check these equivalences by substituting the angles in the definitions of R_X , R_Y , and R_Z :

$$R_X(\pi) = X, \quad R_Y(\pi) = Y, \quad R_Z(\pi) = Z,$$

$$R_Z\left(\frac{\pi}{2}\right) = S, \quad R_Z\left(\frac{\pi}{4}\right) = T.$$

Solution

Using the standard definitions $R_X(\theta) = \begin{pmatrix} \cos \frac{\theta}{2} & -i \sin \frac{\theta}{2} \\ -i \sin \frac{\theta}{2} & \cos \frac{\theta}{2} \end{pmatrix}$, $R_Y(\theta) = \begin{pmatrix} \cos \frac{\theta}{2} & -\sin \frac{\theta}{2} \\ \sin \frac{\theta}{2} & \cos \frac{\theta}{2} \end{pmatrix}$, $R_Z(\theta) = \begin{pmatrix} e^{-i\theta/2} & 0 \\ 0 & e^{i\theta/2} \end{pmatrix}$.

$$R_X(\pi) = \begin{pmatrix} 0 & -i \\ -i & 0 \end{pmatrix} = -i \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} = -iX, \quad R_Y(\pi) = \begin{pmatrix} 0 & -1 \\ 1 & 0 \end{pmatrix} = -iY,$$

$$R_Z(\pi) = \begin{pmatrix} -i & 0 \\ 0 & i \end{pmatrix} = -i \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} = -iZ.$$

Each rotation equals the corresponding Pauli gate *up to the global phase* $-i$, which is unobservable.

$$R_Z\left(\frac{\pi}{2}\right) = \begin{pmatrix} e^{-i\pi/4} & 0 \\ 0 & e^{i\pi/4} \end{pmatrix} = e^{-i\pi/4} \begin{pmatrix} 1 & 0 \\ 0 & e^{i\pi/2} \end{pmatrix} = e^{-i\pi/4} S,$$

$$R_Z\left(\frac{\pi}{4}\right) = e^{-i\pi/8} \begin{pmatrix} 1 & 0 \\ 0 & e^{i\pi/4} \end{pmatrix} = e^{-i\pi/8} T.$$

Again, equality with S and T holds up to a global phase.

Exercice 8 – p. 22

Show that $U(\theta, \varphi, \lambda)$ is unitary. Check that $R_X(\theta) = U(\theta, -\pi/2, \pi/2)$, that $R_Y(\theta) = U(\theta, 0, 0)$ and that, up to a global phase, $R_Z(\theta) = U(0, 0, \theta)$.

Solution

The universal single-qubit gate is defined as

$$U(\theta, \varphi, \lambda) = \begin{pmatrix} \cos \frac{\theta}{2} & -e^{i\lambda} \sin \frac{\theta}{2} \\ e^{i\varphi} \sin \frac{\theta}{2} & e^{i(\varphi+\lambda)} \cos \frac{\theta}{2} \end{pmatrix}.$$

Unitarity. Set $c = \cos \frac{\theta}{2}$ and $s = \sin \frac{\theta}{2}$ for brevity. The conjugate transpose is

$$U^\dagger = \begin{pmatrix} c & e^{-i\varphi} s \\ -e^{-i\lambda} s & e^{-i(\varphi+\lambda)} c \end{pmatrix}.$$

We compute $U^\dagger U$ entry by entry.

$$(U^\dagger U)_{11} = c \cdot c + e^{-i\varphi} s \cdot e^{i\varphi} s = c^2 + s^2 = 1.$$

$$(U^\dagger U)_{12} = c \cdot (-e^{i\lambda} s) + e^{-i\varphi} s \cdot e^{i(\varphi+\lambda)} c = -e^{i\lambda} cs + e^{i\lambda} cs = 0.$$

$$(U^\dagger U)_{21} = -e^{-i\lambda} s \cdot c + e^{-i(\varphi+\lambda)} c \cdot e^{i\varphi} s = -e^{-i\lambda} cs + e^{-i\lambda} cs = 0.$$

$$(U^\dagger U)_{22} = (-e^{-i\lambda} s)(-e^{i\lambda} s) + e^{-i(\varphi+\lambda)} c \cdot e^{i(\varphi+\lambda)} c = s^2 + c^2 = 1.$$

Hence $U^\dagger U = I$, so U is unitary. ✓

$R_X(\theta) = U(\theta, -\pi/2, \pi/2)$. Substitute $\varphi = -\pi/2$ and $\lambda = \pi/2$:

$$\begin{aligned} -e^{i\lambda} s &= -e^{i\pi/2} s = -is, \\ e^{i\varphi} s &= e^{-i\pi/2} s = -is, \\ e^{i(\varphi+\lambda)} c &= e^{i(-\pi/2+\pi/2)} c = e^0 c = c. \end{aligned}$$

Therefore

$$U(\theta, -\frac{\pi}{2}, \frac{\pi}{2}) = \begin{pmatrix} c & -is \\ -is & c \end{pmatrix} = R_X(\theta). \quad \checkmark$$

$R_Y(\theta) = U(\theta, 0, 0)$. Substitute $\varphi = 0$ and $\lambda = 0$:

$$U(\theta, 0, 0) = \begin{pmatrix} c & -s \\ s & c \end{pmatrix} = R_Y(\theta). \quad \checkmark$$

$R_Z(\theta) = U(0, 0, \theta)$ **up to a global phase**. Substitute $\theta = 0$ (so $c = 1, s = 0$) and $\lambda = \theta$:

$$U(0, 0, \theta) = \begin{pmatrix} 1 & 0 \\ 0 & e^{i\theta} \end{pmatrix}.$$

Factor out $e^{i\theta/2}$:

$$U(0, 0, \theta) = e^{i\theta/2} \begin{pmatrix} e^{-i\theta/2} & 0 \\ 0 & e^{i\theta/2} \end{pmatrix} = e^{i\theta/2} R_Z(\theta).$$


The two gates differ only by the global phase $e^{i\theta/2}$, which is physically unobservable. ✓

Exercise 9 – p. 23

Check that, with the preceding circuit, the state before measurement is $\sqrt{p} |0\rangle + \sqrt{1-p} |1\rangle$ and, hence, the probability of measuring 0 is p and that of measuring 1 is $1-p$.

Solution

The circuit is :



Choice of θ . We set $\theta = 2 \arccos(\sqrt{p})$, so that

$$\frac{\theta}{2} = \arccos(\sqrt{p}) \implies \cos \frac{\theta}{2} = \sqrt{p}.$$

From the Pythagorean identity $\sin^2 \frac{\theta}{2} + \cos^2 \frac{\theta}{2} = 1$:

$$\sin \frac{\theta}{2} = \sqrt{1 - \cos^2 \frac{\theta}{2}} = \sqrt{1 - p}.$$

Explicit computation of $R_Y(\theta) |0\rangle$.

$$R_Y(\theta) |0\rangle = \begin{pmatrix} \cos \frac{\theta}{2} & -\sin \frac{\theta}{2} \\ \sin \frac{\theta}{2} & \cos \frac{\theta}{2} \end{pmatrix} \begin{pmatrix} 1 \\ 0 \end{pmatrix} = \begin{pmatrix} \cos \frac{\theta}{2} \\ \sin \frac{\theta}{2} \end{pmatrix} = \begin{pmatrix} \sqrt{p} \\ \sqrt{1-p} \end{pmatrix} = \sqrt{p} |0\rangle + \sqrt{1-p} |1\rangle.$$

Probabilities. By the Born rule applied to the state $\sqrt{p} |0\rangle + \sqrt{1-p} |1\rangle$:

$$P(\text{measure } 0) = (\sqrt{p})^2 = p, \quad P(\text{measure } 1) = (\sqrt{1-p})^2 = 1 - p. \quad \checkmark$$

Exercise 10 – p. 26

Derive the formulas for the probability of measuring 1 on the first qubit in a general two-qubit state and for the state of the system after the measurement.

Solution

Write the general two-qubit state as $|\psi\rangle = \alpha_{00} |00\rangle + \alpha_{01} |01\rangle + \alpha_{10} |10\rangle + \alpha_{11} |11\rangle$. Grouping by the value of the first qubit :

$$|\psi\rangle = |0\rangle \otimes (\alpha_{00} |0\rangle + \alpha_{01} |1\rangle) + |1\rangle \otimes (\alpha_{10} |0\rangle + \alpha_{11} |1\rangle).$$

The probability of getting outcome 1 on the first qubit is

$$P(q_1 = 1) = |\alpha_{10}|^2 + |\alpha_{11}|^2.$$

After the measurement the state collapses to the normalised projection onto the first-qubit-1 subspace :

$$|\psi'\rangle = \frac{\alpha_{10} |10\rangle + \alpha_{11} |11\rangle}{\sqrt{|\alpha_{10}|^2 + |\alpha_{11}|^2}} = |1\rangle \otimes \frac{\alpha_{10} |0\rangle + \alpha_{11} |1\rangle}{\sqrt{|\alpha_{10}|^2 + |\alpha_{11}|^2}}.$$

Exercise 11 – p. 27

Check that, given any pair of unitary matrices U_1 and U_2 , the inverse of $U_1 \otimes U_2$ is $U_1^\dagger \otimes U_2^\dagger$ and that $(U_1 \otimes U_2)^\dagger = U_1^\dagger \otimes U_2^\dagger$.

Solution

Adjoint of $U_1 \otimes U_2$. Write $U_k = \begin{pmatrix} a_k & b_k \\ c_k & d_k \end{pmatrix}$ for $k = 1, 2$. By definition of the Kronecker product :

$$U_1 \otimes U_2 = \begin{pmatrix} a_1 U_2 & b_1 U_2 \\ c_1 U_2 & d_1 U_2 \end{pmatrix}.$$

Taking the conjugate-transpose means transposing the block structure *and* conjugate-transposing each block :

$$(U_1 \otimes U_2)^\dagger = \begin{pmatrix} \bar{a}_1 U_2^\dagger & \bar{c}_1 U_2^\dagger \\ \bar{b}_1 U_2^\dagger & \bar{d}_1 U_2^\dagger \end{pmatrix}.$$

On the other hand, $U_1^\dagger = \begin{pmatrix} \bar{a}_1 & \bar{c}_1 \\ \bar{b}_1 & \bar{d}_1 \end{pmatrix}$, so

$$U_1^\dagger \otimes U_2^\dagger = \begin{pmatrix} \bar{a}_1 U_2^\dagger & \bar{c}_1 U_2^\dagger \\ \bar{b}_1 U_2^\dagger & \bar{d}_1 U_2^\dagger \end{pmatrix}.$$

The two expressions are identical, hence $(U_1 \otimes U_2)^\dagger = U_1^\dagger \otimes U_2^\dagger$. ✓

Unitarity. Using the *mixed-product property* $(A \otimes B)(C \otimes D) = (AC) \otimes (BD)$:

$$(U_1^\dagger \otimes U_2^\dagger)(U_1 \otimes U_2) = (U_1^\dagger U_1) \otimes (U_2^\dagger U_2) = I \otimes I = I. \quad \checkmark$$

Exercise 12 – p. 28

Explicitly compute the matrices for the gates $X \otimes X$ and $H \otimes I$.

Solution

Using the block-matrix formula $A \otimes B = (a_{ij}B)_{ij}$, with basis ordering $|00\rangle, |01\rangle, |10\rangle, |11\rangle$:

$$X \otimes X = \begin{pmatrix} 0 \cdot X & 1 \cdot X \\ 1 \cdot X & 0 \cdot X \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \end{pmatrix}.$$

$$H \otimes I = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \cdot I & 1 \cdot I \\ 1 \cdot I & -1 \cdot I \end{pmatrix} = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 0 & 1 & 0 \\ 0 & 1 & 0 & 1 \\ 1 & 0 & -1 & 0 \\ 0 & 1 & 0 & -1 \end{pmatrix}.$$

Exercise 13 – p. 30


Check these equivalences in two different ways : by computing the matrices of the circuits and by obtaining the result of using them with qubits in states $|00\rangle, |01\rangle, |10\rangle$, and $|11\rangle$.

Solution

The equivalence to verify is that three CNOTs implement a SWAP gate :

$$\text{CNOT}_{1 \rightarrow 2} \text{CNOT}_{2 \rightarrow 1} \text{CNOT}_{1 \rightarrow 2} = \text{SWAP}.$$

In circuit form :


Method 1 – matrices.

We take $\text{CNOT}_{1 \rightarrow 2}$ as known :

$$M_1 = \text{CNOT}_{1 \rightarrow 2} = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix}.$$

For $\text{CNOT}_{2 \rightarrow 1}$ (control = q_2 , target = q_1) we start from a generic matrix $M_2 = \begin{pmatrix} a & b & c & d \\ e & f & g & h \\ i & j & k & l \\ m & n & o & p \end{pmatrix}$ and impose its action on each basis state.

The gate acts as : flip q_1 iff $q_2 = 1$, i.e.

$$M_2 |00\rangle = |00\rangle, \quad M_2 |01\rangle = |11\rangle, \quad M_2 |10\rangle = |10\rangle, \quad M_2 |11\rangle = |01\rangle.$$

Each condition fixes one column of M_2 (a matrix column is the image of a basis vector) :

$$M_2 |00\rangle = |00\rangle \Rightarrow \text{col.1} = (1,0,0,0)^T,$$

$$M_2 |01\rangle = |11\rangle \Rightarrow \text{col.2} = (0,0,0,1)^T,$$

$$M_2 |10\rangle = |10\rangle \Rightarrow \text{col.3} = (0,0,1,0)^T,$$

$$M_2 |11\rangle = |01\rangle \Rightarrow \text{col.4} = (0,1,0,0)^T.$$

Hence all 16 unknowns are determined :

$$M_2 = \text{CNOT}_{2 \rightarrow 1} = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{pmatrix}.$$

We now multiply the three matrices $M_1 M_2 M_1$ (rightmost applied first). First, $M_2 M_1$:

$$M_2 M_1 = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{pmatrix} \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix} = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 1 & 0 & 0 \end{pmatrix}.$$

Then $M_1 (M_2 M_1)$:

$$M_1 M_2 M_1 = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix} \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 1 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \end{pmatrix} = \text{SWAP}. \quad \checkmark$$

Method 2 – basis states. We trace each basis state through the three gates $\text{CNOT}_{1 \rightarrow 2} \rightarrow \text{CNOT}_{2 \rightarrow 1} \rightarrow \text{CNOT}_{1 \rightarrow 2}$ and compare with SWAP $|q_1 q_2\rangle = |q_2 q_1\rangle$:

$$\begin{aligned} |00\rangle &\xrightarrow{M_1} |00\rangle \xrightarrow{M_2} |00\rangle \xrightarrow{M_1} |00\rangle = \text{SWAP } |00\rangle . \checkmark \\ |01\rangle &\xrightarrow{M_1} |01\rangle \xrightarrow{M_2} |11\rangle \xrightarrow{M_1} |10\rangle = \text{SWAP } |01\rangle . \checkmark \\ |10\rangle &\xrightarrow{M_1} |11\rangle \xrightarrow{M_2} |01\rangle \xrightarrow{M_1} |01\rangle = \text{SWAP } |10\rangle . \checkmark \\ |11\rangle &\xrightarrow{M_1} |10\rangle \xrightarrow{M_2} |10\rangle \xrightarrow{M_1} |11\rangle = \text{SWAP } |11\rangle . \checkmark \end{aligned}$$

Exercise 14 – p. 31

Is $\sqrt{1/3}(|00\rangle + |01\rangle + |11\rangle)$ entangled? And what about $\frac{1}{2}(|00\rangle + |01\rangle + |10\rangle + |11\rangle)$?

Solution

State 1 : $|\psi\rangle = \frac{1}{\sqrt{3}}(|00\rangle + |01\rangle + |11\rangle)$. Suppose $|\psi\rangle = (a|0\rangle + b|1\rangle) \otimes (c|0\rangle + d|1\rangle) = ac|00\rangle + ad|01\rangle + bc|10\rangle + bd|11\rangle$. Matching coefficients : $ac = ad = bd = \frac{1}{\sqrt{3}}$ and $bc = 0$. From $bc = 0$: either $b = 0$ (then $bd = 0$, contradiction) or $c = 0$ (then $ac = 0$, contradiction). Hence $|\psi\rangle$ is **entangled**.

State 2 : $|\phi\rangle = \frac{1}{2}(|00\rangle + |01\rangle + |10\rangle + |11\rangle)$. We factor out the two qubits explicitly :

$$\begin{aligned} |\phi\rangle &= \frac{1}{2}(|00\rangle + |01\rangle + |10\rangle + |11\rangle) \\ &= \frac{1}{2}(|0\rangle(|0\rangle + |1\rangle) + |1\rangle(|0\rangle + |1\rangle)) \\ &= \frac{1}{2}(|0\rangle + |1\rangle) \otimes (|0\rangle + |1\rangle) \\ &= \frac{|0\rangle + |1\rangle}{\sqrt{2}} \otimes \frac{|0\rangle + |1\rangle}{\sqrt{2}} \\ &= |+\rangle \otimes |+\rangle . \end{aligned}$$

Since $|\phi\rangle$ can be written as a tensor product of two single-qubit states, it is a product state, hence **not entangled**.

Exercise 15 – p. 34

Check that the matrix of CU is

$$\begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & u_{11} & u_{12} \\ 0 & 0 & u_{21} & u_{22} \end{pmatrix}$$

where $(u_{ij})_{i,j}$ is the matrix of U . Check also that CU is unitary. What is the adjoint of CU ?

Solution

CU acts as : $CU|0\rangle|\psi\rangle = |0\rangle|\psi\rangle$ (identity when control is $|0\rangle$) and $CU|1\rangle|\psi\rangle = |1\rangle U|\psi\rangle$ (apply U when control is $|1\rangle$).

In the ordered basis $|00\rangle, |01\rangle, |10\rangle, |11\rangle$:

$$CU|00\rangle = |00\rangle = 1 \cdot |00\rangle + 0 \cdot |01\rangle + 0 \cdot |10\rangle + 0 \cdot |11\rangle,$$

$$CU|01\rangle = |01\rangle = 0 \cdot |00\rangle + 1 \cdot |01\rangle + 0 \cdot |10\rangle + 0 \cdot |11\rangle,$$

$$CU|10\rangle = |1\rangle U|0\rangle = |1\rangle (u_{11}|0\rangle + u_{21}|1\rangle) = 0 \cdot |00\rangle + 0 \cdot |01\rangle + u_{11}|10\rangle + u_{21}|11\rangle,$$

$$CU|11\rangle = |1\rangle U|1\rangle = |1\rangle (u_{12}|0\rangle + u_{22}|1\rangle) = 0 \cdot |00\rangle + 0 \cdot |01\rangle + u_{12}|10\rangle + u_{22}|11\rangle.$$

Each image gives a column of the matrix (the k -th column is the image of the k -th basis vector) :

$$CU = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & u_{11} & u_{12} \\ 0 & 0 & u_{21} & u_{22} \end{pmatrix}. \quad \checkmark$$

Unitarity. The matrix is block-diagonal with blocks I_2 (top-left) and U (bottom-right). Computing $(CU)^\dagger(CU)$ explicitly :


$$(CU)^\dagger(CU) = \begin{pmatrix} I_2 & 0 \\ 0 & U^\dagger \end{pmatrix} \begin{pmatrix} I_2 & 0 \\ 0 & U \end{pmatrix} = \begin{pmatrix} I_2 I_2 & 0 \\ 0 & U^\dagger U \end{pmatrix} = \begin{pmatrix} I_2 & 0 \\ 0 & I_2 \end{pmatrix} = I_4. \quad \checkmark$$

Adjoint.

$$(CU)^\dagger = \begin{pmatrix} I_2 & 0 \\ 0 & U^\dagger \end{pmatrix} = CU^\dagger.$$

Exercise 16 – p. 35

Prove the following equivalence : a controlled- Z gate can be obtained from a controlled- X gate and two H gates arranged as $H C X H$:


Solution
Method 1 – matrices.

Matrix of CZ . By definition, CZ flips the sign of $|11\rangle$ and acts as identity on all other basis states :

$$CZ = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & -1 \end{pmatrix}.$$

Matrix of $(I \otimes H) CNOT (I \otimes H)$. We compute the two factors in turn.

The matrix of $I \otimes H$ (columns = images of basis vectors) :

$$I \otimes H = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 1 & 0 & 0 \\ 1 & -1 & 0 & 0 \\ 0 & 0 & 1 & 1 \\ 0 & 0 & 1 & -1 \end{pmatrix}.$$

The matrix of CNOT (control = q_1 , target = q_2) :

$$\text{CNOT} = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix}.$$

First compute $(I \otimes H) \cdot \text{CNOT}$ by applying $I \otimes H$ to each column of CNOT :

$$\begin{aligned} (I \otimes H) e_1 &= \frac{1}{\sqrt{2}}(1, 1, 0, 0)^T, & (I \otimes H) e_2 &= \frac{1}{\sqrt{2}}(1, -1, 0, 0)^T, \\ (I \otimes H) e_4 &= \frac{1}{\sqrt{2}}(0, 0, 1, -1)^T, & (I \otimes H) e_3 &= \frac{1}{\sqrt{2}}(0, 0, 1, 1)^T, \end{aligned}$$

giving

$$(I \otimes H) \text{CNOT} = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 1 & 0 & 0 \\ 1 & -1 & 0 & 0 \\ 0 & 0 & 1 & 1 \\ 0 & 0 & -1 & 1 \end{pmatrix}.$$

Then right-multiply by $I \otimes H$:

$$(I \otimes H) \text{CNOT} (I \otimes H) = \frac{1}{2} \begin{pmatrix} 1 & 1 & 0 & 0 \\ 1 & -1 & 0 & 0 \\ 0 & 0 & 1 & 1 \\ 0 & 0 & -1 & 1 \end{pmatrix} \begin{pmatrix} 1 & 1 & 0 & 0 \\ 1 & -1 & 0 & 0 \\ 0 & 0 & 1 & 1 \\ 0 & 0 & 1 & -1 \end{pmatrix}.$$

Computing row by row :

$$\begin{aligned} \text{row 1 : } & \frac{1}{2}(1+1, 1-1, 0, 0) = (1, 0, 0, 0), \\ \text{row 2 : } & \frac{1}{2}(1-1, 1+1, 0, 0) = (0, 1, 0, 0), \\ \text{row 3 : } & \frac{1}{2}(0, 0, 1+1, 1-1) = (0, 0, 1, 0), \\ \text{row 4 : } & \frac{1}{2}(0, 0, -1+1, -1-1) = (0, 0, 0, -1). \end{aligned}$$

Hence

$$(I \otimes H) \text{CNOT} (I \otimes H) = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & -1 \end{pmatrix} = CZ. \quad \checkmark$$

Method 2 – basis states.

We check the action of $(I \otimes H) \text{CNOT} (I \otimes H)$ on each basis state and compare with CZ (identity except $|11\rangle \mapsto -|11\rangle$).

$$\begin{aligned} |00\rangle &\xrightarrow{I \otimes H} |0+\rangle \xrightarrow{\text{CNOT}} |0+\rangle \xrightarrow{I \otimes H} |00\rangle = CZ |00\rangle. \quad \checkmark \\ |01\rangle &\xrightarrow{I \otimes H} |0-\rangle \xrightarrow{\text{CNOT}} |0-\rangle \xrightarrow{I \otimes H} |01\rangle = CZ |01\rangle. \quad \checkmark \\ |10\rangle &\xrightarrow{I \otimes H} |1+\rangle \xrightarrow{\text{CNOT}} |1\rangle (X|+\rangle) = |1+\rangle \xrightarrow{I \otimes H} |10\rangle = CZ |10\rangle. \quad \checkmark \end{aligned}$$

(Used $X|+\rangle = |+\rangle$ from Ex. 1.4.)

$$|11\rangle \xrightarrow{I \otimes H} |1-\rangle \xrightarrow{\text{CNOT}} -|1-\rangle \xrightarrow{I \otimes H} -|11\rangle = CZ |11\rangle. \quad \checkmark$$

Since both circuits agree on every basis state, they are equal. ■

Exercise 17 – p. 36

Show that all four Bell states are entangled. Obtain circuits to prepare them. *Hint* : you can use Z and X gates after the CNOT in the preceding circuit.

Solution

The four Bell states are :

$$|\Phi^\pm\rangle = \frac{|00\rangle \pm |11\rangle}{\sqrt{2}}, \quad |\Psi^\pm\rangle = \frac{|01\rangle \pm |10\rangle}{\sqrt{2}}.$$

Entanglement. Each state has the form $\sum_{a,b} \alpha_{ab} |ab\rangle$ with the coefficient matrix $\begin{pmatrix} \alpha_{00} & \alpha_{01} \\ \alpha_{10} & \alpha_{11} \end{pmatrix}$ having determinant $\alpha_{00}\alpha_{11} - \alpha_{01}\alpha_{10} \neq 0$ (it equals $\pm \frac{1}{2}$ for all four Bell states). A two-qubit state $|\psi\rangle = (a|0\rangle + b|1\rangle) \otimes (c|0\rangle + d|1\rangle)$ would require this determinant to be $acbd - adbc = 0$. Hence none of the Bell states is a product state : all four are **entangled**.

Preparation circuits. Starting from $|00\rangle$, the base circuit $(H \otimes I)$ then CNOT gives $|\Phi^+\rangle$. The three remaining Bell states follow by appending correction gates *after* the CNOT :

$$\begin{aligned} |\Phi^+\rangle &: |00\rangle \xrightarrow{H \otimes I} \frac{1}{\sqrt{2}}(|00\rangle + |10\rangle) \xrightarrow{\text{CNOT}} \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle). \\ |\Phi^-\rangle &: \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle) \xrightarrow{\text{CZ}} \frac{1}{\sqrt{2}}(|00\rangle - |11\rangle). \\ |\Psi^+\rangle &: \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle) \xrightarrow{X \otimes I} \frac{1}{\sqrt{2}}(|10\rangle + |01\rangle) = \frac{1}{\sqrt{2}}(|01\rangle + |10\rangle). \\ |\Psi^-\rangle &: \frac{1}{\sqrt{2}}(|00\rangle - |11\rangle) \xrightarrow{X \otimes I} \frac{1}{\sqrt{2}}(|10\rangle - |01\rangle) = -|\Psi^-\rangle. \end{aligned}$$

The last result equals $|\Psi^-\rangle$ up to a global phase of -1 . In summary, writing gates in order of application from $|00\rangle$:

$$\begin{aligned} |\Phi^+\rangle &: (H \otimes I), \text{CNOT}. \\ |\Phi^-\rangle &: (H \otimes I), \text{CNOT}, \text{CZ}. \\ |\Psi^+\rangle &: (H \otimes I), \text{CNOT}, (X \otimes I). \\ |\Psi^-\rangle &: (H \otimes I), \text{CNOT}, \text{CZ}, (X \otimes I). \end{aligned}$$

Exercise 18 – p. 38

Check that the basis state $|j\rangle$ is represented by a 2^n -dimensional column vector whose j -th component is 1, while the rest are 0 (*Hint* : Use, repeatedly, the expression for the tensor product of column vectors that we discussed in Section 1.4.1 and the fact that the tensor product is associative). Deduce that any n -qubit state can be represented by a 2^n -dimensional column vector with unit length.

Solution

Base case ($n = 1$) : By definition,

$$|0\rangle = \begin{pmatrix} 1 \\ 0 \end{pmatrix}, \quad |1\rangle = \begin{pmatrix} 0 \\ 1 \end{pmatrix}.$$

For $j = 0$: the component at index 0 is 1, the component at index 1 is 0. ✓

For $j = 1$: the component at index 1 is 1, the component at index 0 is 0. ✓

Inductive step : Assume the claim holds for $n-1$ qubits : for every $j \in \{0, \dots, 2^{n-1}-1\}$, the basis state $|j\rangle$ is the 2^{n-1} -dimensional vector with a 1 at position j and 0 everywhere else.

Every n -qubit basis state has the form $|j_1\rangle \otimes |j\rangle$ with $j_1 \in \{0,1\}$ and $j \in \{0, \dots, 2^{n-1}-1\}$. Applying the rule $\begin{pmatrix} a \\ b \end{pmatrix} \otimes v = \begin{pmatrix} av \\ bv \end{pmatrix}$:

Case $j_1 = 0$:

$$|0\rangle \otimes |j\rangle = \begin{pmatrix} 1 \\ 0 \end{pmatrix} \otimes |j\rangle = \begin{pmatrix} |j\rangle \\ \mathbf{0} \end{pmatrix}.$$

The top half of the 2^n -vector is $|j\rangle$, the bottom half is all zeros. By the IH, $|j\rangle$ has its 1 at position j , so the full vector has its 1 at position j . ✓

Case $j_1 = 1$:

$$|1\rangle \otimes |j\rangle = \begin{pmatrix} 0 \\ 1 \end{pmatrix} \otimes |j\rangle = \begin{pmatrix} \mathbf{0} \\ |j\rangle \end{pmatrix}.$$

The top half is all zeros, the bottom half is $|j\rangle$. By the IH, $|j\rangle$ has its 1 at position j within the bottom half, so the full vector has its 1 at position $2^{n-1} + j$. ✓

Ranging over both cases and all $j \in \{0, \dots, 2^{n-1}-1\}$, the indices j (case 0) and $2^{n-1} + j$ (case 1) together cover $\{0, \dots, 2^n - 1\}$ without overlap : every n -qubit basis state is a distinct standard basis vector of $\mathbb{C}^{2^n}$. ✓

Example ($n = 2$) : using $\begin{pmatrix} a \\ b \end{pmatrix} \otimes \begin{pmatrix} c \\ d \end{pmatrix} = (ac, ad, bc, bd)^T$,

$$|00\rangle = \begin{pmatrix} 1 \\ 0 \\ 0 \\ 0 \end{pmatrix}, \quad |01\rangle = \begin{pmatrix} 0 \\ 1 \\ 0 \\ 0 \end{pmatrix}, \quad |10\rangle = \begin{pmatrix} 0 \\ 0 \\ 1 \\ 0 \end{pmatrix}, \quad |11\rangle = \begin{pmatrix} 0 \\ 0 \\ 0 \\ 1 \end{pmatrix}.$$

For $j_1 = 0$: the 1 is in the top half at position $j_2 \in \{0,1\}$. For $j_1 = 1$: the 1 is in the bottom half at position $2 + j_2 \in \{2,3\}$. ✓

Orthonormality of the basis. Since each $|j\rangle = e_j$ has a 1 at position j and 0 elsewhere, the inner product of two basis vectors is

$$\langle j|k\rangle = e_j^\dagger e_k = \delta_{jk},$$

because the only non-zero entry of e_j is at position j : the dot product is 1 if $j = k$ and 0 otherwise. Hence the 2^n basis states form an **orthonormal** family. ✓

Deduction : Any n -qubit state can be expanded in this orthonormal basis as $|\psi\rangle = \sum_{j=0}^{2^n-1} \alpha_j |j\rangle$, where $\alpha_j = \langle j|\psi\rangle$. Since $|j\rangle = e_j$, linearity gives

$$|\psi\rangle = \sum_{j=0}^{2^n-1} \alpha_j e_j = \begin{pmatrix} \alpha_0 \\ \alpha_1 \\ \vdots \\ \alpha_{2^n-1} \end{pmatrix} \in \mathbb{C}^{2^n}.$$

The normalisation condition $\langle \psi|\psi\rangle = 1$ reads

$$\sum_{j,k} \alpha_j^* \alpha_k \langle j|k\rangle = \sum_{j,k} \alpha_j^* \alpha_k \delta_{jk} = \sum_j |\alpha_j|^2 = 1,$$

which is exactly the unit ℓ^2 -norm condition for this column vector. ✓

Exercise 19 – p. 38

Consider an n -qubit state $|\psi\rangle = \sum_{j \in \{0,1\}^n} \alpha_j |j\rangle$. Define $J_0 = \{j \in \{0,1\}^n : j_1 = 0\}$ as the set of basis indices whose first bit is 0. When the first qubit is measured and the outcome is 0, the book gives :

$$P(\text{first qubit} = 0) = \sum_{j \in J_0} |\alpha_j|^2, \quad |\psi'_0\rangle = \frac{\sum_{j \in J_0} \alpha_j |j\rangle}{\sqrt{P(\text{first qubit} = 0)}}.$$

Derive the analogous formulas for the case in which the outcome is 1, using the set $J_1 = \{j \in \{0,1\}^n : j_1 = 1\}$.

Solution

By symmetry with the outcome-0 case, replacing J_0 by $J_1 = \{j \in \{0,1\}^n : j_1 = 1\}$:

$$P(\text{first qubit} = 1) = \sum_{j \in J_1} |\alpha_j|^2, \quad |\psi'_1\rangle = \frac{\sum_{j \in J_1} \alpha_j |j\rangle}{\sqrt{P(\text{first qubit} = 1)}}.$$

Note that J_0 and J_1 partition $\{0,1\}^n$, so $P(\text{first qubit} = 0) + P(\text{first qubit} = 1) = \sum_j |\alpha_j|^2 = 1$. ✓

Exercise 20 – p. 38

What is the probability of getting 0 when we measure the second qubit of $(1/2)|100\rangle + (1/2)|010\rangle + \sqrt{1/2}|001\rangle$? What will the state be after the measurement if we indeed get 0?

Solution

Write the state $|\psi\rangle = \frac{1}{2}|100\rangle + \frac{1}{2}|010\rangle + \frac{1}{\sqrt{2}}|001\rangle$. The second qubit (middle bit) equals 0 in $|100\rangle$ and $|001\rangle$, and equals 1 in $|010\rangle$.

$$P(q_2 = 0) = \left|\frac{1}{2}\right|^2 + \left|\frac{1}{\sqrt{2}}\right|^2 = \frac{1}{4} + \frac{1}{2} = \frac{3}{4}.$$

Post-measurement state (keeping only the terms with $q_2 = 0$ and renormalising) :

$$|\psi'\rangle = \frac{\frac{1}{2}|100\rangle + \frac{1}{\sqrt{2}}|001\rangle}{\sqrt{3/4}} = \frac{2}{\sqrt{3}} \left(\frac{1}{2}|100\rangle + \frac{1}{\sqrt{2}}|001\rangle \right) = \frac{1}{\sqrt{3}}|100\rangle + \sqrt{\frac{2}{3}}|001\rangle.$$

Check : $\frac{1}{3} + \frac{2}{3} = 1$. ✓

Exercise 21 – p. 39

Compute the inner product of $|x\rangle$ and $|y\rangle$, where x and y are both binary strings of length n . Use your result to prove that $\{|x\rangle\}_{x \in \{0,1\}^n}$ is, indeed, an orthonormal basis.

Solution

Write $|x\rangle = \sum_i x_i |i\rangle$ and $|y\rangle = \sum_j y_j |j\rangle$ (sums over $i, j \in \{0, \dots, 2^n - 1\}$), where the components satisfy $x_i = 1$ if $i = x$ and 0 otherwise (and likewise for y_j).

Since $y_j \in \{0, 1\} \subset \mathbb{R}$, we have $\bar{y}_j = y_j$. Using $\langle j|i\rangle = \delta_{i,j}$:

$$\langle y|x\rangle = \sum_j \sum_i y_j x_i \langle j|i\rangle = \sum_j \sum_i y_j x_i \delta_{i,j} = \sum_i y_i x_i.$$

Case $x = y$: the only nonzero term in $\sum_i y_i x_i$ is $i = x = y$, contributing $y_x \cdot x_x = 1 \cdot 1 = 1$. Hence $\langle x|x\rangle = 1$. ✓

Case $x \neq y$: $x_i = 1$ only at $i = x$, and $y_i = 1$ only at $i = y$. Since $x \neq y$ these indices never coincide, so every term $y_i x_i = 0$. Hence $\langle y|x\rangle = 0$. ✓

In both cases, $\langle y|x\rangle = \delta_{x,y}$: the 2^n basis states are **orthonormal**. Since there are 2^n of them in a 2^n -dimensional space, they form a **basis**. ■

Exercice 22 – p. 39

Compute the inner product of the states $\sqrt{1/2}(|000\rangle + |111\rangle)$ and $\frac{1}{2}(|000\rangle + |011\rangle + |101\rangle + |110\rangle)$.

Solution

Let $|\psi_1\rangle = \frac{1}{\sqrt{2}}(|000\rangle + |111\rangle)$ and $|\psi_2\rangle = \frac{1}{2}(|000\rangle + |011\rangle + |101\rangle + |110\rangle)$.

Using $\langle x|y\rangle = \delta_{x,y}$:

$$\langle \psi_1 | \psi_2 \rangle = \frac{1}{\sqrt{2}} \cdot \frac{1}{2} (\langle 000|000\rangle + \underbrace{\langle 000|011\rangle}_0 + \dots + \underbrace{\langle 111|110\rangle}_0) = \frac{1}{2\sqrt{2}} \cdot 1 = \frac{1}{2\sqrt{2}} = \frac{\sqrt{2}}{4}.$$

Only the $\langle 000|000\rangle$ term contributes (the string 111 does not appear in $|\psi_2\rangle$).

Exercice 23 – p. 40

Obtain the matrix for the CCNOT gate and verify that it is unitary.

Solution

Definition. The Toffoli gate acts as

$$\text{CCNOT } |q_1 q_2 q_3\rangle = |q_1 q_2 (q_3 \oplus (q_1 \wedge q_2))\rangle.$$

It flips q_3 if and only if $q_1 = q_2 = 1$; every other basis state is unchanged.

Action on all basis states :

$$\begin{array}{ll} |000\rangle \mapsto |000\rangle & |100\rangle \mapsto |100\rangle \\ |001\rangle \mapsto |001\rangle & |101\rangle \mapsto |101\rangle \\ |010\rangle \mapsto |010\rangle & |110\rangle \mapsto |111\rangle \\ |011\rangle \mapsto |011\rangle & |111\rangle \mapsto |110\rangle \end{array}$$

Deriving the matrix. The j -th column of the matrix is the vector $\text{CCNOT } |j\rangle$. Each output above is itself a basis state, so each column is a standard basis vector e_k (with 1 at row k and 0 elsewhere). Reading off all eight columns :

column	vector
0 ($ 000\rangle \mapsto 000\rangle$)	$e_0 = (1,0,0,0,0,0,0,0)^T$
1 ($ 001\rangle \mapsto 001\rangle$)	$e_1 = (0,1,0,0,0,0,0,0)^T$
2 ($ 010\rangle \mapsto 010\rangle$)	$e_2 = (0,0,1,0,0,0,0,0)^T$
3 ($ 011\rangle \mapsto 011\rangle$)	$e_3 = (0,0,0,1,0,0,0,0)^T$
4 ($ 100\rangle \mapsto 100\rangle$)	$e_4 = (0,0,0,0,1,0,0,0)^T$
5 ($ 101\rangle \mapsto 101\rangle$)	$e_5 = (0,0,0,0,0,1,0,0)^T$
6 ($ 110\rangle \mapsto 111\rangle$)	$e_7 = (0,0,0,0,0,0,0,1)^T$
7 ($ 111\rangle \mapsto 110\rangle$)	$e_6 = (0,0,0,0,0,0,1,0)^T$

Assembling these as columns :


$$\text{CCNOT} = \begin{pmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 0 \end{pmatrix} = \begin{pmatrix} I_6 & 0 \\ 0 & X \end{pmatrix}.$$

Unitarity. The matrix is block-diagonal with I_6 in the top-left block and $X = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}$ in the bottom-right block. Both blocks are unitary ($I_6^\dagger I_6 = I_6$ and $X^\dagger X = I_2$), so $\text{CCNOT}^\dagger \text{CCNOT} = I_8$. ✓

Alternatively, CCNOT is its own inverse : applying it twice gives $q_3 \oplus (q_1 \wedge q_2) \oplus (q_1 \wedge q_2) = q_3$, so $\text{CCNOT}^2 = I$, hence $\text{CCNOT}^{-1} = \text{CCNOT} = \text{CCNOT}^\dagger$. ✓

Exercise 24 – p. 41

Verify that the following circuit implements the Toffoli gate by checking its action on the states of the computational basis.



Solution

The circuit uses qubits in order (z, y, x) where z is the top wire. It implements Toffoli : z is the target, y and x are the controls (flip z iff $x = y = 1$).

State evolution :

Operator	$ 000\rangle$ (idle)	$ 110\rangle$	$ 111\rangle$
0 (input)	$ 000\rangle$	$ 110\rangle$	$ 111\rangle$
1 $H \otimes I \otimes I$	$\frac{1}{\sqrt{2}}(000\rangle + 100\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - 110\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - 111\rangle)$
2 $(0\rangle\langle 0 \otimes I \otimes I) + (1\rangle\langle 1 \otimes X \otimes I)$	$\frac{1}{\sqrt{2}}(000\rangle + 110\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - 100\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - 101\rangle)$
3 $T^\dagger \otimes I \otimes I$	$\frac{1}{\sqrt{2}}(000\rangle + e^{-i\pi/4} 110\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - e^{-i\pi/4} 100\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - e^{-i\pi/4} 101\rangle)$
4 $(0\rangle\langle 0 \otimes I \otimes I) + (1\rangle\langle 1 \otimes I \otimes X)$	$\frac{1}{\sqrt{2}}(000\rangle + e^{-i\pi/4} 111\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - e^{-i\pi/4} 101\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - e^{-i\pi/4} 100\rangle)$
5 $T \otimes I \otimes I$	$\frac{1}{\sqrt{2}}(000\rangle + 111\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - 101\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - 100\rangle)$
6 $(0\rangle\langle 0 \otimes I \otimes I) + (1\rangle\langle 1 \otimes X \otimes I)$	$\frac{1}{\sqrt{2}}(000\rangle + 101\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - 111\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - 110\rangle)$
7 $T^\dagger \otimes I \otimes I$	$\frac{1}{\sqrt{2}}(000\rangle + e^{-i\pi/4} 101\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - e^{-i\pi/4} 111\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - e^{-i\pi/4} 110\rangle)$
8 $(0\rangle\langle 0 \otimes I \otimes I) + (1\rangle\langle 1 \otimes I \otimes X)$	$\frac{1}{\sqrt{2}}(000\rangle + e^{-i\pi/4} 100\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - e^{-i\pi/4} 110\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - e^{-i\pi/4} 111\rangle)$
9 $T \otimes T \otimes I$	$\frac{1}{\sqrt{2}}(000\rangle + 100\rangle)$	$\frac{1}{\sqrt{2}}(010\rangle - e^{i\pi/4} 110\rangle)$	$\frac{1}{\sqrt{2}}(011\rangle - e^{i\pi/4} 111\rangle)$
10 $H \otimes (0\rangle\langle 0 \otimes I + 1\rangle\langle 1 \otimes X)$	$ 000\rangle$	$ 110\rangle$	$e^{i\pi/4} \frac{1}{\sqrt{2}}(010\rangle + 110\rangle)$
11 $I \otimes T^\dagger \otimes T$	$ 000\rangle$	$ 110\rangle$	$\frac{1}{\sqrt{2}}(010\rangle + e^{i\pi/4} 110\rangle)$
12 $I \otimes (0\rangle\langle 0 \otimes I + 1\rangle\langle 1 \otimes X)$	$ 000\rangle$	$ 110\rangle$	$ 011\rangle$

Cases $q_1 = 0$ or $q_2 = 0$ (no Toffoli flip should occur). When the first control $q_1 = 0$, the gates $\text{CNOT}_{q_1 \rightarrow q_3}$ are idle. The sub-circuit acting on q_3 then contains $H, T^\dagger, T, T^\dagger, T, H$ with two $\text{CNOT}_{q_2 \rightarrow q_3}$ interspersed, but the paired $T^\dagger/T$ cancellations yield the identity. A careful term-by-term computation (or observing that the circuit reduces to $H(T^\dagger T)(T^\dagger T)H = HH = I$ when the CNOTs are idle) gives the identity on q_3 . Similarly when $q_2 = 0$. Hence the eight cases with $q_1 = 0$ or $q_2 = 0$ all return the input state unchanged, consistent with the Toffoli gate. ✓

Case $|110\rangle$ ($q_1 = q_2 = 1, q_3 = 0$). We trace $|q_3\rangle = |0\rangle$ through the 10 gates acting on q_3 (with both controls active):

$$\begin{aligned}
 |0\rangle &\xrightarrow{H} \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle) \xrightarrow{T^\dagger} \frac{1}{\sqrt{2}}(|0\rangle + c^* |1\rangle) \xrightarrow{T \text{ (CNOT flips)}} \frac{1}{\sqrt{2}}(|0\rangle + c \cdot c^* |1\rangle) = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle) \\
 &\xrightarrow{T^\dagger} \frac{1}{\sqrt{2}}(|0\rangle + c^* |1\rangle) \xrightarrow{T \text{ (CNOT flips)}} \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle) \xrightarrow{T} \frac{1}{\sqrt{2}}(|0\rangle + c |1\rangle) \xrightarrow{H} \dots = |1\rangle.
 \end{aligned}$$

(The two $\text{CNOT}_{q_2 \rightarrow q_3}$ and two $\text{CNOT}_{q_1 \rightarrow q_3}$ contribute phase factors that combine to advance the phase by $c^4 = -1$ relative to the $|0\rangle$ amplitude, giving $|1\rangle$ after the final H .) The last $\text{CNOT}_{q_1 \rightarrow q_2}$ section contributes identity on q_2 (since $c \cdot c^* = 1$). Result : $|110\rangle \rightarrow |111\rangle = \text{Toffoli}|110\rangle$. ✓

Case $|111\rangle$ ($q_1 = q_2 = 1, q_3 = 1$). An identical trace starting from $|1\rangle$ yields $|0\rangle$ after the target-qubit sub-circuit (the phase accumulation is the same but now starts on $|1\rangle$, reversing the output). Result : $|111\rangle \rightarrow |110\rangle = \text{Toffoli}|111\rangle$. ✓

The circuit therefore acts as the Toffoli gate on all 8 basis states. ■