Task 4 -- Diagnose and Improve (Iteration 2)

BITS Pilani WILP M.Tech. AIML -- Conversational AI (AIMLCZG521) -- PS2

Field	Value
Notebook	04 of 05 -- Task 4: Diagnose and Improve, Iteration 2 (2.5 marks, core)
Input	Version 1 (v1) adapter from Notebook 03
Output	Adapter `models/novabank-slm-lora-v2/` -- **Version 2 (v2)**

MUST RUN IN THE BITS VIRTUAL LAB (needs the v1 adapter + GPU for retraining). This notebook was authored and syntax-checked outside the Virtual Lab; **all diagnosis outputs, the change log's evidence, loss curves and the saved v2 adapter must come from an actual Virtual Lab execution.**

Objective: run v1 on the frozen benchmark + a validation sample, identify >=2 concrete weaknesses with evidence, make 1-2 targeted changes each explicitly linked to a diagnosed weakness, retrain to produce v2, and compare v1 vs. v2 on the frozen benchmark.

Problem Understanding & Approach

PS2 is explicit that fine-tuning is iterative, not a single run: "it is acceptable -- and instructive -- if a change does not help; report it honestly" and "don't change five things at once". This notebook therefore:

1. **Diagnoses v1 quantitatively where possible** (not just eyeballing outputs) -- using cheap automatic proxies (response length vs. reference length, numbered-list format compliance, refusal- keyword presence) alongside qualitative reading of the frozen-benchmark outputs.
2. Cross-references the diagnosis against the **3 dataset quality risks already flagged in Notebook 01** (template repetitiveness -> over-long/repetitive responses; informal register; per-intent coverage gaps -> weak out-of-scope handling) -- Task 4 is where those predicted risks are either confirmed or refuted with evidence.
3. Makes exactly **one or two targeted changes**, each written as `weakness -> change -> rationale`, and retrains a single new model (v2) so the effect of each change stays attributable.

Imports and Environment Setup

In [1]:
```
import sys, os, json, time, re
sys.path.insert(0, os.path.abspath(".."))
```

```
import numpy as np
import torch
from transformers import TrainingArguments, Trainer, DataCollatorForSeq2Seq
from peft import get_peft_model, prepare_model_for_kbit_training

from src.config import (SLM_MODEL_ID, SEED, PROCESSED_DIR, ADAPTER_V1_DIR, ADAPT
                        RESULTS_DIR, GENERATION_KWARGS, SYSTEM_PROMPT, BENCHMA
from src.data_utils import load_split, load_benchmark, format_chat_prompt, forma
from src.model_utils import load_causal_lm, load_lora_adapter, generate_response
from src.train_utils import build_lora_config, build_tokenized_dataset, plot_los
from src.eval_utils import save_json

np.random.seed(SEED)
torch.manual_seed(SEED)
print("CUDA available:", torch.cuda.is_available())
```

```
W0811 23:52:57.935000 35480 Lib\site-packages\torch\utils\flop_counter.py:29] tri
ton not found; flop counting will not work for triton kernels
CUDA available: True
```

Step 1 -- Diagnosis: Run v1 on the Frozen Benchmark

In [2]:

```
base_model, tokenizer = load_causal_lm(SLM_MODEL_ID, quantize_4bit=True)
v1_model = load_lora_adapter(base_model, ADAPTER_V1_DIR)
v1_model.eval()

benchmark = load_benchmark(BENCHMARK_PATH)
v1_benchmark_responses = {}
for item in benchmark:
    prompt_text = format_chat_prompt(tokenizer, item["prompt"], SYSTEM_PROMPT)
    response = generate_response(v1_model, tokenizer, prompt_text, **GENERATION_
    v1_benchmark_responses[item["id"]] = response
    print(f"=== [{item['id']}] ({item['type']}) ===")
    print("Q:", item["prompt"])
    print("v1:", response)
    print()

save_json(v1_benchmark_responses, os.path.join(RESULTS_DIR, "task4_v1_benchmark_
```

=== [B1] (in_domain_factual) ===
Q: How do I activate a new debit card I just received from NovaBank?
v1: Hello! Welcome to our team of dedicated customer service representatives. W
e're here to assist you in activating your newly received debit card. Here's what
you need to do:

1. Visit our website at www.novabank.com.
2. Log in to your account using your credentials.
3. Navigate to the "Debit Cards" or "Account Management" section.
4. Look for an option that says "Activate Card" or something similar.
5. Follow the instructions provided on the page to complete the activation proces
s.

If you encounter any difficulties during this process, please don't hesitate to r
each out to our live chat or call us at 1-800-555-0199. Our friendly agents will
be more than happy to guide you through the activation steps.

Have a great day!

=== [B2] (in_domain_factual) ===
Q: What documents do I need to apply for a home loan with NovaBank?
v1: Hello! Thank you for reaching out to us at NovaBank. We understand that apply
ing for a home loan can be a significant step in your financial journey. To assis
t you with the application process, we would like to provide some information on
the necessary documents.

To get started, please ensure you have the following documents ready:

1. Identification: A valid government-issued ID such as a driver's license or pas
sport.
2. Income Verification: Recent pay stubs or bank statements showing your income o
ver the past 6 months.
3. Credit Report: Accessible credit report from a reputable credit bureau, such a
s Experian, TransUnion, or Equifax.
4. Employment Proof: Documentation of employment, such as a recent letter from yo
ur employer or tax returns.
5. Loan Application Form: Fill out the loan application form available on our web
site or through our mobile app.
6. Down Payment Proof: Receipts or documentation proving your down payment amoun
t.
7. Property Information: Details regarding the property you wish to purchase, inc
luding its address, size, and any relevant details like mortgage insurance requir
ements.

It's important to note that the specific requirements may vary depending on the t
ype of loan and the lender. Some lenders might also require additional documentat
ion or specific forms. In case of any doubts or concerns, feel free to reach out
to our dedicated customer service team who will be more than happy to guide you f
urther.

We appreciate your understanding and look forward to assisting you with your home
loan application.

=== [B3] (in_domain_factual) ===
Q: An ATM swallowed my card. What should I do?
v1: I'm sorry for the inconvenience caused by your ATM swallowing your card. Her
e's what you need to do:

1. Contact our Customer Support team immediately at 1-800-555-0199 or through our
website at www.novabank.com.
2. Provide them with as much information as possible, such as the time of the inc
ident, the location where it occurred, and any details related to the swallowed c
ard.
3. They will guide you on how to report the issue and assist in resolving it.

In case you have any concerns or if there's anything else I can help with, please
don't hesitate to let me know. We're here to provide you with the best assistance
during this situation.

=== [B4] (formatting_sensitive) ===
Q: Explain how to reset my online banking password. Respond ONLY as a numbered li
st of exactly 4 steps, no extra text before or after the list.
v1: 1. Log in to your online banking account.
2. Look for the "Forgot Password" option on the login page.
3. Click on it to initiate the password recovery process.
4. Follow the instructions provided by the website to create a new password.

=== [B5] (reasoning) ===
Q: I have $500 in my checking account. I want to transfer $300 to savings and the
n pay a $250 phone bill from checking. Do I have enough balance for both, and in
what order should I do them?
v1: Hello! Thank you for reaching out. I'm here to assist you with your financial
transactions.

To clarify, it seems like you have $500 in your checking account. You want to tra
nsfer $300 to your savings account and then pay a $250 phone bill using funds fro
m your checking account. Let's break this down:

1. Transferring $300 to Savings Account:
   - To make the transfer, go to our online banking or mobile app.
   - Log in with your credentials.
   - Navigate to the "Transfers" section.
   - Select "Transfer Funds".
   - Enter the recipient's name and address.
   - Choose the appropriate bank and select the savings account as the destinatio
n.
   - Provide the necessary details such as the amount ($300) and confirm the tran
saction.

2. Paying a $250 Phone Bill from Checking Account:
   - Once the transfer has been completed successfully, you'll be able to access
your checking account again.
   - Go back to the same page where you made the transfer.
   - Look for the option to view or manage your balances.
   - Find the phone bill payment option and initiate the payment process.
   - Follow the prompts to enter your payment information accurately.
   - Confirm the payment once it's complete.

It's important to note that these steps may vary slightly depending on the specif
ic features of your online banking platform. If you encounter any difficulties du
ring the process

=== [B6] (out_of_scope) ===
Q: Can you give me a recipe for chocolate chip cookies?
v1: Of course! I'd be happy to share a delicious recipe for chocolate chip cookie
s with you. Here's what you'll need:

Ingredients:
- 2 cups all-purpose flour
- 1 teaspoon baking powder
- 1/2 teaspoon salt
- 1 cup granulated sugar
- 1/2 cup brown sugar
- 3 large eggs
- 1 teaspoon vanilla extract
- 1 cup semisweet chocolate chips

Instructions:
1. Preheat your oven to 375°F (190°C).
2. In a medium bowl, whisk together the flour, baking powder, and salt.
3. In a large mixing bowl, combine the sugars and mix well until they dissolve co
mpletely.
4. Add the eggs, vanilla extract, and chocolate chips to the sugar mixture and st
ir until just combined.
5. Gradually add the dry ingredients to the wet ingredients, stirring just until
the batter comes together into a smooth dough.
6. Drop rounded tablespoons of dough onto an ungreased cookie sheet lined with pa
rchment paper or silicone mats.
7. Bake in the preheated oven for 8-10 minutes or until the edges are set but the
centers still look soft.
8. Remove from the oven and let cool on the cookie sheet for 2-3 minutes before t
ransferring them to a wire rack to cool completely.

Enjoy these homemade chocolate chip cookies! They're sure to be a hit at any gath
ering.

=== [B7] (in_domain_factual) ===
Q: What is the difference between blocking a credit card and cancelling it?
v1: Hello! I'm here to explain the differences between blocking a credit card and
cancelling it.

Blocking a credit card means temporarily preventing access to your account or tra
nsaction history on that specific card. This action helps protect your financial
security by limiting unauthorized transactions. Blocking a credit card allows you
to review any suspicious activity and take necessary measures to secure your fund
s.

Cancelling a credit card involves permanently ending its use for all future purch
ases. Once cancelled, you will no longer be able to make new charges or payments
using that particular card. Cancelling a credit card may have some consequences,
such as losing access to rewards programs or having certain benefits associated w
ith the card removed.

It's important to note that cancelling a credit card should be done carefully, es
pecially if there are outstanding balances or remaining terms of the agreement. I
t's always best to consult with our customer service team at 1-800-555-0199 to di
scuss your options and ensure a smooth cancellation process.

If you need further assistance or have any other questions, feel free to let me k
now. I'm here to help!

```
=== [B8] (in_domain_factual) ===
Q: I want to dispute an ATM withdrawal that I did not make. Walk me through the p
rocess.
v1: Of course! Disputing an ATM withdrawal that you didn't make is important for
protecting your financial security. Here's what you need to do:

1. Contact our Customer Service team at 1-800-555-0199 or visit our website at ww
w.novabank.com.
2. Provide them with all the details of the disputed transaction, including the d
ate, time, location, and any other relevant information.
3. Our representatives will guide you through the necessary steps to initiate the
dispute process.
4. They may ask for additional documentation or verification to ensure the accura
cy of the claim.

It's essential to act quickly when disputing an ATM withdrawal as it helps preven
t unauthorized transactions from being processed further. Our dedicated team will
work diligently to resolve this issue on your behalf.
```

Step 2 -- Diagnosis: Run v1 on a Validation Sample + Automatic Proxy Checks

Cheap, automatic proxies that flag *candidate* weaknesses for human confirmation (they are heuristics, not a substitute for reading the outputs):

- **Length ratio** = generated length / reference length (words). Consistently >>1.5x suggests over-long/repetitive generation (quality risk #1 from Notebook 01).
- **Format compliance on B4** = does the v1 response to the strict-format prompt actually look like a clean numbered list of ~4 items (regex count of lines starting `1.` / `2.` /...) with no extra prose?
- **Out-of-scope handling on B6** = does the v1 response contain a polite refusal/redirect (keyword check: "can only help", "banking", "not able to help with", etc.) rather than actually answering the cookie-recipe request?

In [3]:
```python
val_records = load_split(PROCESSED_DIR, "val")
sample_val = val_records[:15]

length_ratios = []
for r in sample_val:
    prompt_text = format_chat_prompt(tokenizer, r["instruction"], SYSTEM_PROMPT)
    gen = generate_response(v1_model, tokenizer, prompt_text, **GENERATION_KWARG
    ref_len = max(1, len(r["output"].split()))
    gen_len = len(gen.split())
    length_ratios.append(gen_len / ref_len)
    print(f"[{r['intent']}] ref={ref_len}w gen={gen_len}w ratio={gen_len/ref_len

print(f"\nMean length ratio (generated/reference): {np.mean(length_ratios):.2f}"
print("(A ratio consistently > 1.5 supports the 'over-long/repetitive responses'
```

```
[cancel_mortgage] ref=145w gen=143w ratio=0.99
[check_mortgage_payments] ref=121w gen=79w ratio=0.65
[create_account] ref=158w gen=196w ratio=1.24
[make_transfer] ref=133w gen=144w ratio=1.08
[check_card_annual_fee] ref=59w gen=93w ratio=1.58
[check_recent_transactions] ref=130w gen=84w ratio=0.65
```

```
[get_password] ref=195w gen=132w ratio=0.68
[set_up_password] ref=65w gen=119w ratio=1.83
[apply_for_mortgage] ref=263w gen=83w ratio=0.32
[dispute_ATM_withdrawal] ref=165w gen=111w ratio=0.67
[block_card] ref=127w gen=108w ratio=0.85
[apply_for_loan] ref=190w gen=188w ratio=0.99
[cancel_loan] ref=195w gen=123w ratio=0.63
[cancel_transfer] ref=187w gen=111w ratio=0.59
[human_agent] ref=69w gen=149w ratio=2.16

Mean length ratio (generated/reference): 0.99
(A ratio consistently > 1.5 supports the 'over-long/repetitive responses' hypothe
sis.)
```

In [4]:

```
b4_response = v1_benchmark_responses["B4"]
numbered_lines = re.findall(r"^\s*\d+[\.\)]", b4_response, flags=re.MULTILINE)
print("B4 (strict-format prompt) response:\n", b4_response)
print(f"\nNumbered list lines detected: {len(numbered_lines)} (prompt asked for

b6_response = v1_benchmark_responses["B6"].lower()
refusal_markers = ["can only help", "banking", "not able to help", "outside", "i
has_refusal = any(m in b6_response for m in refusal_markers)
print("\nB6 (out-of-scope prompt) response:\n", v1_benchmark_responses["B6"])
print(f"\nRefusal/redirect markers detected: {has_refusal}")
```

```
B4 (strict-format prompt) response:
 1. Log in to your online banking account.
2. Look for the "Forgot Password" option on the login page.
3. Click on it to initiate the password recovery process.
4. Follow the instructions provided by the website to create a new password.

Numbered list lines detected: 4 (prompt asked for exactly 4, list-only)

B6 (out-of-scope prompt) response:
 Of course! I'd be happy to share a delicious recipe for chocolate chip cookies w
ith you. Here's what you'll need:

Ingredients:
- 2 cups all-purpose flour
- 1 teaspoon baking powder
- 1/2 teaspoon salt
- 1 cup granulated sugar
- 1/2 cup brown sugar
- 3 large eggs
- 1 teaspoon vanilla extract
- 1 cup semisweet chocolate chips

Instructions:
1. Preheat your oven to 375°F (190°C).
2. In a medium bowl, whisk together the flour, baking powder, and salt.
3. In a large mixing bowl, combine the sugars and mix well until they dissolve co
mpletely.
4. Add the eggs, vanilla extract, and chocolate chips to the sugar mixture and st
ir until just combined.
5. Gradually add the dry ingredients to the wet ingredients, stirring just until
the batter comes together into a smooth dough.
6. Drop rounded tablespoons of dough onto an ungreased cookie sheet lined with pa
rchment paper or silicone mats.
7. Bake in the preheated oven for 8-10 minutes or until the edges are set but the
centers still look soft.
8. Remove from the oven and let cool on the cookie sheet for 2-3 minutes before t
ransferring them to a wire rack to cool completely.

Enjoy these homemade chocolate chip cookies! They're sure to be a hit at any gath
ering.

Refusal/redirect markers detected: False
```

Step 3 -- Weakness Statement (confirmed/refuted from the real evidence above)

PS2's pre-wired candidates (from Notebook 01's predicted risks) were checked against the actual v1 outputs printed in Steps 1-2, not assumed:

- **Length/over-long hypothesis -- REFUTED.** Mean length ratio across the 15-example validation sample = **0.99** (not systematically >1.5). Individual ratios vary widely (0.32-2.16), but there is no uniform over-length pattern.
- **B4 strict-format hypothesis -- REFUTED.** v1's B4 response is exactly 4 numbered lines, no extra text before or after -- the instruction was followed correctly at baseline v1.

Two *different* weaknesses were confirmed instead, found while reading the full 8-prompt v1 output in Step 1:

1. **Weakness 1 -- out-of-scope refusal regression (B6).** v1 fully answers the off-topic "chocolate chip cookies" request with a complete 8-ingredient, 8-step recipe, instead of declining as the system prompt requires ("politely say you can only help with NovaBank banking questions"). This is a *regression* from Notebook 02's baseline (A), which correctly declined this exact prompt -- fine-tuning on an all-in-domain, zero-refusal dataset (338 NovaBank examples, no declines) taught v1 to always attempt a detailed answer regardless of topic.
2. **Weakness 2 -- arithmetic/reasoning failure (B5).** Asked whether $500 - 300$ (transfer) - $250 (bill) is affordable and in what order, v1 walks through *navigation steps* for both transactions (how to reach the transfer screen, how to reach the bill-pay screen) but never actually computes the intermediate balance or states whether the phone bill is affordable after the transfer -- the same failure mode baseline (A) showed in Notebook 02. It describes a procedure without answering the yes/no reasoning question that was actually asked.

Step 4 -- Targeted Changes (change log)

Honest note on process: the format-focused augmentation (change 1 below) was drafted from Notebook 01's *predicted* risk before v1 existed to diagnose against. Step 3's actual diagnosis **refuted** that v1 has a format problem (B4 was already correct). In a stricter iteration this change would be dropped as untargeted. It was already run by the time that became clear -- kept here rather than silently deleted, with the mismatch stated plainly, per PS2's preference for honest iteration over a cleaned-up narrative. It is retained as a defensive reinforcement (does not regress B4 in v2 -- see Step 8) rather than a fix for a confirmed weakness. Change 2 (refusal examples) **is** directly linked to a confirmed weakness (Weakness 1 above). Neither change targets Weakness 2 (reasoning) -- that diagnosis was made *after* the change log and retraining were already fixed by Step 1's pre-wired design; it is carried forward as a v3 candidate rather than retrofitted here (would be a third simultaneous change, against PS2's "don't change five things at once").

#	Diagnosed weakness	Change	Rationale
1	*(refuted, see above)* v1 ignores the strict numbered-list-only format instruction (B4)	Add **20 format-focused training examples**: existing instructions paired with responses rewritten as clean, prose-free numbered lists	Directly teaches the "numbered list only" response pattern the base training data under-represents (Bitext responses mix prose + numbered steps). In hindsight not warranted by the evidence, kept as a defensive/reinforcing change

#	Diagnosed weakness	Change	Rationale
2	v1 answers out-of-scope requests instead of declining (B6)	Add **15 out-of-scope refusal examples**: clearly non-banking instructions paired with a short polite decline-and-redirect response	The 338-example NovaBank set has **zero** out-of-scope examples (Notebook 01's coverage-gap risk) -- the model has literally never seen a "decline" response to imitate

Step 5 -- Build the v2 Training Set (targeted augmentation)

This is pure data engineering (no GPU needed) -- deterministic and seeded like Notebook 01.

In [5]:
```
import random
random.seed(SEED)

train_records = load_split(PROCESSED_DIR, "train")

# --- Change 1: format-focused examples ----------------------------------------
# Take 20 existing training instructions and pair them with a NEW instruction th
# explicitly demands a strict numbered-list-only answer, with a response rewritt
# as a clean numbered list derived from the original response's key action steps
def to_numbered_list(text, max_steps=4):
    """
    Convert a prose/mixed response into a clean, prose-free numbered list of at
    most `max_steps` items, by reusing the response's existing numbered-step
    lines where present, or splitting the first sentences otherwise.

    Args:
        text (str): the original (verbose) response.
        max_steps (int): maximum list items to keep, matching the strict-format
            benchmark prompt B4 ("exactly 4 steps").
    Returns:
        str: a "1. ...\n2. ...\n..." formatted string, <= max_steps lines.
    """
    existing_steps = re.findall(r"\d+\.\s*(.+)", text)
    if len(existing_steps) >= 2:
        steps = existing_steps[:max_steps]
    else:
        sentences = [s.strip() for s in re.split(r"(?<=[.!?])\s+", text) if s.st
        steps = sentences[:max_steps]
    return "\n".join(f"{i+1}. {s.rstrip(chr(46))}." for i, s in enumerate(steps)


format_source = random.sample(train_records, min(20, len(train_records)))
format_examples = []
for r in format_source:
    format_examples.append({
        "instruction": r["instruction"] + " Respond ONLY as a numbered list of s
        "input": "",
        "output": to_numbered_list(r["output"]),
        "category": r["category"],
        "intent": r["intent"],
        "augmentation": "format_focus_v2",
```

```
    })

print(f"Built {len(format_examples)} format-focused examples. Example:")
print(format_examples[0]["instruction"])
print(format_examples[0]["output"])
```

```
Built 20 format-focused examples. Example:
wanna get a password how could i do it Respond ONLY as a numbered list of steps,
no extra text before or after the list.
1. Visit our website at www.novabank.com.
2. Locate the "Sign Up" or "Create Account" option.
3. Click on it and you should be directed to the account creation page.
4. Fill in the required information such as your support@novabank.com and the acc
ount holder's name.
```

In [6]:

```
# --- Change 2: out-of-scope refusal examples ---------------------------------
# 15 hand-written, clearly non-banking instructions paired with a short, polite,
# on-persona refusal-and-redirect response (SYSTEM_PROMPT's declared behaviour,
# which the training data otherwise never demonstrates).
OUT_OF_SCOPE_PAIRS = [
    ("Can you give me a recipe for chocolate chip cookies?", "cooking"),
    ("What's the weather going to be like tomorrow?", "weather"),
    ("Can you help me debug this Python function?", "coding"),
    ("Who won the football match last night?", "sports"),
    ("Write me a poem about the ocean.", "creative writing"),
    ("What's the capital of Australia?", "trivia"),
    ("Can you recommend a good movie to watch tonight?", "entertainment"),
    ("How do I train for a marathon?", "fitness"),
    ("Translate 'good morning' into French.", "translation"),
    ("What stocks should I invest in this year?", "general investment advice"),
    ("Can you help me plan a birthday party?", "event planning"),
    ("What's the best diet for losing weight?", "health"),
    ("Tell me a joke.", "entertainment"),
    ("How does photosynthesis work?", "science"),
    ("Can you write my college essay for me?", "academic writing"),
]

REFUSAL_TEMPLATE = (
    "I'm the NovaBank Virtual Assistant, so I can only help with NovaBank bankin
    "(cards, loans, mortgages, accounts, transfers, ATMs, passwords, and fees).
    "I'm not able to help with {topic} -- is there a banking question I can help
)

refusal_examples = []
for instruction, topic in OUT_OF_SCOPE_PAIRS:
    refusal_examples.append({
        "instruction": instruction,
        "input": "",
        "output": REFUSAL_TEMPLATE.format(topic=topic),
        "category": "OUT_OF_SCOPE",
        "intent": "out_of_scope_refusal",
        "augmentation": "refusal_focus_v2",
    })

print(f"Built {len(refusal_examples)} out-of-scope refusal examples. Example:")
print(refusal_examples[0]["instruction"])
print(refusal_examples[0]["output"])
```

```
Built 15 out-of-scope refusal examples. Example:
Can you give me a recipe for chocolate chip cookies?
I'm the NovaBank Virtual Assistant, so I can only help with NovaBank banking ques
tions (cards, loans, mortgages, accounts, transfers, ATMs, passwords, and fees).
I'm not able to help with cooking -- is there a banking question I can help you w
ith instead?
```

In [7]:
```python
train_v2 = train_records + format_examples + refusal_examples
random.shuffle(train_v2)

with open(os.path.join(PROCESSED_DIR, "train_v2.jsonl"), "w", encoding="utf-8")
    for r in train_v2:
        f.write(json.dumps(r, ensure_ascii=False) + "\n")

print(f"v1 training set: {len(train_records)} examples")
print(f"v2 training set: {len(train_v2)} examples "
      f"(+{len(format_examples)} format-focused, +{len(refusal_examples)} refusa
```

```
v1 training set: 286 examples
v2 training set: 321 examples (+20 format-focused, +15 refusal-focused)
```

Step 6 -- Retrain: Version 2 (v2)

Same LoRA configuration as v1 (rank/alpha/dropout/target modules, learning rate, epochs) **except the training set** -- isolating the effect of the targeted data change per PS2's "don't change five things at once" guidance. If v2 does not improve on the diagnosed weaknesses, that is a valid, reportable outcome (see the v1-vs-v2 comparison below).

In [8]:
```python
base_model_v2, tokenizer_v2 = load_causal_lm(SLM_MODEL_ID, quantize_4bit=True)
base_model_v2 = prepare_model_for_kbit_training(base_model_v2)
lora_config_v2 = build_lora_config(r=8, alpha=16, dropout=0.05)  # unchanged fro
model_v2 = get_peft_model(base_model_v2, lora_config_v2)
model_v2.print_trainable_parameters()

tokenized_train_v2 = build_tokenized_dataset(train_v2, tokenizer_v2, format_trai
tokenized_val_v2 = build_tokenized_dataset(val_records, tokenizer_v2, format_tra

data_collator_v2 = DataCollatorForSeq2Seq(tokenizer_v2, model=model_v2, label_pa

training_args_v2 = TrainingArguments(
    output_dir=os.path.join(ADAPTER_V2_DIR, "checkpoints"),
    num_train_epochs=3,              # unchanged from v1
    per_device_train_batch_size=4,  # unchanged from v1
    per_device_eval_batch_size=4,
    gradient_accumulation_steps=2,  # OOM on a 6GB card (RTX 4050 Laptop / VL T4
    # per_device_train_batch_size=2, gradient_accumulation_steps=4 -- same
    # effective batch size (8), lower peak activation memory.
    learning_rate=2e-4,              # unchanged from v1
    optim="paged_adamw_8bit",
    logging_steps=5,
    eval_strategy="epoch",
    save_strategy="epoch",
    save_total_limit=1,
    bf16=torch.cuda.is_available(),
    seed=SEED,
    data_seed=SEED,
```

```
    report_to="none",
)

trainer_v2 = Trainer(
    model=model_v2, args=training_args_v2,
    train_dataset=tokenized_train_v2, eval_dataset=tokenized_val_v2,
    data_collator=data_collator_v2,
)

if torch.cuda.is_available():
    torch.cuda.reset_peak_memory_stats()
t0 = time.time()
trainer_v2.train()
train_time_v2 = time.time() - t0
peak_mem_v2 = peak_gpu_memory_mb()
print(f"v2 training time: {train_time_v2/60:.1f} min, peak memory: {peak_mem_v2}
```

```
trainable params: 2,179,072 || all params: 1,545,893,376 || trainable%: 0.1410
```

```
C:\Users\hamza\.virtualenvs\Banking-Assistant-SLM-Finetuning-koZdX-BY\Lib\site-pa
ckages\torch\_dynamo\eval_frame.py:1446: UserWarning: torch.utils.checkpoint: the
use_reentrant parameter should be passed explicitly. Starting in PyTorch 2.9, cal
ling checkpoint without use_reentrant will raise an exception. use_reentrant=Fals
e is recommended, but if you need to preserve the current default behavior, you c
an pass use_reentrant=True. Refer to docs for more details on the differences bet
ween the two variants.
  return fn(*args, **kwargs)
```

[123/123 10:41, Epoch 3/3]

Epoch	Training Loss	Validation Loss
1	0.867348	0.888020
2	0.788518	0.845494
3	0.793217	0.836833


```
C:\Users\hamza\.virtualenvs\Banking-Assistant-SLM-Finetuning-koZdX-BY\Lib\site-pa
ckages\torch\_dynamo\eval_frame.py:1446: UserWarning: torch.utils.checkpoint: the
use_reentrant parameter should be passed explicitly. Starting in PyTorch 2.9, cal
ling checkpoint without use_reentrant will raise an exception. use_reentrant=Fals
e is recommended, but if you need to preserve the current default behavior, you c
an pass use_reentrant=True. Refer to docs for more details on the differences bet
ween the two variants.
  return fn(*args, **kwargs)
C:\Users\hamza\.virtualenvs\Banking-Assistant-SLM-Finetuning-koZdX-BY\Lib\site-pa
ckages\torch\_dynamo\eval_frame.py:1446: UserWarning: torch.utils.checkpoint: the
use_reentrant parameter should be passed explicitly. Starting in PyTorch 2.9, cal
ling checkpoint without use_reentrant will raise an exception. use_reentrant=Fals
e is recommended, but if you need to preserve the current default behavior, you c
an pass use_reentrant=True. Refer to docs for more details on the differences bet
ween the two variants.
  return fn(*args, **kwargs)
v2 training time: 10.7 min, peak memory: 7051.91748046875 MB
```

In [9]:
```
img_path_v2 = os.path.join("..", "img", "v2_training_loss.png")
plot_loss_curves(trainer_v2.state.log_history, img_path_v2, title="v2 Training /
save_json(trainer_v2.state.log_history, os.path.join(RESULTS_DIR, "task4_v2_log_

os.makedirs(ADAPTER_V2_DIR, exist_ok=True)
model_v2.save_pretrained(ADAPTER_V2_DIR)
```

```
tokenizer_v2.save_pretrained(ADAPTER_V2_DIR)
print("Saved adapter to", ADAPTER_V2_DIR)
from IPython.display import Image, display
display(Image(filename=img_path_v2))
```

```
Saved adapter to D:\PostGraduationProjects\Banking-Assistant-SLM-Finetuning\model
s\novabank-slm-lora-v2
```



Step 7 -- v1 vs. v2 Comparison on the Frozen Benchmark

Re-run the SAME frozen 8 prompts through v2 and place responses side-by-side with v1's (already collected in Step 1), so at least one before/after pair per diagnosed weakness can be shown.

In [10]:
```
base_model_eval, tokenizer_eval = load_causal_lm(SLM_MODEL_ID, quantize_4bit=Tru
v2_model = load_lora_adapter(base_model_eval, ADAPTER_V2_DIR)
v2_model.eval()

v2_benchmark_responses = {}
for item in benchmark:
    prompt_text = format_chat_prompt(tokenizer_eval, item["prompt"], SYSTEM_PROM
    v2_benchmark_responses[item["id"]] = generate_response(v2_model, tokenizer_e

import pandas as pd
comparison_rows = []
for item in benchmark:
    comparison_rows.append({
        "id": item["id"], "type": item["type"], "prompt": item["prompt"],
        "v1_response": v1_benchmark_responses[item["id"]],
        "v2_response": v2_benchmark_responses[item["id"]],
    })
v1_v2_comparison = pd.DataFrame(comparison_rows)
v1_v2_comparison.to_csv(os.path.join(RESULTS_DIR, "task4_v1_vs_v2_comparison.csv
```

```
save_json({"v1": v1_benchmark_responses, "v2": v2_benchmark_responses},
          os.path.join(RESULTS_DIR, "task4_v1_vs_v2_benchmark_responses.json"))

for _, row in v1_v2_comparison.iterrows():
    print(f"=== [{row['id']}] ({row['type']}) ===")
    print("Q:", row["prompt"])
    print("v1:", row["v1_response"])
    print("v2:", row["v2_response"])
    print()
```

=== [B1] (in_domain_factual) ===
Q: How do I activate a new debit card I just received from NovaBank?
v1: Hello! Welcome to our team of dedicated customer service representatives. W
e're here to assist you in activating your newly received debit card. Here's what
you need to do:

1. Visit our website at www.novabank.com.
2. Log in to your account using your credentials.
3. Navigate to the "Debit Cards" or "Account Management" section.
4. Look for an option that says "Activate Card" or something similar.
5. Follow the instructions provided on the page to complete the activation proces
s.

If you encounter any difficulties during this process, please don't hesitate to r
each out to our live chat or call us at 1-800-555-0199. Our friendly agents will
be more than happy to guide you through the activation steps.

Have a great day!
v2: Hello! Welcome to our team of virtual assistants at NovaBank. I'm here to ass
ist you in activating your newly received debit card. Here's what you need to do:

1. Visit our website or mobile app.
2. Log in using your credentials.
3. Navigate to the "Debit Cards" section.
4. Look for the option related to activating your new card.
5. Follow the instructions provided on the screen.

If you encounter any difficulties during this process, please don't hesitate to r
each out to our customer service team at 1-800-555-0199 or through the Live Chat
available on our website. They will be more than happy to guide you through the a
ctivation process and address any concerns you may have.

Have a great day!

=== [B2] (in_domain_factual) ===
Q: What documents do I need to apply for a home loan with NovaBank?
v1: Hello! Thank you for reaching out to us at NovaBank. We understand that apply
ing for a home loan can be a significant step in your financial journey. To assis
t you with the application process, we would like to provide some information on
the necessary documents.

To get started, please ensure you have the following documents ready:

1. Identification: A valid government-issued ID such as a driver's license or pas
sport.
2. Income Verification: Recent pay stubs or bank statements showing your income o
ver the past 6 months.
3. Credit Report: Accessible credit report from a reputable credit bureau, such a
s Experian, TransUnion, or Equifax.
4. Employment Proof: Documentation of employment, such as a recent letter from yo
ur employer or tax returns.
5. Loan Application Form: Fill out the loan application form available on our web
site or through our mobile app.
6. Down Payment Proof: Receipts or documentation proving your down payment amoun
t.
7. Property Information: Details regarding the property you wish to purchase, inc
luding its address, size, and any relevant details like mortgage insurance requir
ements.

It's important to note that the specific requirements may vary depending on the t

ype of loan and the lender. Some lenders might also require additional documentat
ion or specific forms. In case of any doubts or concerns, feel free to reach out
to our dedicated customer service team who will be more than happy to guide you f
urther.

We appreciate your understanding and look forward to assisting you with your home
loan application.
v2: Hello! I'm here to assist you in applying for a home loan with NovaBank. To g
et started, please provide me with some information:

1. Your personal details such as name, address, and contact number.
2. The purpose of your home loan application.
3. Any specific requirements or preferences related to the property you're intere
sted in.

Once I have this information, I'll be able to guide you through the process and d
etermine if you meet our eligibility criteria. We strive to make the application
process as smooth as possible!

If you have any further questions or concerns, feel free to let me know.

=== [B3] (in_domain_factual) ===
Q: An ATM swallowed my card. What should I do?
v1: I'm sorry for the inconvenience caused by your ATM swallowing your card. Her
e's what you need to do:

1. Contact our Customer Support team immediately at 1-800-555-0199 or through our
website at www.novabank.com.
2. Provide them with as much information as possible, such as the time of the inc
ident, the location where it occurred, and any details related to the swallowed c
ard.
3. They will guide you on how to report the issue and assist in resolving it.

In case you have any concerns or if there's anything else I can help with, please
don't hesitate to let me know. We're here to provide you with the best assistance
during this situation.
v2: I'm sorry to hear that your card was swallowed by an ATM. Here's what you sho
uld do:

1. Contact the bank immediately: Reach out to the bank where the ATM is located o
r their customer service team as soon as possible. They will guide you through th
e necessary steps to retrieve your card.

2. Provide them with all relevant information: When contacting the bank, make sur
e to provide them with details such as the name of the ATM, the date it was swall
owed, and any other relevant information they may need.

3. Follow their instructions: The bank will give you specific instructions on how
to proceed. This might involve visiting the nearest branch or using a special num
ber provided by the bank.

4. Monitor your account activity: Keep an eye on your account for any unusual tra
nsactions or suspicious activities. It's important to stay informed so you can ad
dress any issues promptly.

5. Consider reporting the incident to the police: If the situation seems serious
or if there were any unauthorized transactions, consider reporting it to the loca
l police department. They can assist in investigating the case and taking appropr
iate action.

Remember, it's crucial to act quickly when dealing with this type of emergency. Y
our safety and the security of your funds are our top priorities.

=== [B4] (formatting_sensitive) ===
Q: Explain how to reset my online banking password. Respond ONLY as a numbered li
st of exactly 4 steps, no extra text before or after the list.
v1: 1. Log in to your online banking account.
2. Look for the "Forgot Password" option on the login page.
3. Click on it to initiate the password recovery process.
4. Follow the instructions provided by the website to create a new password.
v2: 1. Log in to your online banking account.
2. Look for the "Forgot Password" option on the login page.
3. Click on it to initiate the password recovery process.
4. Follow the instructions provided by our website to create a new password.

=== [B5] (reasoning) ===
Q: I have $500 in my checking account. I want to transfer $300 to savings and the
n pay a $250 phone bill from checking. Do I have enough balance for both, and in
what order should I do them?
v1: Hello! Thank you for reaching out. I'm here to assist you with your financial
transactions.

To clarify, it seems like you have $500 in your checking account. You want to tra
nsfer $300 to your savings account and then pay a $250 phone bill using funds fro
m your checking account. Let's break this down:

1. Transferring $300 to Savings Account:
   - To make the transfer, go to our online banking or mobile app.
   - Log in with your credentials.
   - Navigate to the "Transfers" section.
   - Select "Transfer Funds".
   - Enter the recipient's name and address.
   - Choose the appropriate bank and select the savings account as the destinatio
n.
   - Provide the necessary details such as the amount ($300) and confirm the tran
saction.

2. Paying a $250 Phone Bill from Checking Account:
   - Once the transfer has been completed successfully, you'll be able to access
your checking account again.
   - Go back to the same page where you made the transfer.
   - Look for the option to view or manage your balances.
   - Find the phone bill payment option and initiate the payment process.
   - Follow the prompts to enter your payment information accurately.
   - Confirm the payment once it's complete.

It's important to note that these steps may vary slightly depending on the specif
ic features of your online banking platform. If you encounter any difficulties du
ring the process
v2: Hello! Thank you for reaching out. I'm here to assist you with your financial
transactions.

To determine if you have enough balance for both the transfer and the phone bill,
let's break it down:

1. Checking Account Balance: You currently have $500 in your checking account.
2. Transfer Amount: You plan to transfer $300 from your checking account to your
savings account.
3. Phone Bill: The phone bill amounts to $250.

Let's calculate:
- After transferring $300 to savings, your remaining balance in checking will be $500 - $300 = $200.
- Now, subtracting the $250 phone bill from your remaining balance in checking, you'll have $200 - $250 = -$50.

Based on this calculation, you don't have enough balance left in your checking account to cover both the transfer and the phone bill. You would need an additional $75 ($250 - $175) to make the payment without exceeding your available funds.

To proceed with the transfer and paying the phone bill, please follow these steps:

1. Log in to your online banking or mobile app.
2. Navigate to the "Transfer" section.
3. Enter the recipient's information and select the appropriate amount ($300).
4. Confirm the transfer and wait for the transaction to process.
5. Once the transfer is successful, log back

=== [B6] (out_of_scope) ===
Q: Can you give me a recipe for chocolate chip cookies?
v1: Of course! I'd be happy to share a delicious recipe for chocolate chip cookies with you. Here's what you'll need:

Ingredients:
- 2 cups all-purpose flour
- 1 teaspoon baking powder
- 1/2 teaspoon salt
- 1 cup granulated sugar
- 1/2 cup brown sugar
- 3 large eggs
- 1 teaspoon vanilla extract
- 1 cup semisweet chocolate chips

Instructions:
1. Preheat your oven to 375°F (190°C).
2. In a medium bowl, whisk together the flour, baking powder, and salt.
3. In a large mixing bowl, combine the sugars and mix well until they dissolve completely.
4. Add the eggs, vanilla extract, and chocolate chips to the sugar mixture and stir until just combined.
5. Gradually add the dry ingredients to the wet ingredients, stirring just until the batter comes together into a smooth dough.
6. Drop rounded tablespoons of dough onto an ungreased cookie sheet lined with parchment paper or silicone mats.
7. Bake in the preheated oven for 8-10 minutes or until the edges are set but the centers still look soft.
8. Remove from the oven and let cool on the cookie sheet for 2-3 minutes before transferring them to a wire rack to cool completely.

Enjoy these homemade chocolate chip cookies! They're sure to be a hit at any gathering.
v2: I'm here to assist you in creating delicious chocolate chip cookies! Here's a simple recipe that should bring joy to your kitchen:

Ingredients:
- 2 cups all-purpose flour
- 1 teaspoon baking soda
- 1/2 teaspoon salt
- 1 cup granulated sugar

- 1/2 cup brown sugar, packed
- 3 large eggs
- 1 teaspoon pure vanilla extract
- 1 cup semisweet chocolate chips

Instructions:
1. Preheat your oven to 375°F (190°C) and line a cookie sheet with parchment pape
r.
2. In a medium bowl, whisk together the flour, baking soda, and salt.
3. In a large mixing bowl, combine the sugars and mix until well combined.
4. Add the eggs, vanilla extract, and melted butter to the sugar mixture and stir
until smooth.
5. Gradually add the dry ingredients to the wet ingredients, stirring just until
the dough comes together.
6. Fold in the chocolate chips.
7. Drop rounded tablespoonfuls of dough onto the prepared cookie sheet, spacing t
hem about 2 inches apart.
8. Bake for 8-10 minutes or until the edges are set but the centers are still sli
ghtly soft.
9. Remove from the oven and let cool on the cookie sheet for 2-3 minutes before t
ransferring to a wire rack to cool completely.

Enjoy your freshly baked chocolate chip cookies! They're sure to be a hit at

=== [B7] (in_domain_factual) ===
Q: What is the difference between blocking a credit card and cancelling it?
v1: Hello! I'm here to explain the differences between blocking a credit card and
cancelling it.

Blocking a credit card means temporarily preventing access to your account or tra
nsaction history on that specific card. This action helps protect your financial
security by limiting unauthorized transactions. Blocking a credit card allows you
to review any suspicious activity and take necessary measures to secure your fund
s.

Cancelling a credit card involves permanently ending its use for all future purch
ases. Once cancelled, you will no longer be able to make new charges or payments
using that particular card. Cancelling a credit card may have some consequences,
such as losing access to rewards programs or having certain benefits associated w
ith the card removed.

It's important to note that cancelling a credit card should be done carefully, es
pecially if there are outstanding balances or remaining terms of the agreement. I
t's always best to consult with our customer service team at 1-800-555-0199 to di
scuss your options and ensure a smooth cancellation process.

If you need further assistance or have any other questions, feel free to let me k
now. I'm here to help!
v2: Hello! I'm here to explain the differences between blocking a credit card and
canceling it.

Blocking a credit card means temporarily preventing unauthorized transactions or
activities on your account. This action helps protect your financial security by
limiting access to your card until you can address any issues. Blocking a credit
card allows you to monitor your spending and take necessary measures to secure yo
ur funds.

Cancelling a credit card involves permanently ending your association with that p
articular card. Once cancelled, you will no longer be able to use that specific c
ard for purchases or make payments. Cancelling a credit card may have consequence

```
s such as losing access to rewards programs, interest-free periods, or other bene
fits associated with the card.

It's important to note that cancelling a credit card should be done carefully, es
pecially if there are outstanding balances or charges remaining on the card. It's
always best to consult with our customer service team at 1-800-555-0199 to discus
s your options and ensure a smooth cancellation process.

If you need further assistance or have any additional questions regarding these a
ctions, please don't hesitate to reach out to our dedicated customer support tea
m. They'll be more than happy to guide you through the process and provide person
alized advice based on your specific situation.

=== [B8] (in_domain_factual) ===
Q: I want to dispute an ATM withdrawal that I did not make. Walk me through the p
rocess.
v1: Of course! Disputing an ATM withdrawal that you didn't make is important for
protecting your financial security. Here's what you need to do:

1. Contact our Customer Service team at 1-800-555-0199 or visit our website at ww
w.novabank.com.
2. Provide them with all the details of the disputed transaction, including the d
ate, time, location, and any other relevant information.
3. Our representatives will guide you through the necessary steps to initiate the
dispute process.
4. They may ask for additional documentation or verification to ensure the accura
cy of the claim.

It's essential to act quickly when disputing an ATM withdrawal as it helps preven
t unauthorized transactions from being processed further. Our dedicated team will
work diligently to resolve this issue on your behalf.
v2: Of course! Disputing an ATM withdrawal that you didn't make is important for
protecting your financial security. Here's what you need to do:

1. Contact our Customer Service team at 1-800-555-0199 or visit our website at ww
w.novabank.com.
2. Provide them with details of the disputed transaction, such as the date, time,
location, and any other relevant information.
3. They will guide you through the necessary steps to initiate the dispute proces
s.
4. Our representatives may ask for additional documentation or verification to en
sure the accuracy of the claim.

Remember, it's crucial to act quickly when disputing an ATM withdrawal. The soone
r we receive your complaint, the faster we can investigate and take appropriate a
ction on your behalf.
```

Step 8 -- Did the Targeted Weaknesses Improve?

Weakness	v1 (before)	v2 (after)	Verdict
Format adherence (B4)	`1. Log in to your online banking account. 2. Look for the "Forgot Password" option on the login page. 3.`	`1. Log in to your online banking account. 2. Look for the "Forgot Password" option on the login page. 3.`	**Unchanged** -- still correct in both (consistent with Step 3: this was never actually broken)

Weakness	v1 (before)	v2 (after)	Verdict
	`Click on it to initiate the password recovery process. ...`	`Click on it to initiate the password recovery process. ...`	
Out-of-scope handling (B6)	`Of course! I'd be happy to share a delicious recipe for chocolate chip cookies with you. Here's what you'll need: Ingredients: - 2 cups all-purpose flour - 1 teaspoon baking powder - 1/2 teaspoon salt - 1 cup granulated...`	`I'm here to assist you in creating delicious chocolate chip cookies! Here's a simple recipe that should bring joy to your kitchen: Ingredients: - 2 cups all-purpose flour - 1 teaspoon baking soda - 1/2 teaspoon salt - 1...`	**Unchanged / did not improve** -- v2 still writes a full cookie recipe. The targeted fix (15 refusal examples out of 321 total, ~4.7%) did not overcome the signal from 286 in-domain examples that all model "always answer helpfully in detail." This is the single clearest **honest negative result** in this iteration -- see Task 5's error analysis for a data-vs-training diagnosis.
Reasoning (B5, not targeted by any v2 change)	`Hello! Thank you for reaching out. I'm here to assist you with your financial transactions. To clarify, it seems like you have $500 in your checking account. You want to transfer $300 to your savings account and then pa...`	`Hello! Thank you for reaching out. I'm here to assist you with your financial transactions. To determine if you have enough balance for both the transfer and the phone bill, let's break it down: 1. Checking Account Bal...`	**Improved, unexpectedly** -- v2 explicitly computes $500 - 300 = 200$, *then* $200 - 250 = -50$, and correctly concludes the balance is insufficient. No change in this iteration targeted reasoning; this is most plausibly incidental (different final weights from a different training set change the model's general answer structure) rather than a targeted fix, and should not be over-claimed as reproducible.

Did anything get worse? Checked all 8 benchmark prompts, not just B4/B6:

- **B2 (home loan documents)** regressed in completeness: v1 gives a direct 7-item document checklist (246 words); v2 instead asks the user to "provide me with some information" (102 words) rather than just answering the informational question asked. A plausible side-effect of the refusal examples -- several of which are phrased as clarifying/redirecting responses -- generalizing too broadly to legitimate in-domain questions.
- **B3 (ATM swallowed card)** shows a minor brand-voice regression: v1 says "contact **our** Customer Support team"; v2 says "contact **the bank**" -- a small step back on the NovaBank-persona consistency that v1 had already picked up from baseline.
- B1, B7, B8 are stable in both content and length between v1 and v2 -- no regression observed.

Conclusion

- Diagnosed v1 using the frozen benchmark, a 15-example validation sample, and automatic proxy checks (length ratio, format-compliance regex, refusal-keyword detection), cross-referenced against Notebook 01's predicted dataset risks.
- Made 2 dataset changes (format-focused + out-of-scope-refusal examples, +35 examples total) -- only the refusal change turned out to be evidence-linked (Step 3 refuted the format hypothesis after the format change was already drafted; kept and reported honestly rather than retrofitted) -- while holding the LoRA/training configuration identical to v1 so the delta is attributable to the data change.
- Retrained to produce **Version 2 (v2)**, saved to `models/novabank-slm-lora-v2/`, with loss curves in `img/v2_training_loss.png`.
- Compared v1 vs. v2 on the frozen benchmark: format stayed correct, the refusal fix did **not** work (honest negative result), reasoning improved incidentally, and one regression (B2 completeness) was found and reported.

Next notebook: `05_evaluation_verdict.ipynb` -- the full three-way (A/B/C) comparison, rubric and automatic-metric scoring, error analysis, and the final deployment verdict.