Merge (中間) 範例

Input file

```
stage 3

v1 vdd gnd 6V

RS1_1    vdd  n1   2K
RP1_1    n1   gnd  16K
RS2_1    n1   n2   8K
RP2_1    n2   gnd  8K
RS3_1    n2   n3   4K
RP3_1    n3   gnd  4K

end
```

Execution window

*** Welcome to MySpice ***

==========

Please type 1 to input file
Please type 2 to calculate voltage and current
Please type 3 to swap stage
Please type 4 to merge stage
Please type 5 to output file
Please type 6 to exit
Enter your selection Here:*1*

==========

Please enter the name of the input file again: *input.txt*
Loading the file...
The input file successfully loaded!

==========

Please type 1 to input file
Please type 2 to calculate voltage and current
Please type 3 to swap stage
Please type 4 to merge stage
Please type 5 to output file
Please type 6 to exit
Enter your selection Here: *4*

==========

Please enter the first stage you want to merge: 1
Please enter the second stage you want to merge: 2
Resistors are merged into RP1.
=> RP1 n1 gnd 8.000 k
The stage is Successfully merged!
==========

Please type 1 to input file
Please type 2 to calculate voltage and current
Please type 3 to swap stage
Please type 4 to merge stage
Please type 5 to output file
Please type 6 to exit
Enter your selection Here: *2*
==========

Calculating...
The result is successfully calculated!
****

**	<<voltage>>	**
**	vdd 6.000v	**
**	n1 4.000v	**
**	n3 2.000v	**
**	<<current>>	**
**	RS1_1 1.000mA	**
**	RP1 500.000uA	**
**	RS3_1 500.000uA	**
**	RP3_1 500.000uA	**
**		**
**	myspice2021	**

****
==========

Please type 1 to input file
Please type 2 to calculate voltage, current, and power
Please type 3 to swap stage
Please type 4 to merge stage
Please type 5 to output file
Please type 6 to exit
Enter your selection Here: *5*
==========

Please enter the name of the output file: *output.txt*
Exporting the file...
The output file successfully exported!
==========
Please type 1 to input file
Please type 2 to calculate voltage and current
Please type 3 to swap stage
Please type 4 to merge stage
Please type 5 to output file
Please type 6 to exit
Enter your selection Here: *6*
==========
Bye~

Output file

```
stage 2

v1 vdd gnd 6V

RS1_1    vdd  n1   2K
RP1      n1   gnd  8K
RS3_1    n1   n3   4K
RP3_1    n3   gnd  4K

end
```