

CLOAK & DAGGER Slave PCB Assembly Parts List

Designator	Description	Part No.
Capacitors		
C1	100 pF, 100 V, Dipped Fixed Mica Capacitor	128002-101
C2	39 pF, 100 V, Dipped Fixed Mica Capacitor	128002-390
C3	0.1 μ F, 50 V, $\pm 10\%$, Ceramic Capacitor	122002-104
C4-C51	0.22 μ F, 25 V, $\pm 20\%$, Axial-Lead Ceramic Capacitor	122004-224
C52-C54	100 μ F, 35 V, Axial-Lead Aluminum Electrolytic Capacitor (Acceptable substitute is part no. 124001-107)	24-350107
C55-C101	0.1 μ F, 50 V, $\pm 10\%$, Ceramic Capacitor	122002-104
Coil		
L1	100 uH, $\pm 10\%$ Inductor	141002-001
Diodes		
CR1, CR2	Red Light-Emitting Diode	38-MV5053
Integrated Circuits		
1B	Type-74LS244 Line Driver/Receiver Integrated Circuit	37-74LS244
1C	Type-74LS244 Line Driver/Receiver Integrated Circuit	37-74LS244
1D	Static RAM Integrated Circuit	137211-120
1E/F	PROM Integrated Circuit	136023-309
1F/H	PROM Integrated Circuit	136023-310
1J	PROM Integrated Circuit	136023-311
1K	PROM Integrated Circuit	136023-312
1L	PROM Integrated Circuit	136023-313
1M	PROM Integrated Circuit	136023-314
1N	PROM Integrated Circuit	136023-315
2B/D	8-Bit Microprocessor Integrated Circuit	90-6012
2E	Type-74LS245 Tri-State Octal Bus Transceiver Integrated Circuit	37-74LS245
2F/H	Type-74LS244 Line Driver/Receiver Integrated Circuit	37-74LS244
2F	Type-74LS245 Tri-State Octal Bus Transceiver Integrated Circuit	37-74LS245
2H/J	Type-74LS245 Tri-State Octal Bus Transceiver Integrated Circuit	37-74LS245
2J	Type-74LS374 Octal D-Type Flip-Flop Integrated Circuit	37-74LS374
2K	Type-74LS138 3-8 Line Decoder/Multiplexer Integrated Circuit	137177-001
2L	Type-74LS08 Quad 2-Input AND Gate Integrated Circuit	37-74LS08
2M	Type-74S260 Dual 5-Input NOR Gate Integrated Circuit	37-74S260
2N	Type-74LS163A 4-Bit Synchronous Counter Integrated Circuit	37-74LS163A
3B	Type-74LS74 Dual D-Type Flip-Flop Integrated Circuit	37-74LS74
3C	Type-74LS244 Dual D-Type Flip-Flop Integrated Circuit	37-74LS74
3D	Line Driver/Receiver Integrated Circuit	37-74LS244
3E	Type-74LS04 Hex Inverter Integrated Circuit	37-74LS04
3H	Custom Integrated Circuit	137321-1111
3J	Type-74153 Dual Data Selector/Multiplexer Integrated Circuit	37-74153
3L	Type-74LS139 Dual 2-4 Decoder/Multiplexer Integrated Circuit	37-74LS139
3M	Type-74LS163A 4-Bit Synchronous Counter Integrated Circuit	37-74LS163A
3N	PROM Integrated Circuit	136023-116
4B	Type-7406 Buffer/Driver, Hex Inverter Integrated Circuit	37-7406
4C	Type-74LS163A 4-Bit Synchronous Counter Integrated Circuit	37-74LS163A

(continued on next page)

CLOAK & DAGGER Slave PCB Assembly Parts List, continued

Designator	Description	Part No.
4D	Type-74LS86 Quad 2-Input EXOR Gate Integrated Circuit	37-74LS86
4F	Type-74153 Dual Data Selector/Multiplexer Integrated Circuit	37-74153
4H	Type-74LS169A Up/Down Binary, Synchronous 4-Bit Counter Integrated Circuit	137109-001
4J	Type-74LS169A Up/Down Binary, Synchronous 4-Bit Counter Integrated Circuit	137109-001
4K	Type-74153 Dual Data Selector/Multiplexer Integrated Circuit	37-74153
4L	Type-74LS32 Quad 2-Input OR Gate Integrated Circuit	37-74LS32
4M	Type-74LS74 Dual D-Type Flip-Flop Integrated Circuit	37-74LS74
4N	Type-74LS175 Quad D-Type Flip-Flop Integrated Circuit	37-74LS175
5A	Type-74LS194 Shift Register Integrated Circuit	37-74LS194
5B	Type-74LS157 Quad Data Selector/Multiplexer Integrated Circuit	37-74LS157
5C	Type-74LS160 4-Bit/Binary Counter Integrated Circuit	37-74LS160
5D	Type-74LS194 Shift Register Integrated Circuit	37-74LS194
5E	Type-74LS194 Shift Register Integrated Circuit	37-74LS194
5F	Type-74LS86 Quad 2-Input EXOR Gate Integrated Circuit	37-74LS86
5H	Type-74LS169A Up/Down Binary, Synchronous 4-Bit Counter Integrated Circuit	137109-001
5J	Type-74LS169A Up/Down Binary, Synchronous 4-Bit Counter Integrated Circuit	137109-001
5K	Type-74LS04 Hex Inverter Integrated Circuit	37-74LS04
5L	Type-74LS109A Integrated Circuit	37-74LS109A
5M	Type-74LS00 Quad 2-Input NAND Gate Integrated Circuit	37-74LS00
5N	Type-74LS32 Quad 2-Input OR Gate Integrated Circuit	37-74LS32
6A	Type-74LS157 Quad Data Selector/Multiplexer Integrated Circuit	37-74LS157
6B	Type-74LS151 1-8 Data Selector/Multiplexer Integrated Circuit	37-74LS151
6C	Type-74LS151 1-8 Data Selector/Multiplexer Integrated Circuit	37-74LS151
6D	Type-74LS157 Quad Data Selector/Multiplexer Integrated Circuit	37-74LS157
6E	Type-74LS157 Quad Data Selector/Multiplexer Integrated Circuit	37-74LS157
6F	Type-74LS151 1-8 Data Selector/Multiplexer Integrated Circuit	37-74LS151
6H	Type-74LS139 Dual 2-4 Decoder/Multiplexer Integrated Circuit	37-74LS139
6J	Type-74153 Dual Data Selector/Multiplexer Integrated Circuit	37-74153
6K	Type-74LS00 Quad 2-Input NAND Gate Integrated Circuit	37-74LS00
6L	Type-74LS74 Dual D-Type Flip-Flop Integrated Circuit	37-74LS74
6M	Type-74LS02 Quad 2-Input NOR Gate Integrated Circuit	37-74LS02
6N	Type-74LS08 Quad 2-Input AND Gate Integrated Circuit	37-74LS08
7A-7F	Random-Access-Memory Integrated Circuit	100017-001
7H, 7J	Type-74LS157 Quad Data Selector/Multiplexer Integrated Circuit	37-74LS157
7K	Type-74S00 Quad 2-Input NAND Gate Integrated Circuit	37-74S00
7L	Type-74LS74 Dual D-Type Flip-Flop Integrated Circuit	37-74LS74
7M	Type-74LS74 Dual D-Type Flip-Flop Integrated Circuit	37-74LS74
7N	Type-74LS00 Quad 2-Input NAND Gate Integrated Circuit	37-74LS00
8A-8F	Type-4116 Random-Access-Memory Integrated Circuit	100017-001
8H	Type-74LS02 Quad 2-Input NOR Gate Integrated Circuit	37-74LS02
8J	Type-74LS02 Quad 2-Input NOR Gate Integrated Circuit	37-74LS02
8K	Type-74109 Dual J-K Flip-Flop Integrated Circuit	37-74109
8L	Type-74LS32 Quad 2-Input OR Gate Integrated Circuit	37-74LS32
8M	Type-74LS00 Quad 2-Input NAND Gate Integrated Circuit	37-74LS00
8N	Type-74S74 Dual D-Type Flip-Flop Integrated Circuit	37-74S74

(continued on next page)

CLOAK & DAGGER Slave PCB Assembly Parts List, continued

Designator	Description	Part No.
9A-9F	Type-4116 Random-Access-Memory Integrated Circuit	100017-001
9H, 9J	Type-74LS02 Quad 2-Input NOR Gate Integrated Circuit	37-74LS02
9K	Type-74LS74 Dual D-Type Flip-Flop Integrated Circuit	37-74LS74
9L	Type-74LS02 Quad 2-Input NOR Gate Integrated Circuit	37-74LS02
9M	Type-74S04 Hex Inverter Integrated Circuit	37-74S04
9N	Type-74S74 Dual D-Type Flip-Flop Integrated Circuit	37-74S74
10A-10F	Type-4116 Random-Access-Memory Integrated Circuit	100017-001
Resistors		
R1, R2	10 k Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-103
R3	220 Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-221
R4-R6	470 Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-471
R7, R8	27 Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-270
R9-R11	10 k Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-103
R12	150 Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-151
R13-R17	1 k Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-102
R18	470 Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-471
R19-R25	27 Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-270
R26	10 k Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-103
R27	100 Ω , $\pm 5\%$, $\frac{1}{4}$ W Resistor	110000-101
Sockets		
1D	24 Contact, Medium-Insertion-Force IC Socket	79-42C24
1E/F	28 Contact, Medium-Insertion-Force IC Socket	79-42C28
1F/H	28 Contact, Medium-Insertion-Force IC Socket	79-42C28
1J	28 Contact, Medium-Insertion-Force IC Socket	79-42C28
1K	28 Contact, Medium-Insertion-Force IC Socket	79-42C28
1L	28 Contact, Medium-Insertion-Force IC Socket	79-42C28
1M	28 Contact, Medium-Insertion-Force IC Socket	79-42C28
1N	28 Contact, Medium-Insertion-Force IC Socket	79-42C28
2B/D	40 Contact, Medium-Insertion-Force IC Socket	79-42C40
3H	24 Contact, Medium-Insertion-Force IC Socket	79-42C24
Transistor		
Q1	350 mW, 60 V, Switching NPN Transistor	34-2N3904
Miscellaneous		
Y1	10 MHz Crystal	90-123
	Test Points (Acceptable substitute is part no. 020670-01)	179051-002