Rajalakshmi Engineering College

Name: Harsha G

Email: 240801112@rajalakshmi.edu.in

Roll no: 240801112 Phone: 8939522475

Branch: REC

Department: I ECE FB

Batch: 2028

Degree: B.E - ECE



NeoColab_REC_CS23231_DATA STRUCTURES

REC_DS using C_Week 3_COD_Question 5

Attempt : 1 Total Mark : 10 Marks Obtained : 10

Section 1: Coding

1. Problem Statement

Milton is a diligent clerk at a school who has been assigned the task of managing class schedules. The school has various sections, and Milton needs to keep track of the class schedules for each section using a stack-based system.

He uses a program that allows him to push, pop, and display class schedules for each section. Milton's program uses a stack data structure, and each class schedule is represented as a character. Help him write a program using a linked list.

Input Format

The input consists of integers corresponding to the operation that needs to be performed:

Choice 1: Push the character onto the stack. If the choice is 1, the following input is a space-separated character, representing the class schedule to be pushed onto the stack.

Choice 2: Pop class schedule from the stack

Choice 3: Display the class schedules in the stack.

Choice 4: Exit the program.

Output Format

The output displays messages according to the choice and the status of the stack:

- If the choice is 1, push the given class schedule to the stack and display the following: "Adding Section: [class schedule]"
- If the choice is 2, pop the class schedule from the stack and display the following: "Removing Section: [class schedule]"
- If the choice is 2, and if the stack is empty without any class schedules, print "Stack is empty. Cannot pop."
- If the choice is 3, print the class schedules in the stack in the following: "Enrolled Sections: " followed by the class schedules separated by space.
- If the choice is 3, and there are no class schedules in the stack, print "Stack is empty"
- If the choice is 4, exit the program and display the following: "Exiting the program"
 - If any other choice is entered, print "Invalid choice"

Refer to the sample output for the exact format.

Sample Test Case

Input: 1 d

3

2

```
Output: Adding Section: d
Adding Section: h
Enrolled C
    Removing Section: h
    Enrolled Sections: d
    Exiting program
    Answer
    #include <stdio.h>
    #include <stdlib.h>
    struct Node {
    char data;
      struct Node* next;
    struct Node* top = NULL;
    // You are using GCC
    void push(char value) {
       //Type your code here
       struct Node *newnode=(struct Node*)malloc(sizeof(struct Node*));
       newnode->data=value;
       newnode->next=top;
top=newnode;
       printf("Adding Section:%c\n",value);
    void pop() {
       //Type your code here
       if(top==NULL)
       {
         printf("Stack is empty.Cannot pop.\n");
         return;
       }
       else
         struct Node *temp=top;
         top=top->next;
         printf("Removing Section:%c\n",temp->data);
```

```
free(temp);
                          240801112
     void displayStack() {
       //Type your code here
       if(top==NULL)
         printf("Stack is empty\n");
         return;
       }
       else
        struct Node *temp=top;
         printf("Enrolled Sections:");
         while(temp!=0)
           printf("%c ",temp->data);
           temp=temp->next;
         printf("\n");
       }
     }
     int main() {
       int choice:
do {
       char value;
         scanf("%d", &choice);
         switch (choice) {
           case 1:
              scanf(" %c", &value);
             push(value);
              break:
           case 2:
              pop();
              break;
            case 3:
              displayStack();
                                                    240801112
              break;
           case 4:
              printf("Exiting program\n");
              break:
```

240801712

```
240801112
                                    240801112
    } } while (choice != 4);
     return 0;
   }
                                                 Marks: 10/10
   Status: Correct
240801112
                                    240801112
                                                      240801112
```

2,40801712

2,40801112

240801112

240801112