JP1: BRIDGE ONE SIDE ONLY. JP2: REGULATOR OR A105 POWER, NEVER BOTH.

U1 ESP32-C3-WROOM-02-N4
J1 DC-1024 compatible 5.5/2.1mm
J2 USB-C POWER ONLY
J3 LED OUT
J4 M5STACK A105
U2 LMR36510FADDAR
JH1 DIP LEFT
JH2 DIP RIGHT
JP1 INPUT USB|DC
JP2 3V3 REG|A105
Q1 RJP020N06T100
L1 22uH >=1.5A
RFBT 57.6k 1%
RFBB 24.9k 1%
REN 10k
RBOOT 10k
RCC1 5.1k 1%
RCC2 5.1k 1%
RG 100R
RPD 100k
CIN1 2.2uF 50V
CIN2 220nF 100V
CBOOT 100nF 25V
CVCC 1uF 10V
COUT1 22uF 10V
COUT2 22uF 10V
C3V3 10uF 10V
CDEC 100nF
CEN 1uF 10V

Power-only USB-C; selectable USB/DC input; selectable regulator/A105 3V3

Sheet: /
File: esp32-c3-compact-dip-led.kicad_sch

Title: ESP32-C3 Compact DIP + PWM

Size: A3 | Date: | Rev:
KiCad E.D.A. 9.0.6 | Id: 1/1