VLSI Devices
Lecture 7

Sung-Min Hong (smhong@gist.ac.kr)
Semiconductor Device Simulation Laboratory
Department of Electrical Engineering and Computer Science
Gwangju Institute of Science and Technology (GIST)

L7

MOS capacitor

- Voltage across the capacitor, V_g
  - Silicon charge, Q_s
  - Gate charge, $Q_g = -Q_s$
  - Therefore, we can consider

$$-Q_s(V_g)$$

An ideal capacitor

- Consider a planar capacitor.
  - Its dielectric layer is SiO_2. It is 2-nm-thick.
  - Then,

$$C_{ox} = \frac{\epsilon_{ox}}{t_{ox}} = 1.73\ \mu\mathrm{F/cm^2}$$

  - Draw its $Q(V)$ curve.

$-Q_s(V_g)$ of a MOS capacitor

- We cannot find a capacitance value for all biases. Instead,

$$C_g = \frac{dQ_g}{dV_g} = -\frac{dQ_s}{dV_g}$$

Taur, Eq. (4.34)



Just draw C_g.

- Bias-dependent capacitance
  - Remember that $C_{ox} = 1.73\ \mu\mathrm{F/cm^2}$.
  - Frequency?



Expressions

- Remember the MOS equation.

$$V_g - V_{fb} = \frac{Q_g}{C_{ox}} + \phi_s$$

Taur, ~Eq. (4.7)

  - Differentiation w.r.t. Q_g yields

$$\frac{dV_g}{dQ_g} = \frac{1}{C_{ox}} + \frac{d\phi_s}{dQ_g}$$

  - We obtain

$$\frac{1}{C_g} = \frac{dV_g}{dQ_g} = \frac{1}{C_{ox}} + \frac{d\phi_s}{dQ_g} = \frac{1}{C_{ox}} + \frac{1}{C_{si}}$$

Taur, Eq. (4.36)

$$C_{si} = \frac{dQ_g}{d\phi_s} = -\frac{dQ_s}{d\phi_s}$$

Homework#7

- Due: 08:00 on March 30
- Submit a PDF report through the GIST LMS system.
  - We know $Q_s(\phi_s)$. Derive an explicit expression for C_{si}.

Example of a long-channel MOSFET

- Effective oxide thickness of 1.2 nm
  - Gate workfunction of 4.3 eV
  - Substrate doping of $1.5X10^{18}$ cm^{-3}
  - V_{dd} of 1.2 V



Computer program

- For accurate prediction of electrical characteristics
  - Gate workfunction of 4.3 eV

Hole density at $V_g = V_d = 0$ V

- Depletion of holes



Ramping the gate voltage up

- From 0 V to 1.2 V (V_{dd})
  - Estimate the threshold voltage.



Semi-logarithmic graph

- Estimate the subthreshold slope, the DIBL, I_{ON}, and I_{OFF}.



Output characteristics

- Results from V_g = 0.6 V to 1.2 V (0.2 V step)



Thank you!