

PHASE

2

Getting to C: Screen, Serial and kprintf

Give the kernel a stack, jump into C, and build the two output channels you will debug with for the rest of the project

Overall progress toward Turk-OS 1.0 (this phase in red)

10% → 16%

🕒 Duration

1–2 weeks

★ Difficulty

★★☆☆☆ (2/5)

✂ You need

Phase 1: a Multiboot kernel that boots, a Makefile, GDB workflow

🔧 You will have

A kernel written mostly in C that prints a coloured banner and the machine's memory size on the VGA text screen, mirrors every message to the serial port (so it appears in your terminal), and has kprintf, panic and ASSERT.

1 Why this phase

From now on, most of Turk-OS is written in C. Getting there takes one small piece of assembly (a stack) and a few compiler flags. Right after that comes the most important debugging tool you will build: a way to print. With no operating system under you, printf does not exist, so you will write the drivers it would normally sit on.

You will build two output channels. The **VGA text screen** is what a user sees. The **serial port** is what a developer needs: QEMU can redirect it to your terminal or a log file, where messages can be scrolled back, searched, and kept after a crash. When something goes wrong in Phase 6 or Phase 8, the serial log is usually your only witness. Both drivers also introduce the two ways a CPU talks to devices, memory-mapped I/O and port I/O, which you will use in every driver from here on.

2 Concepts you need

2.1 What C needs before kmain can run

A C function expects three things from its environment. It expects a **valid stack**, because every call pushes a return address and locals live there; Multiboot leaves ESP undefined, so the loader must reserve memory for a stack and point ESP at its top. It expects **zeroed .bss**, because the C standard says globals without an initialiser start at zero; GRUB and QEMU load ELF kernels by their program headers and zero-fill the part of each segment beyond the file contents, so .bss is handled for you, but it is worth confirming once in GDB. And it expects **the calling convention**: arguments on the stack, so the loader can pass the Multiboot magic and information pointer to kmain by pushing them.

2.2 Two ways to talk to a device

Memory-mapped I/O places a device's memory or registers at ordinary physical addresses. The VGA text buffer lives at 0xB8000: write a byte there and a character appears on screen. You use normal pointer accesses, marked `volatile` so the compiler can't optimise them away. **Port-mapped I/O** uses a separate 64 K address space reachable only through the `in` and `out` instructions. The VGA cursor and the serial port are controlled this way. **MOS** §5.1.3 compares the two designs and explains why x86 has both.

2.3 The VGA text buffer

In text mode the screen is 80 columns by 25 rows. Each cell is two bytes: the character (in code page 437, which extends ASCII) and an attribute byte whose low four bits are the foreground colour and whose high four bits are the background (Figure 1). Cell (row, col) is at index $row \times 80 + col$. The blinking hardware cursor is separate: you position it by writing a 16-bit cell index to the CRT controller through ports $0x3D4$ (register select) and $0x3D5$ (data), register 14 for the high byte and 15 for the low byte.




Figure 1: One 16-bit VGA text cell. White on blue is attribute $0x1F$; the cell for “A” is then $0x1F41$.

2.4 The serial port

A PC’s first serial port (COM1) is a 16550-compatible UART with its registers at I/O ports $0x3F8$ – $0x3FF$. You initialise it once, choosing the speed with a divisor of its 115 200 Hz base clock and the frame format (8 data bits, no parity, one stop bit, known as “8N1”). After that, sending a byte means waiting until the *line status* register says the transmitter is empty, then writing the byte to the data port. QEMU’s `-serial stdio` connects this port to your terminal.

2.5 A console abstraction and kprintf

Rather than making every function choose where to print, write one `kprintf` that formats a string and hands each character to a small console layer, which forwards it to every registered output (Figure 2). Formatting uses `stdarg.h`, which is available in freestanding mode because it is implemented by the compiler itself.




Figure 2: Output path. Adding a third sink later (a log buffer for `dmesg`) is one line.

3 Reading plan

Priority	Book	What to read	Pages	Why now
REQUIRED	LOB	Ch. 3 <i>Getting to C</i> : stack, calling C from assembly, packing structs, compiling C, build tools	19–22	Tasks 2.1–2.3 almost step by step.
REQUIRED	LOB	Ch. 4 <i>Output</i> : framebuffer, cursor, serial port, configuring the line, buffers and modem	23–31	The two drivers of this phase.
REQUIRED	OSTEP	Ch. 36 <i>I/O Devices</i> (§36.1–36.7: canonical device, protocol, interrupts, DMA, device interaction, drivers)	405–412	The mental model for every driver you will write.

Priority	Book	What to read	Pages	Why now
RECOMMENDED	MOS	§5.1 <i>Principles of I/O Hardware</i> , especially §5.1.3 <i>Memory-Mapped I/O</i>	337–351	Why x86 has both port and memory-mapped I/O.
RECOMMENDED	MOS	§5.6.2 <i>Output Software</i> (text windows, escape sequences)	399–405	How a text console turns bytes into a screen.
RECOMMENDED	OSDI	§3.8.6 <i>Implementation of the Display Driver</i>	357–366	MINIX writing to video memory and scrolling.
OPTIONAL	OSC	§12.2 <i>I/O Hardware</i>	490–500	Another view: polling, interrupts, DMA.
OPTIONAL	MOS	§1.8 <i>The World According to C</i> (if skipped in Phase 0)	73–77	Organising headers for a multi-file project.

Q Real-system lens: how MINIX 3 does it

Open `drivers/tty/console.c` (15900) in **OSDI**. MINIX keeps a per-console struct with the cursor position and the video memory address, and it scrolls either by copying memory or by moving the hardware's display start. Compare its `out_char` and `scroll_screen` with what you write in Task 2.5. Notice that the MINIX console driver runs as a separate process and receives characters in messages; in Turk-OS it is an ordinary function call.

4 Build it

Task 2.1 Give the loader a stack and call C

Reserve 16 KiB in `.bss`, point ESP at its top (the stack grows down), push the two Multiboot values in reverse order and call `kmain`. Also set bit 1 of the Multiboot flags so GRUB fills in the memory size fields, and bit 0 so boot modules are page-aligned (you will use modules in Phase 10).

boot/loader.s

```
global loader
extern kmain

MB_ALIGN      equ 1 << 0           ; align boot modules on 4 KiB pages
MB_MEMINFO    equ 1 << 1           ; ask for mem_lower / mem_upper and the memory map
MAGIC_NUMBER  equ 0x1BADB002
FLAGS         equ MB_ALIGN | MB_MEMINFO
CHECKSUM      equ -(MAGIC_NUMBER + FLAGS)

KERNEL_STACK_SIZE equ 16384

section .multiboot
align 4
    dd MAGIC_NUMBER
    dd FLAGS
    dd CHECKSUM

section .bss
align 16
kernel_stack_bottom:
    resb KERNEL_STACK_SIZE
kernel_stack_top:

section .text
loader:
```

```

mov esp, kernel_stack_top ; C needs a stack before anything else
push ebx                  ; arg 2: physical address of the Multiboot info
push eax                  ; arg 1: magic value 0x2BADB002
call kmain                ; kmain(magic, mbi)
.hang:
cli                        ; kmain should never return; if it does, stop
hlt
jmp .hang

```

Task 2.2 The first C code

Start with the smallest C that proves the jump worked: write a character straight into video memory.

kernel/kmain.c (first version)

```

#include <stdint.h>

void kmain(uint32_t magic, uint32_t mbi_addr)
{
    (void)magic; (void)mbi_addr;
    volatile uint16_t *vga = (volatile uint16_t *)0xB8000;
    vga[0] = 0x1F00 | 'T';    /* white on blue, top-left corner */
    vga[1] = 0x1F00 | 'K';
}

```

✓ **Verify:** A blue “TK” appears in the top-left corner. In GDB, break `kmain` stops there and `p/x magic` prints `0x2badb002`.

Task 2.3 Compile C for the kernel

Extend the Makefile with a C rule. The flags say: freestanding (no hosted library assumptions), warnings on and treated seriously, debug info for GDB, and keep frame pointers for backtraces in Phase 3. Link through `gcc` so that `libgcc` is available; GCC sometimes emits calls into it (64-bit division, for example).

Makefile (additions)

```

CC      := i686-elf-gcc
CFLAGS  := -std=gnu11 -ffreestanding -O2 -g -Wall -Wextra -fno-omit-frame-pointer -Iinclude
LDFLAGS := -T link.ld -ffreestanding -nostdlib
C_SRCS  := $(wildcard kernel/*.c kernel/drivers/*.c lib/*.c)
OBJS     := $(BUILD)/boot/loader.o $(patsubst %.c,$(BUILD)/%.o,$(C_SRCS))

$(BUILD)/kernel.elf: $(OBJS) link.ld
    $(CC) $(LDFLAGS) -o $@ $(OBJS) -lgcc

$(BUILD)/%.o: %.c
    @mkdir -p $(dir $@)
    $(CC) $(CFLAGS) -c $< -o $@

run: $(BUILD)/kernel.elf
    qemu-system-i386 -kernel $< -serial stdio

```

Task 2.4 Port I/O helpers

C has no way to express in and out, so wrap them. **LOB** writes them as separate assembly functions, which is a good exercise in `cdecl` (the port is at `[esp+4]`, the value at `[esp+8]`). Most kernels use GCC inline assembly instead, which avoids a function call per port access. Write the assembly version first to practise, then switch to this header:

```
include/io.h

#pragma once
#include <stdint.h>

static inline void outb(uint16_t port, uint8_t val)
{
    __asm__ volatile ("outb %0, %1" : : "a"(val), "Nd"(port));
}

static inline uint8_t inb(uint16_t port)
{
    uint8_t ret;
    __asm__ volatile ("inb %1, %0" : "=a"(ret) : "Nd"(port));
    return ret;
}

/* A write to an unused port takes about 1 microsecond: a tiny delay for old devices. */
static inline void io_wait(void) { outb(0x80, 0); }
```

Task 2.5 The VGA text driver

Write `kernel/drivers/vga.c` with `vga_init`, `vga_clear`, `vga_set_color`, `vga_putc` and `vga_write`. `vga_putc` must handle `\n` (new line), `\r`, `\t` (next multiple of 8), and `\b` (backspace, needed in Phase 4). When the cursor passes the last row, scroll: move rows 1–24 up by one with `memmove` and clear the last row. After each character, move the hardware cursor.

```
kernel/drivers/vga.c (core pieces)

#define VGA_WIDTH 80
#define VGA_HEIGHT 25
static volatile uint16_t *const vga_buf = (volatile uint16_t *)0xB8000;
static uint8_t color = 0x07; /* light grey on black */
static uint16_t row, col;

static inline uint16_t vga_cell(char c, uint8_t attr)
{
    return (uint16_t)attr << 8 | (uint8_t)c;
}

static void move_cursor(void)
{
    uint16_t pos = row * VGA_WIDTH + col;
    outb(0x3D4, 14); outb(0x3D5, pos >> 8); /* cursor location high byte */
    outb(0x3D4, 15); outb(0x3D5, pos & 0xFF); /* cursor location low byte */
}
```

✓ **Verify:** Print 100 numbered lines: the screen scrolls and the last 25 are visible. The cursor blinks after the last character.

Task 2.6 The serial driver

Write `kernel/drivers/serial.c`. The initialisation sequence below sets 38 400 baud 8N1 with FIFOs enabled, following **LOB** chapter 4. Each register offset is relative to the base port `0x3F8`.

```
kernel/drivers/serial.c

#define COM1 0x3F8

void serial_init(void)
{
    outb(COM1 + 1, 0x00); /* interrupt enable register: all off (we poll) */
    outb(COM1 + 3, 0x80); /* line control: set DLAB to access the divisor */
}
```

```

    outb(COM1 + 0, 0x03); /* divisor low byte: 115200 / 3 = 38400 baud */
    outb(COM1 + 1, 0x00); /* divisor high byte */
    outb(COM1 + 3, 0x03); /* line control: 8 data bits, no parity, 1 stop, DLAB=0 */
    outb(COM1 + 2, 0xC7); /* FIFO control: enable, clear, 14-byte threshold */
    outb(COM1 + 4, 0x03); /* modem control: DTR and RTS set */
}

static int tx_empty(void) { return inb(COM1 + 5) & 0x20; } /* line status bit 5 */

void serial_putc(char c)
{
    if (c == '\n')
        serial_putc('\r'); /* terminals expect CR LF */
    while (!tx_empty())
        ;
    outb(COM1, (uint8_t)c);
}

```

✓ **Verify:** With `make run` (which passes `-serial stdio`), text you send to the serial port appears in your terminal. Also try `-serial file:build/serial.log`.

Task 2.7 kprintf and the console layer

Write `lib/printf.c` with `kvprintf(void (*putc)(char), const char *fmt, va_list ap)` as the engine, and `kprintf` on top of it using the console. Support `%c`, `%s`, `%d`, `%i`, `%u`, `%x`, `%p` and `%%`, plus zero-padding with a width (`%08x`), which makes addresses readable. Use `utoa` and `itoa` from Phase 0.

lib/printf.c (skeleton)

```

#include <stdarg.h>

void kprintf(const char *fmt, ...)
{
    va_list ap;
    va_start(ap, fmt);
    kvprintf(console_putc, fmt, ap);
    va_end(ap);
}

```

✓ **Verify:** Write a test that prints `0`, `-1`, `INT_MIN`, `0xFFFFFFFF` with `%u` and `%x`, `%08x` of `0xB8000`, a NULL string (`print (null)`), and `%%`. Compare with what the same format string gives in a Linux test program.

Task 2.8 panic and ASSERT

When the kernel detects something impossible, it must stop loudly instead of continuing with corrupt state. `panic` prints the message with file and line, disables interrupts and halts. `ASSERT` calls it when a condition is false. Use `ASSERT` generously from now on; it is the cheapest debugging tool you have.

include/panic.h

```

#pragma once
void panic_at(const char *file, int line, const char *fmt, ...) __attribute__((noreturn));

#define panic(...) panic_at(__FILE__, __LINE__, __VA_ARGS__)
#define ASSERT(cond) \
    do { if (!(cond)) panic("assertion failed: %s", #cond); } while (0)

```

Task 2.9 Read the Multiboot information

Check that magic equals `0x2BADB002`; otherwise panic with “not loaded by a Multiboot loader”. Define the beginning of the Multiboot information structure as a packed struct (see **LOB** “Packing Structs” and the Multiboot spec §3.3). If bit 0 of `flags` is set, `mem_lower` and `mem_upper` hold the KiB of memory below 1 MiB and above 1 MiB. Print a banner: Turk-OS 0.2 - 127 MiB RAM.

include/multiboot.h (first fields)

```
struct multiboot_info {
    uint32_t flags;
    uint32_t mem_lower;      /* KiB below 1 MiB, valid if flags bit 0 */
    uint32_t mem_upper;      /* KiB above 1 MiB, valid if flags bit 0 */
    uint32_t boot_device;
    uint32_t cmdline;        /* physical address of the command line */
    uint32_t mods_count;     /* boot modules (Phase 10) */
    uint32_t mods_addr;
    uint32_t syms[4];
    uint32_t mmap_length;    /* memory map (Phase 5) */
    uint32_t mmap_addr;
} __attribute__((packed));
```

✓ **Verify:** `qemu-system-i386 -kernel build/kernel.elf -serial stdio -m 128` reports roughly 127 MiB. Change `-m` and watch the number follow.

5 Testing and debugging

From this phase on, run QEMU with `-serial stdio` every time and put a `kprintf` at each boot step (“GDT loaded”, “paging on”, ...). When the kernel dies, the last line in the log tells you where.

Symptom	Likely cause	What to do
QEMU reboots in a loop right after call <code>kmain</code>	Stack not set, or ESP pointing at the wrong end of the reserved area	Run with <code>-d int,cpu_reset -no-reboot</code> to see the fault; check <code>esp</code> in GDB before the call.
Linker: undefined reference to <code>memset</code> (or <code>memcpy</code>)	GCC emits these calls itself for struct copies and array initialisation, even when freestanding	Provide them in <code>lib/string.c</code> . They must exist in every kernel.
Linker: undefined reference to <code>__stack_chk_fail</code>	Host compiler with the stack protector enabled	Use the cross compiler (or add <code>-fno-stack-protector</code>).
Nothing appears on screen, no crash	Missing <code>volatile</code> , so the optimiser removed the stores	Declare the buffer pointer as <code>volatile uint16_t *</code> .
Serial output is garbled or missing	Wrong divisor or line settings, or not waiting for the transmitter	Re-check the register sequence; poll bit 5 of the line status register.
<code>%d</code> prints wrong values for negative numbers	Converting <code>INT_MIN</code> by negating an int overflows	Negate into an unsigned before converting.

6 Milestone

🚩 Milestone: The kernel can talk

- ☐ `kmain` runs on your own 16 KiB stack and receives the Multiboot magic and information pointer.
- ☐ The screen shows a coloured Turk-OS banner with the RAM size, and scrolling works.
- ☐ The same messages appear in your terminal through the serial port.

- ☐ kprintf passes the edge-case tests; panic and ASSERT print file and line and halt.
- ☐ The Makefile builds C and assembly, links with libgcc, and make run opens serial on stdio.

Self-check questions

1. Why must ESP be set before call kmain, and why does it point at the *end* of the reserved area?
2. Which does the VGA text buffer use, memory-mapped or port-mapped I/O? Which does the cursor use?
3. Why is stdarg.h available in a freestanding kernel when stdio.h is not?
4. What does __attribute__((packed)) do, and what would go wrong without it in multiboot_info?
5. Why might GCC call memcpy in a kernel that never calls it explicitly?
6. What is the serial divisor for 115 200 baud? For 9 600?

7 Going further

Add log levels (INFO, WARN, ERROR) with different colours on screen and a prefix on serial. Keep a copy of every message in a ring buffer in memory; in Phase 4 you can add a dmesg command that prints it. Turkish letters are worth a look too: code page 437 contains ç, ö, ü, Ç, Ö and Ü but not ğ, ş, ı, İ, Ğ or Ş. Write a small UTF-8 to CP437 converter for the letters that exist and substitute the rest for now. Phase 15 offers two ways to get full Turkish text: a custom VGA font, or a graphical framebuffer with your own font.

Next: **Phase 3 Segmentation, the IDT and CPU Exceptions** →

Books used in this plan

- LOB** Erik Helin, Adam Renberg. *The little book about OS development*, 2015. The hands-on x86 guide. Free at <https://littleosbook.github.io>.
- OSTEP** Remzi H. Arpaci-Dusseau, Andrea C. Arpaci-Dusseau. *Operating Systems: Three Easy Pieces*, v0.90, Arpaci-Dusseau Books, 2015. Main theory text. Free at <https://pages.cs.wisc.edu/~remzi/OSTEP/>.
- OSC** A. Silberschatz, P.B. Galvin, G. Gagne. *Operating System Concepts*, 10th ed., Wiley, 2018. Reference theory text.
- MOS** Andrew S. Tanenbaum, Herbert Bos. *Modern Operating Systems*, 4th ed., Pearson, 2015. Hardware, I/O, design, security.
- OSDI** Andrew S. Tanenbaum, Albert S. Woodhull. *Operating Systems: Design and Implementation*, 3rd ed., Pearson Prentice Hall, 2006. MINIX 3 with full source listing.

The books do not come with this plan. **LOB** and **OSTEP** are free online; buy or borrow the other three (the roadmap lists their ISBNs). Page numbers are the *printed* page numbers of these editions, not PDF page indices. With another edition, or with the free **OSTEP** chapters (each one starts at page 1), find the reading by its chapter and section numbers. MINIX source references like kernel/proc.c (07400) give the file and its starting line in **OSDI** Appendix B.