

## Wiring Connections

To set up the ISD1820 Voice Recorder module with your Arduino, make the following connections:

- **Power:** Connect the **VCC** pin on the ISD1820 module to the **5V** pin on the Arduino.
- **Ground:** Connect the **GND** pin on the module to any **GND** pin on the Arduino.
- **Playback Control:** Connect the **PLAYE** (Play Edge) pin on the module to digital **Pin 3** on the Arduino.
- **Record Control:** Connect the **REC** (Record) pin on the module to digital **Pin 4** on the Arduino.
- **Audio Output:** Connect your speaker wires directly to the **SP+** and **SP-** screw terminals (or pins) on the ISD1820 module.

## Required Libraries

- **No external libraries are required.** \* The code strictly uses the built-in standard Arduino functions (like digitalWrite and delay) to send digital pulses to the module's control pins. You just need the standard Arduino IDE installed to compile and upload the code.