Magnetic Force on a Current-Carrying Wire

Goal.

- See where the force on a current-carrying wire, $F = IlB\sin\alpha$, comes from — it's just $q\vec{v}\times\vec{B}$ summed over every moving charge in the wire.
- Use the right-hand rule both ways: given I and $\vec{B}$, find $\vec{F}$; and given the $\vec{F}$ you need, find the current direction that produces it.
- Work a full numerical example end to end: find the current that lets a wire "float" against gravity in a magnetic field (Example 29.13).

1. Where the force on a wire comes from

A current is moving charge. A short segment of wire, length Δx, carrying charge Δq with drift velocity $\vec{v}_{\mathrm{d}}$, feels the same magnetic force as any moving charge: $F = \Delta q\, v_{\mathrm{d}} B$. The charge crosses the segment in a time $\Delta t = \Delta x / v_{\mathrm{d}}$, so $\Delta q =$ _____ (in terms of I and Δt). Substituting:

$$F = \Delta q\, v_{\mathrm{d}} B = _____$$

Adding up every such segment over the full length l of wire (when the wire is perpendicular to $\vec{B}$) gives $F = IlB$. More generally, for a wire at angle α to the field:


$\vec{F}_{\mathrm{wire}} =$

Check. The box above should look just like the moving-charge force law $\vec{F} = q\vec{v}\times\vec{B}$, with two substitutions. What plays the role of q, and what plays the role of $\vec{v}$?

NOTE — Right-hand rule for a current-carrying wire: point your right _____ in the direction of the current (parallel to $\vec{l}$), your _____ in the direction of $\vec{B}$. Your _____ then points along $\vec{F}$.

2. Worked example: magnetic levitation (Example 29.13)

A uniform field $B = 0.10$ T is horizontal, parallel to the floor. A straight segment of 1.0-mm-diameter copper wire, also parallel to the floor, is perpendicular to the field. What current through the wire, and in which direction, will allow the wire to "float" in the magnetic field?



Label $\vec{B}$'s direction, and sketch in the current direction and $\vec{F}_B$ once you've worked out which way they go.

MODEL. The wire floats if the magnetic force on it points _____ and has magnitude _____, exactly balancing the downward gravitational force.

SOLVE — set the forces equal. With the wire perpendicular to $\vec{B}$:

$$F = IlB = _____$$

The weight comes from the copper's density $\rho = 8920$ kg/m^3 and the wire's volume. Write the mass as $m = \rho V$, with V the volume of a cylinder of radius r and length l:

$$IlB = _____$$

Check. One factor appears on both sides of that equation and cancels. Which one — and why should the current needed to float the wire *not* depend on how long the wire is?

Solve for the current:

$I =$

Plug in $r = 0.00050$ m, $g = 9.80$ m/s^2, and the given B and ρ:

$I =$

Direction. With $\vec{B}$ pointing into the page (as drawn), the right-hand rule says the current must flow _____ to make $\vec{F}_B$ point _____.

Check. The book notes this idea is only useful once you can get current into and out of the floating segment. If the lead-in wires run straight down to the segment (parallel to $\vec{B}$), why do *they* feel no force while the segment does?