

Max time: 10 Min
 ID No: _____


Name: _____

Max Marks: 08
 Sec No.: _____

1. From which address(s) is the IP of the NMI handler fetched by the 8086 processor? [2M]

00008H - 1M or 0008 - 1M or 0009 - 1M
00009H - 1M or 0008 - 1M

2. The base address of 8255 is DAh (Use DAh and next possible addresses in increasing sequence for 8255).. You wish to switch on a LED (as shown below) directly connected to PC6 of 8255 interfaced to 8086 using BSR mode.



- a. Fill in the blanks with 2 lines of code (only two instructions- no data declarations allowed) to configure 8255 in BSR mode

mov al, 10000000b [1M] (*take all don't care's as 0, mention values in hex only)

out FF, al [1M]
H

- b. Fill in the blanks with 2 lines of code that can be used to switch on LED connected to port PC6 (only two instructions- no data declarations allowed)

mov al, 00001101b [1M] (*take all don't care's as 0, mention values in hex only)

out FF, al [1M]

- c. What is the address of Port B DFH [1M]

- d. Which address line from 8086 will be connected to the following A1 pin of 8255. A5 [1M]

D ₇	D ₆	D ₅	D ₄	D ₃	D ₂	D ₁	D ₀
1 - I/O Mode	Port A Mode		Port A	Port C	Port B	Port B	Port C
	00 - Mode 0		1 - i/p	Upper	Mode	1 - i/p	Lower
	01 - Mode 1		0 - o/p	1 - i/p	0 - Mode 0	0 - o/p	1 - i/p
	1x - Mode 2			0 - o/p	1 - Mode 1		0 - o/p
Group A				Group B			

D ₇	D ₆	D ₅	D ₄	D ₃	D ₂	D ₁	D ₀					
0-BSR	x	x	x	Bit ₂	Bit ₁	Bit ₀	Bit Set/Reset					
Don't Care Condition				PC	0	1	2	3	4	5	6	7
				B ₀	0	1	0	1	0	1	0	1
				B ₁	0	0	1	1	0	0	1	1
				B ₂	0	0	0	0	1	1	1	1
				1 - Set 0 - Reset								

1101 1010

1101 1100