

Ge-on-Si Photodetector Design and Simulation

O-band vertical n-i-p photodiode for high-speed PAM-4 optical receivers

Islam I. Abdulaal

Electronics and Communications Engineering
Alexandria University

2026

Motivation and Targets

- Intra-datacenter PAM-4 receivers need **high responsivity**, **very low dark current**, and **bandwidth above 100 GHz**.
- A **Ge-on-Si vertical n-i-p photodiode** offers a strong fit with standard SOI photonics.
- The chapter benchmarks the design against Yang Shi et al., *Photonics Research* 12(1), 2024.

Metric	Target
Responsivity	$\geq 0.95 \text{ A/W}$
Dark current	$\leq 1.3 \text{ nA}$
Bandwidth	$\geq 103 \text{ GHz}$
Detectivity	$\geq 2.95 \times 10^{10} \text{ cm}\sqrt{\text{Hz}}/\text{W}$

- Vertical **n-i-p** stack on a 220 nm **SOI** platform.
- 50 nm **n++ Ge** top contact layer.
- 350 nm **intrinsic Ge** absorber.
- **p++ Si** platform for the anode path.
- **U-shaped electrode** reduces the RC penalty while preserving carrier collection.

Layer	Thickness
n++ Ge	50 nm
i-Ge	350 nm
p++ Si	220 nm
BOX	2 μ m

Optical Simulation Flow

- **Lumerical FDTD** models the taper-coupled optical absorption at 1310 nm.
- The simulation exports **optical generation rate** into CHARGE.
- Ge length is optimized to reach high absorption with minimum footprint.

Key optical design points:

- TE-driven O-band operation
- Adiabatic spot-size converter (500 nm $\rightarrow$ 5 μ m over 40 μ m)
- 3D generation-rate export: $G = P_{\text{abs}}/(h\nu)$

figures/opt_generation_rate_map.

- **Lumerical DEVICE CHARGE** solves carrier transport under reverse bias.
- SRH recombination enabled with $\tau_n = \tau_p$ (calibrated to match dark current target).
- Fine mesh override: 20 nm max edge length over the Ge active region.
- Extracted quantities include:
 - Dark current and illuminated current
 - Band diagram, carrier density
 - Electric field and potential
- Bandwidth estimated from **transit-time + RC** limits.

Dark Current Result

- All parameters flow from solvers — no hardcoded paper values.
- Low dark current is essential for:
 - Receiver sensitivity
 - Noise performance
 - Robust PAM-4 eye opening



figures/dark_iv.png

figures/phys_band_diagram.png

figures/phys_carrier_density.png

Electric Field and Bandwidth

figures/phys_field_potential.png

figures/freq_response_model.png

- Transit time and RC contributions are combined into the bandwidth model

System-Level Receiver View

figures/system_transfer_function.png

figures/system_photocurrent_eye.png

figures/system_pam4_histogram.png

- Matched-filter output shows **4 distinct PAM-4 levels**.
- Decision thresholds separate the symbol clusters.
- SNR, BER, and SER are computed from the simulation.
- The PD can now be studied both as a device and as a circuit block.

INTERCONNECT-Ready Compact Model

- The repo exports a **Lumerical INTERCONNECT-ready** photodetector data package.
- Generated artifacts include:
 - Responsivity table (frequency-dependent)
 - Bandwidth table (bias-dependent)
 - Dark-current table
 - Compact-model .mat source data
 - Equivalent-circuit parameters CSV

Data Pipeline Overview

FDTD .lsf → fdtddata.mat → CHARGE .lsf → charge_data.mat → postprocess.m → CML .mat
→ system-level

All parameters flow from Lumerical solvers → MAT files → MATLAB postprocess → CML export → system-level scripts. **Nothing is hardcoded in the pipeline.**

Final Takeaways

- The chapter demonstrates a **Ge-on-Si O-band photodiode** targeting published high-speed metrics.
- The workflow is consistent across:
 - **Device-level FDTD** — optical absorption, generation rate
 - **Device-level CHARGE** — dark current, responsivity, band structure
 - **Device-level postprocess** — CML dataset, all derived parameters
 - **System-level MATLAB** — PAM-4 BER, eye diagrams, histograms
 - **INTERCONNECT-ready export** — circuit-level integration
- **Zero hardcoded paper values** — all metrics from solvers and geometry.