

Exp No: 4

7 SEGMENT DISPLAY USING AT89C51 USING PROTEUS

AIM:

To write an assembly language program for 7 Segment Display Using AT89C51 using Keil and Proteus

PROGRAM:

```
ORG 000H
UP:MOV
P2,#0C0H
ACALL
DELAY MOV
P2,#0F9H
ACALL
DELAY MOV
P2,#0A4H
ACALL
DELAY MOV
P2,#0B0H
ACALL
DELAY MOV
P2,#99H
ACALL
DELAY MOV
P2,#92H
ACALL
DELAY MOV
P2,#82H
ACALL
DELAY MOV
P2,#0F8H
ACALL
DELAY MOV
P2, #80H
ACALL
DELAY MOV
P2,#90H
ACALL
DELAY
```

```

DELAY: MOV
R5,#10 H1:MOV
R4,#180
H2:MOV
R3,#255
H3:DJNZ R3,H3
DJNZ R4,H2
DJNZ
R5,H1
RET
END

```

