

- Under no circumstances are traffic controllers to stand or operate unprotected in a lane carrying traffic.
- Traffic controllers are to only communicate with a road user once the vehicle has stopped and is safe to do so.

Replace the following dot point:

- ~~Ensure a single traffic controller never controls more than one lane of traffic or more than one approach. A single traffic controller can operate two PTSS at one time in special circumstances.~~

with

- A single traffic controller must never control more than one lane of traffic or more than one approach when using a STOP/SLOW bat or a PTCD. This may only be varied where a traffic controller is using a PTCD which is capable of alternative arrangements and both the device and manner of operation is approved by the department. See Section 2.6.2 of AGTTM Part 7 for additional requirements and considerations when designing and using PTCDs for traffic control.
- Provide a traffic controller at intersections to guide road users entering from a side road.
- Some intersections require three or more traffic controllers. Where multiple traffic controllers are used they are required to:
 - ensure that road users are not seeing conflicting message from other traffic controllers at different locations of the worksite
 - be in continuous radio contact with each other when they are not visible to each other.

For detailed guidance on traffic controllers see AGTTM Part 7.