

JP1, JP3, JP5: Install for attenuverter (gain from -1 to $+1$), remove for straight attenuator (gain from 0 to $+1$)

JP2, JP4, JP6: Install to normal inputs to $+5.0V$, remove to normal inputs to Ground

For best audio performance: Do not install any jumpers, do not install C1 – C4, use your favorite audio-quality op-amps, use audio-taper pots.

For best CV performance: use 0.1% for all 120K and 200K resistors, install 47pF caps at C1 – C4, and change C5 to 47pF

For acceptable performance for both: use 0.1% for all 120K and 200K resistors, install 22pF caps at C1 – C4, use \$5 op amps

