

Exterior rear view mirror switch (continued)

Component testing procedure

Circuit to test	Connect self-powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Left mirror		Selector switch left	
Up	6 and 3 5 and 1	Up	Closed circuit
Down	1 and 6 5 and 3	Down	Closed circuit
Left	3 and 8 1 and 6	Left	Closed circuit
Right	6 and 3 1 and 8	Right	Closed circuit
Right mirror		Selector switch right	
Up	2 and 1 6 and 3	Up	Closed circuit
Down	1 and 6 2 and 3	Down	Closed circuit
Left	6 and 1 7 and 3	Left	Closed circuit
Right	1 and 7 6 and 3	Right	Closed circuit
Folding mirrors (if equipped)		Selector switch center	
Power mirror fold in	4 and 3	Down	Closed circuit
Power mirror fold out	4 and 1	Up	Closed circuit

