

BYTESMITH

Introduction to ESP32

GPIO, wireless connectivity, and a first digital output

IoT / Embedded Systems

Printable lesson edition - Updated September 14, 2026

LEARNING OBJECTIVES

- Describe an ESP32 and its development board
- Explain GPIO and digital I/O
- Identify the roles of Wi-Fi and Bluetooth
- Prepare Arduino IDE for an ESP32 board
- Reason through a safe LED blink circuit

1. The ESP32 platform

ESP32 refers to a family of microcontrollers used in embedded and connected projects. Devices combine processing, memory, timers, communication peripherals, Wi-Fi, and Bluetooth.

A development board makes the chip easier to use by adding USB connectivity, voltage regulation, reset and boot controls, and accessible header pins.

2. GPIO and voltage

GPIO means General-Purpose Input/Output. A supported pin can read a digital state, drive a digital output, or carry a peripheral signal such as UART, SPI, or I2C.

ESP32 GPIO normally uses 3.3 V logic and is not generally 5 V tolerant. Pin capabilities vary. Always check the exact board pinout before wiring.

3. Wi-Fi and Bluetooth

Wi-Fi lets an ESP32 join an IP network, exchange data with services, or provide a local web interface. Bluetooth supports short-range device communication, including low-energy use cases on supported chips.

4. Arduino IDE workflow

Install the current Arduino IDE and Espressif board support, connect a data-capable USB cable, then select the exact board and serial port. Verify the sketch before upload. A charge-only cable can power a board without providing the data path required for uploads.

5. Basic LED example

The program configures a pin as an output. It drives the pin HIGH, waits, drives it LOW, and waits again. An external LED needs correct polarity and a suitable current-limiting resistor.

```
const int ledPin = 2;

void setup() { pinMode(ledPin, OUTPUT); }

void loop() {
  digitalWrite(ledPin, HIGH); delay(500);
  digitalWrite(ledPin, LOW); delay(500);
}
```

6. Safe troubleshooting

Disconnect power before changing wires. If upload fails, check the cable, board selection, serial port, and board-specific boot procedure. If an LED does not blink, verify the code's pin number, pinout, LED polarity, resistor, and ground. If the board resets, remove the external circuit and inspect for shorts or unstable power.

Quick reference

Concept	Meaning
ESP32	A connected microcontroller family with Wi-Fi and Bluetooth.
Development board	An ESP32 module plus convenient USB, power, controls, and headers.
GPIO	Software-configurable general-purpose input/output pins.
HIGH / LOW	The two logical states of a digital signal.
pinMode	Configures a pin for input, output, or another supported mode.
digitalWrite	Sets a digital output HIGH or LOW.
Resistor	Limits current through the LED and GPIO circuit.
Data USB cable	Carries both power and the data needed to upload code.

Continue online for flashcards, practice questions, the interactive quiz, and the next lesson.