

68030 Memory Decoding

					Long Word Port				Worc
S1	S0	A1	A0	FIELD	LL (D31:24)	LH (23:16)	UL (15:8)	UH (7:0)	W_LL (D31:24)
LONG WORD	0	0	0	0	X	X	X	X	X
	0	0	0	1		X	X	X	
	0	0	1	0			X	X	X
	0	0	1	1				X	
BYTE	0	1	0	0	X				X
	0	1	0	1		X			
	0	1	1	0			X		X
	0	1	1	1				X	
WORD	1	0	0	0	X	X			X
	1	0	0	1		X	X		
	1	0	1	0			X	X	X
	1	0	1	1				X	
3 BYTE	1	1	0	0	X	X	X		X
	1	1	0	1		X	X	X	
	1	1	1	0			X	X	X
	1	1	1	1				X	

```

LL    (!A0 & !A1)
LH    !((A1 # (!A0&S0&!S1)))
UL    !(((!A1&S0&!S1) # (A2&A1) # (!A0&!A1&!S0&S1)))
UH    ((A1&S1) # (!S1&!S0) # (A0&S1&S0) # (A0&A1))

W_LL  !A0
W_LH  !(!A0&S0&!S1)
B_LL  d'1

```


I Port	Byte Port
W_LH (23:16)	B_LL (D31:24)
X	X
X	X
X	X
X	X
	X
X	X
	X
X	X
X	X
X	X
X	X
X	X
X	X
X	X
X	X
	f
f(0,1,2,3,5,, 7,8,9,10,11,12,13,14,15)	(0,1,2,3,4,5,6,7,8,9,1 0,11,12,13,14,15)

