Conflict Serializability Exercises

For each schedule, determine whether it is conflict serializable using the swapping method and the precedence graph method.

Schedule 1

Time	T1	T2
1		R(A)
2	R(B)	
3		R(C)
4		R(B)
5		W(C)
6	W(B)	
8		W(A)
9	R(A)	
10	W(A)	

Or in string format:

R2(A), R1(B), R2(C), R2(B), W2(C), W1(B), W2(A), R1(A), W1(A)

Schedule 2

Time	T1	T2	T3
1	R(A)		
2			R(B)
3	R(B)		
4		R(A)	
5		W(A)	
6			W(B)
7	W(B)		
8	W(A)		
9			R(A)
10			W(A)

Or in string format:

R1(A), R3(B), R1(B), R2(A), W2(A), W3(B), W1(B), W1(A), R3(A), W3(A)

Schedule 3

Time	T1	T2	T3
1	R(A)		
2	R(B)		
3		W(A)	
4	W(B)		
5	W(A)		
6			W(A)

Or in string format:

R1(A), R1(B), W2(A), W1(B), W1(A), W3(A)

Schedule 4

Time	T1	T2
1	R(A)	
2	R(B)	
3		W(A)
4	W(B)	
5	W(A)	

Or in string format:

R1(A), R1(B), W2(A), W1(B), W1(A)

Schedule 5

Time	T1	T2	T3
1		R(A)	
2		R(B)	
3		W(B)	
4			R(B)
5			R(A)
6	R(C)		
7	W(C)		
8			W(B)
9			W(A)
10		R(C)	
11	R(B)		
12	W(B)		
13		W(C)	

Or in string format:

R2(A), R2(B), W2(B), R3(B), R3(A), R1(C), W1(C), W3(B), W3(A), R2(C), R1(B), W1(B), W2(C)

Schedule 6

R2(A), R2(B), W2(B), R2(C), W2(C), R3(B), R3(A), R1(C), W1(C), W3(B), W3(A), R1(B), W1(B)s