Two Phase Locking Exercises

For each schedule, write the two-phase locking steps as we discussed in class.

Show the resulting dependence graph of the conflict serializable schedule it produces.

Schedule 1

$W_1(A), R_2(A), W_1(B), R_2(B)$

Schedule 2

$W_1(A), R_2(A), W_2(B), R_1(B)$

Schedule 3

$R_1(A), R_2(A), W_3(A), R_1(B)$

Schedule 4

$R_1(A), W_2(A), W_1(A)$

Schedule 5

$W_1(A), R_2(A), W_2(B), R_3(B), W_3(C), R_1(C)$