COLLECTION OF CTL DECISIONS

Standard:	**Sub clause:**	**Sheet n. 314**
IEC 61010-1:1990+A1:1992+A2:1995	14.7	**Page 1(1)**
Subject:	**Key words:**	**Decision taken by ETF3 and confirmed by CTL at its 38th meeting, in Toronto**
Mains transformers	- Isolation - Transformer	

Question:

What isolation and loading requirements are applied to auto transformers?

Decision

Tests for loading are applied when applicable as for isolation transformers. No isolation requirements are applied between voltage outlets, however, care must be taken to ensure that circuits separated by voltages are suitably isolated form one another to prevent short circuit of the intervening winding.

Explanation

Auto transformers are subject to overheating tests in the same way as isolating transformers, however, they are not designed to provide isolation and these requirements are, therefore, not applicable as there is direct connection between circuits.

It is important that circuit which do not have a common voltage line are adequately separated such that no short circuit of the intervening windings on the autotransformer can occur.