

Engineering Standards: Why They Matter and How to Use Them

Training Guide for Senior Electrical & Computer Engineering Students

Practical + ethical guidance for selecting, finding, and applying standards

Standards are one of the hidden superpowers of engineering. They let products interoperate, make performance claims comparable, and keep safety and reliability from becoming optional. If you've ever plugged a USB device into a laptop, connected to Wi-Fi, used Ethernet, or shared a floating-point number between two systems, you benefited from standards.

This guide explains (1) why standards exist, (2) the ethics around standards, (3) where to find them, (4) how to choose which standard to follow, and (5) why "let's invent our own protocol" is often a costly trap.

Big Picture: Key takeaway in one line

Standards turn your design from "works in our lab" into "works in the real world, with other people's systems."

1. What Standards Are (and Why Engineers Keep Reusing Them)

A technical standard is a published specification or procedure agreed upon by a community—industry, academia, and often government—to make systems reliable, safe, and interoperable. Standards can define electrical characteristics, protocol behavior, file formats, testing methods, terminology, and more. IEEE describes standards as documents that establish technical specifications and procedures to maximize reliability [1]. NIST highlights that technical standards keep us safe and enable technology to advance [2].

1.1 Why Standards Exist (the short list)

- Interoperability: different vendors can build compatible devices.
- Safety and reliability: proven requirements reduce preventable failures.
- Efficiency: you do not reinvent solved problems; you build on mature interfaces.
- Fair comparison: metrics and test methods become consistent.
- Trust and adoption: customers, regulators, and partners can evaluate compliance.

Rule: If you remember nothing else...

Standards reduce ambiguity.

Ambiguity is where bugs, safety incidents, and expensive integration failures hide.

2. Types of Standards You will Encounter

Not every standard looks the same, and not every organization publishes standards in the same way. Knowing the category helps you find the right document and understand how strongly it is expected to be followed.

2.1 De jure vs de facto vs consortium

- Formal standards bodies: IEEE, ISO/IEC, IEC (often called “de jure” standards).
- Internet standards: IETF RFCs (many are Internet Standards or Best Current Practice) [3].
- Industry consortia specifications: USB-IF (USB), PCI-SIG (PCI Express), JEDEC (memory interfaces).
- De facto standards: widely adopted specifications that become “standard” due to market dominance (still risky if undocumented).

Guidance: Practical implication

If a standard affects safety, security, or regulatory compliance, prefer formal standards and widely recognized consortia specs.

If it is internal-only, you might use a lightweight spec—just do not confuse that with a true external standard.

3. The Ethics Around Standards

Standards are not only technical. They are ethical tools because they influence safety, fairness, and trust. Ignoring relevant standards can expose users to harm, create hidden risks, or mislead stakeholders. Professional responsibilities include knowing when standards apply, following them, and communicating limitations honestly.

3.1 Why standards are an ethics issue

- Safety: standards often encode hard-earned lessons from failures and incidents.
- Security: standard protocols often come with threat models, vetted mechanisms, and compliance tests.
- Fairness and access: standards can prevent exclusion (e.g., accessibility and interoperability requirements).
- Honest communication: claiming compatibility or performance without standard methods can mislead users.

Red Flag: Ethical warning label

If you choose not to follow a relevant standard, you should be able to explain why—and what risks you are accepting.

4. How Standards Get Made (and Why That Matters to You)

Standards are usually produced through consensus processes with review, revision, and balloting. The IEEE Standards Association describes itself as a consensus-building organization that develops and advances technologies through standards [4]. IETF's RFC series documents Internet specifications and practices, with structured statuses and updates/obsoletions [3]. In practice, this means standards evolve, and engineers must track versions and errata.

4.1 Versions, revisions, and errata

- A standard is not a single forever-document; it evolves via revisions and amendments.
- Errata/ECNs (engineering change notices) often clarify mistakes or edge cases.
- Your design should reference the exact version used (e.g., "PCIe Base Spec Rev 7.0").

Habit: Professional habit

Always write the standard name + version in your design docs and test plans.

Example: "IEEE 1800-2023 (SystemVerilog) used for RTL/testbench language definition." [5]

5. How to Find Standards (Fast, Legally, and Reliably)

Senior engineers do not memorize standards; they know how to find them quickly and verify they are using the correct version. Below is a practical map of where to look.

5.1 Common places to search

- IEEE Standards Association catalog (IEEE Std pages) [1][4][5][6].
- IETF RFC repository (many documents are freely accessible) [3].
- USB-IF document library for USB specifications and related compliance materials [7][8].
- PCI-SIG specification pages for PCI Express and related standards [9][10].
- ISO and IEC catalogs for international standards (many require purchase or institutional access) [11][12].
- NIST standards resources and guidance on finding standards [2].

5.2 Practical ‘search recipe’ you can reuse

- Start with the interface name + the standards body (e.g., “IEEE 1800 SystemVerilog”, “PCI-SIG PCI Express Base”).
- Confirm the document title, revision number, and publication date on the official page.
- Look for errata/updates, especially for protocols and safety standards.
- If the PDF is behind a paywall, use your university library (i.e., IEEE Xplore, institutional subscriptions, etc.) rather than random re-uploads.

Security: Avoid sketchy PDFs

Unofficial uploads can be outdated, incomplete, or illegally distributed.

Use official sources or your institution’s library access whenever possible.

6. How to Choose Which Standard to Use

Choosing a standard is a design decision. The best standard is not always the newest, and not always the most feature rich. It is the one that fits your system constraints, ecosystem, and compliance needs.

6.1 A decision checklist

- Scope fit: does the standard address your problem (layers, environment, constraints)?
- Ecosystem: are there mature chips, IP, tools, test gear, and reference designs?
- Interoperability goals: who must your system work with (vendors, operating systems, test frameworks)?
- Compliance and certification: does your product need certification (e.g., USB compliance program) [8]?
- Longevity: will this standard still be supported during your product lifecycle?
- Complexity budget: can your team implement it correctly (time, expertise, verification)?

Warning: Most common mistake

Picking a standard by popularity alone without checking scope and compliance requirements.

Example: ‘We used USB-C’ is not enough—USB-C connectors can carry different protocols and power roles.

7. How to Read a Standard Without Getting Lost

Standards can be dense. The trick is to read them like engineers read datasheets: locate the parts that define behavior, interfaces, and requirements first—then return for edge cases.

7.1 A practical reading approach

- Start with the overview and scope: what is in and out.
- Identify ‘shall’ statements (requirements) vs ‘should/may’ (recommendations/options).
- Find state machines, timing diagrams, electrical limits, and compliance tests.
- Build a ‘requirements-to-test’ table: each requirement gets a verification method.
- Track assumptions and optional features explicitly.

Mindset: A verification mindset

A standard is not implemented until it is tested.

If you cannot explain how you will test compliance, you do not fully understand the requirement.

8. Why You Should Avoid Non-Standard Protocols (Most of the Time)

Students often say: “Let’s invent our own protocol—it’ll be simpler.” Sometimes it is simpler in week 1. By week 6, custom protocols usually create integration pain, untested corner cases, and debugging overhead.

8.1 The costs of ‘rolling your own’

- Interoperability risk: your system will not work with existing tools/devices without adapters.
- Maintenance burden: you become the standards body (documentation, updates, compatibility).
- Security risk: ad-hoc protocols rarely have mature threat modeling.
- Testing gap: no existing compliance test suites or certified equipment.
- Hiring/hand-off risk: new team members will not have shared expectations.

Reality: A reality check

A custom protocol is an engineering product, not a quick hack. If you do not have time to standardize it, you do not have time to maintain it.

8.2 When a custom protocol can be reasonable

- Internal prototypes where interoperability is not required and risk is low.
- Research experiments where the goal is exploring new ideas (and you document clearly).
- Ultra-constrained environments where no existing standard fits (still document and test).

Even then, good teams design custom protocols with a future migration path to standards: clear versioning, framing, error detection, and transparent documentation.

9. Concrete Examples in EE/CE You Already Know

Here are standards you have likely encountered, whether you realize it or not. Seeing real examples makes the idea less abstract.

9.1 IEEE examples

- IEEE 802.11: Wi-Fi standards and evolution [13].
- IEEE 802.3: Ethernet standard family (management and related specifications) [14].
- IEEE 754: floating-point arithmetic formats and rules (critical for portability) [6].
- IEEE 1800 (SystemVerilog): unified hardware design and verification language definition [5].

9.2 Industry consortium examples

- USB specifications and document library (USB-IF) [7] and compliance program [8].
- PCI Express Base specification (PCI-SIG) and revision tracking [10].

9.3 Safety standards examples (systems that can harm people)

- IEC 61508: functional safety for electrical/electronic/programmable electronic systems (framework and SIL concept) [15][16].
- ISO 26262: functional safety for road vehicles (hazards from malfunctioning E/E systems) [11].

Note: Why these examples matter

They show that standards are not just ‘paperwork’—they define how real systems stay compatible and safe.

10. How to Reference Standards in Your Reports and Design Docs

In professional engineering documents, you reference standards like you reference datasheets: precisely.

- Use the full standard name and number (e.g., “IEEE Std 754-2019”).
- Include the revision year/version.
- If your design relies on a specific clause or table, cite the clause number.
- State assumptions and optional features explicitly (what you implemented and what you did not).

Template: Example reference sentence

“Our RTL follows IEEE Std 1800-2023 for SystemVerilog syntax and semantics.” [5]

Closing: A Professional Standard of Behavior

Following standards is not about limiting creativity. It is about choosing where to innovate. Standards let you innovate on the parts that matter—while relying on shared, tested foundations for interfaces, safety, and interoperability.

Takeaway: Final thought

In senior design, internships, and your first job: knowing how to find and use standards will make you faster, safer, and more credible.

References

- [1] IEEE Standards Association, "What are Standards? Why are They Important?"
<https://standards.ieee.org/beyond-standards/what-are-standards-why-are-they-important/>
- [2] NIST, "Learn More About Standards."
<https://www.nist.gov/standardsgov/learn-more-about-standards>
- [3] IETF, "About RFCs."
<https://www.ietf.org/process/rfc/>
- [4] IEEE Standards Association, "About IEEE SA."
<https://standards.ieee.org/about/>
- [5] IEEE SA, "IEEE 1800-2023 (SystemVerilog)."
<https://standards.ieee.org/ieee/1800/7743/>
- [6] IEEE SA, "IEEE 754-2019 (Floating-Point Arithmetic)."
<https://standards.ieee.org/standard/754-2019.html>
- [7] USB-IF, "Document Library."
<https://www.usb.org/documents>
- [8] USB-IF, "Compliance Program."
<https://www.usb.org/compliance>
- [9] PCI-SIG, "Specifications."
<https://pcisig.com/specifications>
- [10] PCI-SIG, "PCI Express Base Specification Overview (current revisions)."
<https://pcisig.com/specification-overview/pci-express-base>
- [11] ISO, "ISO 26262-1:2018 Road vehicles — Functional safety (overview page)."
<https://www.iso.org/standard/68383.html>
- [12] ISO, "ISO/IEC JTC 1 — Information Technology (committee scope)."
<https://www.iso.org/committee/45020.html>
- [13] IEEE SA, "The Evolution of Wi-Fi Technology and Standards (IEEE 802.11)."
<https://standards.ieee.org/beyond-standards/the-evolution-of-wi-fi-technology-and-standards/>
- [14] IEEE SA, "IEEE 802.3 standard page (Ethernet family example)."
<https://standards.ieee.org/ieee/802.3/10422/>
- [15] IEC, "Functional safety (IEC 61508 overview)."
<https://www.iec.ch/functional-safety>
- [16] IEC, "IEC 61508 & Functional Safety (overview PDF)."
<https://assets.iec.ch/public/acos/IEC%2061508%20%26%20Functional%20Safety-2022.pdf?2023040501=>

Final Practice Questions

These questions assess knowledge of multiple topics regarding engineering standards.

Practice Quiz

Answer these right after the reviewing this guide. These are practice (not graded).

1. According to the guide, what is the "hidden superpower" of engineering standards?

- A) They allow engineers to bypass government regulations.
- B) They enable interoperability, comparable performance claims, and consistent safety.
- C) They ensure that every product is designed with the exact same internal components.
- D) They eliminate the need for any testing or verification phases.

2. Which of the following is categorized as a "de jure" or formal standards body?

- A) USB-IF
- B) PCI-SIG
- C) ISO/IEC
- D) A company's internal lightweight specification

3. Why are standards considered an "ethical issue" for engineers?

- A) Because they are legally required in every country globally.
- B) Because they encode hard-earned lessons from past failures and influence user safety and trust.
- C) Because they prevent competitors from entering the market.
- D) Because standard documents are often expensive to purchase.

4. What is the recommended "professional habit" when referencing a standard in design documents?

- A) Use only the common name (e.g., "Wi-Fi").
- B) Reference the most popular version, regardless of what was used.
- C) Always include the full standard name plus the specific version or revision year.
- D) Only cite the standard if the project is being audited.

5. If a student wants to find an IETF RFC (Internet standard) legally and for free, where should they look?

- A) A random PDF re-upload site.
- B) The IETF RFC repository.
- C) The ISO catalog.
- D) The USB-IF document library.

6. When choosing a standard, why is it a mistake to pick one based on "popularity alone"?

- A) Popular standards are always too expensive.
- B) Popularity does not guarantee the standard fits your specific scope, layers, or compliance needs.
- C) Popular standards are usually outdated.
- D) Popular standards do not have mature toolchains.

7. In the context of reading a standard, what is the significance of the word "shall"?

- A) It indicates an optional feature.
- B) It indicates a recommendation for future versions.
- C) It indicates a mandatory requirement.
- D) It indicates a section that is out of scope.

8. According to the guide, what is a major "hidden cost" of inventing a custom protocol instead of using a standard?

- A) It makes the initial week of design too difficult.
- B) You become responsible for all documentation, updates, and maintenance (the "standards body").
- C) It is always more expensive to implement than a standard.
- D) Custom protocols are never allowed in research environments.

9. Which standard would you reference if you were working on functional safety for road vehicles?

- A) IEEE 802.11
- B) IEEE 754
- C) ISO 26262
- D) IEC 61508

10. What is the "verification mindset" regarding standards?

- A) A standard is considered implemented only after it has been tested.
- B) Standards should only be verified by third-party auditors.
- C) Testing is only required if you use a custom protocol.
- D) If a standard is popular, it can be assumed to work without testing.

Answer Key (Self-Check)

Use this key only after attempting the practice quiz.

1. B
2. C
3. B
4. C
5. B
6. B
7. C
8. B
9. C
10. A