» Residual

so we need to optimize:

· Jawbian

$$\frac{\partial r_q}{\partial \delta \theta_{b;b'}} = \frac{\partial \mathcal{L} q_{b;b'}^* \otimes (q_{wb;} \otimes (\frac{1}{2} \delta \theta_{b;b'}))^* \otimes q_{wb;} J_{xyz}}{\partial \delta \theta_{b;b'}}$$

$$\frac{\partial r_{gb}}{\partial \delta \rho_{wbi}} = \frac{\partial r_{q}}{\partial \delta \rho_{wbj}} = \frac{\partial r_{gb}}{\partial \delta \theta_{bbi}} = \frac{\partial r_{qb}}{\partial \delta \theta_{bbi}} = 0$$

$$\frac{\partial \mathcal{L}_{g_b}}{\partial \delta b_{g_j}} = \frac{\partial b_{g_j} + \delta b_{g_j} - b_{g_j}}{\partial \delta b_{g_j}} = \mathcal{I}$$

where
$$x_{k} = \begin{pmatrix} \delta \alpha_{k} \\ \delta \theta_{k} \end{pmatrix}$$
 $x_{k+1} = \begin{pmatrix} \delta \alpha_{k} \\ \delta \theta_{k} \end{pmatrix}$ $w_{k} = \begin{pmatrix} n_{\psi_{k}} \\ n_{\psi_{k+1}} \end{pmatrix}$

$$\begin{array}{ll}
\partial \dot{\theta} = -\left[u_{k} - b_{w_{k}} J_{x} \delta \theta + n_{w} - \delta b_{wt} \right] \\
\delta \dot{\theta}_{k} = -\left[\frac{w_{k} + w_{k+1}}{2} - b_{w_{t}} J_{x} \delta \theta_{k} + \frac{n_{w_{k}} + n_{w_{k+1}}}{2} - \delta b_{w_{k}} \right] \\
\delta \dot{\theta}_{k+1} = \left(J - \left[\frac{w_{k} + w_{k+1}}{2} - b_{w_{k}} J_{x} \delta t \right] \delta \theta_{k} + \frac{n_{w_{k}} + n_{w_{k+1}}}{2} \delta t - \delta b_{w_{k}} \delta t
\end{array}$$

(1)
$$\alpha_{bib_{k+1}} = \alpha_{bib_{k}} + q_{bib_{k}} \theta_{k}$$
 $\widehat{\alpha}_{bib_{k+1}} = \widehat{\alpha}_{bib_{k}} + \widehat{q}_{bib_{k}} \widehat{\theta}_{k}$
 $\widehat{\alpha}_{bib_{k+1}} = \alpha_{bib_{k+1}} + \delta \alpha_{bib_{k+1}}$
 $\widehat{\alpha}_{bib_{k}} = \alpha_{bib_{k}} + \delta \alpha_{bib_{k}}$

$$\widehat{R}_{b,b_k} = R_{b,b_k} \exp([\underline{S}\theta_k]_x) = R_{b,b_k} (\underline{I} + [\underline{I}\theta]_x)$$

$$\widehat{\theta}_k = \theta_k + n_{d_k}$$

 $\alpha_{b_1b_{k+1}} + \delta \alpha_{b_1b_{k+1}} = \alpha_{b_1b_k} + \delta \alpha_{b_1b_k} + R_{b_1b_k} (I + [\delta \theta_k]_x)(\theta_k + n_{\theta_k})$ $\alpha_{b_1b_k} + R_{b_1b_k} \theta_k + \delta \alpha_{b_1b_{k+1}} = \alpha_{b_1b_k} + \delta \alpha_{b_1b_k} + R_{b_1b_k} (I + [\delta \theta_k]_x)(\theta_k + n_{\theta_k})$ $\delta \alpha_{b_1b_{k+1}} = \delta \alpha_{b_1b_k} + R_{b_1b_k} (I + [\delta \theta_k]_x)(\theta_k + n_{\theta_k})$ $- R_{b_1b_k} \theta_k$

$$3 \int b_{w} = n_{bw}$$

$$5 b_{wk} = n_{bw}$$

$$5 b_{wk} = 5 b_{wk} + n_{bw} = 5$$

$$\hat{F}_{k} = \begin{pmatrix} I & -R_{k}[\varphi_{k}]_{x} & O \\ O & I - I \frac{\omega_{k} + \omega_{k+1}}{2} - b_{\omega_{k}}J_{x}\Delta t & -I\Delta t \\ O & O & I \end{pmatrix}$$

$$C_{k} = \begin{pmatrix} R_{k} & O & O & O \\ O & \frac{1}{2}I\Delta t & \frac{1}{2}I\Delta t & O \\ O & O & I\Delta t \end{pmatrix}$$