

JavaScript Project – Mini E-Commerce Website

Project Overview

Create a complete **Mini E-Commerce Website** using:

The project should contain **4 pages** and have a modern and attractive design.

You may use:

- Bootstrap
 - Bootstrap Carousel
 - Bootstrap Icons
 - Font Awesome
 - Google Fonts
-

Required Pages

1. Landing Page (Home)

The home page should contain:

- Header and navigation bar.
- Hero section with title and description.
- Carousel / Slider for offers or featured products.
- Featured products section.
- Categories section.
- Footer.

JavaScript Ideas:

- Auto slider or Bootstrap Carousel.
- Buttons to navigate to products.
- Dynamic rendering of featured products.

2. Products Page

This page contains all products.

Each product card should display:

- Product image
- Product name
- Description
- Price
- Category

- Add to Cart button

JavaScript Requirements:

- Display products dynamically using JavaScript.
- Store products inside an Array of Objects.

Example:

```
{  
  id: 1,  
  title: "Laptop",  
  price: 25000,  
  image: "image.jpg",  
  category: "Electronics"  
}
```

- Allow searching for products.
 - Allow filtering by category.
 - Allow sorting by price or name.
-

3. About Us Page

This page should contain:

- Company information.
- Vision and mission.
- Contact information.

Use good design, images, colors, spacing, and suitable fonts.

4. Dashboard Page (Admin Panel)

Create a dashboard for the Admin.

The admin should be able to perform:

Product Management

- Add Product
- Edit Product
- Delete Product
- Search Product

User Management

- Add User
- Edit User
- Delete User
- Search User

The dashboard should display:

- Total Products
 - Total Users
 - Total Orders (Optional)
-

Authentication System

Create two forms:

Register

User enters:

- Name
- Email
- Password

Save users in Local Storage.

Login

User enters:

- Email
- Password

Check if the user exists.

If login is successful:

- Save current user.
 - Redirect to home page.
-

Cart System (Required Logic)

The cart is one of the most important parts of the project.

Do not build it randomly. Follow the logic below:

Step 1

Create an array called:

```
let cart = [];
```

Step 2

When the user clicks "Add to Cart":

- Check if the product already exists in the cart.

If the product does not exist:

```
quantity = 1
```

If it already exists:

```
quantity++
```

Step 3

Save cart data in:

localStorage

Step 4

Display cart items dynamically.

Each item should contain:

- Image
 - Name
 - Price
 - Quantity
 - Total price
-

Step 5

User can:

- Increase quantity (+)
 - Decrease quantity (-)
 - Remove product
-

Step 6

Calculate:

Subtotal

Tax (Optional)

Shipping (Optional)

Final Total

Admin Dashboard Logic

Products

```
Add Product
↓
Save
↓
Display Products
↓
Edit Product
↓
Update
↓
Delete Product
↓
Refresh UI
```

Users

```
Add User
↓
Save
↓
Display Users
↓
Edit User
↓
Delete User
```

↓
Refresh UI
