

Next check: does RC2 drive the Q7 input?

V064-V070 = 11.2 kohm, matching R18 1.2k + R19 10k. The direct VDD assumption is withdrawn.

Battery and programmer disconnected. Report actual resistance, OL or changing. Compare near-zero readings with your probe/contact baseline and reverse probes to check. A beep alone is not proof of a direct connection.

Test	Fixed probe	Moving probe	What this tests	Reading / reversed if low
D1	V070	V049	R18 input to PIC13/RC2 (unmeasured candidate)	_____

Why this pair: the photo and 11.2 kohm reading support R18 as a series input to Q7, with R19 pulling its base toward VDD. RC2 is one of two GPIOs without a mapped destination. This checks a plausible receiver-enable route; it is not a traced or proven connection.

A - V070: R18 control-input candidate



B - V049: PIC pin13 / RC2



A near-baseline reading would support RC2 as the control source. If not direct, the next alternative is V070 to V026 (PIC21/RB0). Neither pin is assigned by elimination. Report actual ohms, OL or a changing reading.

Rear mosaic is already mirrored to match the front. Circles mark vias; leaders are annotations, not traces. Use board landmarks and the paired photo locator to zoom. The completed V064-V070 reading is resistive, not direct continuity.

No more capacitor sweeps. Q7 local topology is inferred from photo + resistance; the remote control route is unmeasured.