The next step is to split away a multiple of

$$\begin{tikzcd} \bullet_{0} \arrow[r] & \overset{1}{\bullet} & \bullet_{0} \arrow[l] \\ & \bullet_{0} \arrow[u] & \end{tikzcd}$$

to reach a situation where

$$V_1 + V_2 + V_3 = V.$$

By letting $Y = V_1 \cap V_2 \cap V_3$, choosing a complement V' of Y in V, and setting $V_i' = V' \cap V_i$, $i = 1, 2, 3$, we can decompose this representation into

$$\begin{tikzcd} \bullet_{V_1'} \arrow[r, hook] & \overset{V'}{\bullet} & \bullet_{V_3'} \arrow[l, hook'] \\ & \bullet_{V_2'} \arrow[u, hook] & \end{tikzcd} \oplus \begin{tikzcd} \bullet_{Y} \arrow[r, "\sim"] & \overset{Y}{\bullet} & \bullet_{Y} \arrow[l, "\sim"'] \\ & \bullet_{Y} \arrow[u, "\wr"'] & \end{tikzcd},$$

The last summand is a multiple of the indecomposable representation

$$\begin{tikzcd} \bullet_{1} \arrow[r, "\sim"] & \overset{1}{\bullet} & \bullet_{1} \arrow[l, "\sim"'] \\ & \bullet_{1} \arrow[u, "\wr"'] & \end{tikzcd}.$$

So — considering the first summand and renaming the spaces to simplify notation — we are in a situation where

$$V = V_1 + V_2 + V_3, \quad V_1 \cap V_2 \cap V_3 = 0.$$

As a next step, we let $Y = V_1 \cap V_2$ and we choose a complement V' of Y in V such that $V_3 \subset V'$ and set $V_1' = V' \cap V_1, V_2' = V' \cap V_2$. This