

PAW

LoRa-Based Pet Tracking Collar

Complete Project Documentation — Hardware, Firmware & MQTT Bridge

Version 1.0

September 2026

Target Hardware: RAKwireless RAK3172 (STM32WLE5) · u-blox MAX-M10S · LIS2DE12 · ESP32-DEVKIT-V1

Radio: LoRa P2P, 868 MHz (EU868)

1. Executive Summary

PAW is a battery-powered pet tracking collar built around a LoRa Point-to-Point (P2P) radio link, deliberately avoiding any SIM or cellular connectivity. The collar reports the animal's location as a compact 18-byte binary packet, transmitted either on motion (accelerometer wake) or on a guaranteed 30-minute periodic schedule. A separate gateway board receives these packets over the same 868 MHz P2P link and bridges them onto MQTT, where a mobile app subscribes and renders live positions on a map.

This document consolidates all three parts of the assignment — main-board hardware for both the collar and the gateway, the collar's embedded firmware, and the LoRa-to-MQTT bridge with its app-side subscriber — into a single technical reference. Section 2 maps every requested deliverable to the file that satisfies it. Sections 3–5 cover hardware, firmware, and bridge in turn. Section 7 is a candid cross-document consistency review: working across documents authored somewhat independently surfaced a handful of real inconsistencies, the most consequential being a mismatch between the regulator specified in the current BOM and the regulator the battery-life model assumes. These are flagged rather than quietly smoothed over, in the spirit of the evaluation criteria's emphasis on judgment and documentation clarity.

2. Repository & Deliverables Map

Every deliverable requested by the assignment brief, and the file that satisfies it:

Part	Deliverable	File(s)
1	Schematic (collar + gateway)	part1-hardware/collar/collar_schematic.pdf, part1-hardware/bridge/bridge_schematic.pdf
1	Bill of materials	part1-hardware/collar/BOM_Pet_Tracking_Collar.docx, part1-hardware/bridge/BOM_LoRa_Bridge_Receiver.docx
1	One-page write-up (antenna, power budget, 1,000-unit changes)	Collar_Design_Notes.docx, Bridge_Design_Notes.docx (+ Sections 3, 4 of this document)
2	Firmware source	part2-firmware/collar_firmware.cpp
2	State machine diagram	PAW_Technical_Document.docx Fig. 2 (+ Section 4.3 of this document)
2	Power-optimization paragraph + battery-life estimate	PAW_Power_Optimization_Strategy.docx (+ Section 4.7–4.8 of this document)
3	Bridge source code	part3-bridge/gateway_bridge.ino
3	MQTT topic/payload schema documentation	part3-bridge/MQTT_SCHEMA.md (+ Section 5.2 of this document)
3	App-side subscriber + QoS/retained rationale	part3-bridge/app_subscriber.dart (+ Section 5.3 of this document)
—	Top-level README (what's real vs. simulated, how to run)	README.md

3. Part 1 — Hardware

3.1 Collar Main Board

The collar board is organized around five sections: USB-C/CH340E programming interface, battery charging & regulation, a reset network, the RAK3172 MCU/LoRa module with its GPS companion, and the accelerometer.

Component selection

Function	Part	Rationale
MCU + Radio	RAK3172-xx-B-SM-xl (STM32WLE5)	Integrates an Arm Cortex-M4 MCU and a sub-GHz radio in one certified module, avoiding a separate discrete SX126x + MCU layout. Firmware targets RAKwireless's RUI3 API layer directly, which only runs on this module family.
GNSS	u-blox MAX-M10S	Low-power standalone GNSS receiver with fast warm-start behavior, well suited to a duty-cycled wearable that only needs a fix every 30 minutes or on motion.
Accelerometer	LIS2DE12 (schematic silkscreen; BOM/notes also reference the LIS2DW12 class)	Ultra-low-power 3-axis MEMS part with on-chip wake-up-threshold detection — motion is detected entirely in the sensor, so the MCU is only interrupted after a real event, never polling.
Charging	TP4056-42-ESOP8	Standard, low-cost linear Li-ion/LiPo charge-management IC for a single-cell pack; charging only, no discharge protection (flagged as a production gap in Section 3.1's production notes).
Regulation	AMS1117-3.3 LDO	Simple, cheap 3.3 V linear regulator. Its ~5 mA quiescent current is explicitly called out in the design notes as the dominant lever on standby battery life — see Section 7 for why this matters more than it might look.
Programming	USB-C + CH340E USB-UART bridge	Lets the board be flashed/debugged over USB during development without a separate programmer; a production-run candidate for removal (Section 3.1 production notes).




Fig. 1 — Collar main board schematic: USB-C/CH340E interface, battery & voltage control, reset network, RAK3172 MCU/LoRa with MAX-M10S GPS, and LIS2DE12 accelerometer.

Antenna placement rationale

The board carries two RF antennas that must be isolated from each other and from lossy or conductive material nearby:

- GPS antenna (AE2, passive chip antenna, feeding MAX-M10S U2): needs a clear sky view and continuous ground-plane clearance per the vendor keep-out footprint; placed on the outward-facing side of the collar, away from the dog's neck/fur (body tissue and moisture detune and attenuate GNSS) and away from the battery and metal snap/buckle hardware.
- 868 MHz LoRa antenna (E1, ANT-868-CHIP-T, feeding RAK3172 U1): ceramic chip antennas are sensitive to ground-plane length/shape, so the reference layout from the datasheet is followed exactly, with the antenna at a board edge radiating away from the PCB, battery, and GPS antenna.
- The two antennas sit at opposite ends of the PCB to minimize near-field coupling / de-sensing between radios operating simultaneously.
- Both antennas are oriented so their strongest lobe points away from the animal's body — the metal battery cell and any D-ring/buckle are the most common cause of range loss in wearable trackers if left in the near field.

Power budget estimate

Assumes a 300 mAh, 3.7 V Li-Po cell (see Section 7 for why the cell capacity used here differs from the figures used in the firmware's battery-life model):

State	Dominant load	Approx. current
Sleep	MCU standby, radio & GPS off, accelerometer wake-on-motion, regulator quiescent draw	~5–8 mA (AMS1117) / ~10–50 μ A (low-IQ, production target)
GPS on	MAX-M10S acquisition + fix	~20–25 mA
LoRa TX burst	RAK3172 PA drive, ~14 dBm typical up to +22 dBm boost, 0.1–1 s/packet	~20–40 mA (14 dBm) – ~100–120 mA (22 dBm)

Illustrative duty cycle — one GPS fix + one LoRa uplink every 10 minutes (30 s GPS-on, 1 s TX, remainder sleep): with the AMS1117 LDO in the current design (always-on, ~5 mA quiescent), average current $\approx$ 6 mA $\rightarrow$ ~50 hours (~2 days) on 300 mAh. With a low-IQ regulator (μ A-class quiescent), average current $\approx$ 1.3 mA $\rightarrow$ ~225 hours (~9–10 days) on the same cell.

Takeaway: the always-on linear regulator, not the GPS or radio, is the single biggest lever on standby battery life.

Changes for a 1,000-unit production run

- Power path: replace the AMS1117 LDO with a nanopower buck converter or a low-IQ LDO (sub- μ A to low- μ A quiescent) to remove the dominant sleep-current drain identified above.
- Battery safety: add a dedicated battery protection IC (over-discharge / over-current / short-circuit) — TP4056 alone only manages charging, which is a field-reliability and safety gap at volume.
- BOM cost at scale: RAK3172 and MAX-M10S pricing drops materially at 500–1,000+ unit reel quantities versus the single-unit prices used in the current BOM.
- Programming interface: consider a do-not-populate USB-C/CH340E section, programming instead via a pogo-pin test jig at assembly — saves BOM cost and board area across 1,000 units unless end-user USB firmware updates are a requirement.
- RF certification: the 868 MHz LoRa link and GNSS antenna placement need ETSI (or applicable regional) radio certification before a production run — schedule early, since it can drive layout changes.
- Enclosure & sourcing: move from a prototype/3D-printed enclosure to an injection-molded, IP-rated housing, and source assembly through a volume-capable contract manufacturer.

Collar bill of materials (summary)

Full BOM with reference designators and per-line costs: BOM_Pet_Tracking_Collar.docx. Section totals:

Section	Items	Subtotal (₹)
USB Type-C & CH340E interface	5	84
Battery & voltage controller	6	417
Reset system	3	13
GPS section (MAX-M10S)	2	1,470
MCU / LoRa section (RAK3172)	3	1,157
Accelerometer sensor	1	133
PCB & mechanical	1	420
Grand total (per unit, prototype qty)	—	₹3,696

3.2 Gateway / MQTT Bridge Board

The gateway pairs an ESP32-DEVKIT-V1 (Wi-Fi + MQTT client) with a second RAK3172 module configured for continuous LoRa P2P receive, bridged over a UART link.




Fig. 2 — Gateway schematic: ESP32-DEVKIT-V1 host MCU, reset network, and RAK3172 LoRa receiver with an external whip antenna.

Antenna placement rationale

- Single RF antenna (E2, ANT-868-PW-RA, external screw-mount whip) feeding the RAK3172's RF pin. Being external rather than a PCB trace or chip antenna gives placement freedom, but ground-plane extent and feed routing still matter for match and efficiency.
- Mount vertically at the enclosure edge for an omnidirectional pattern typical of gateway installs; keep clear of metal enclosure panels/brackets and away from the ESP32's own onboard Wi-Fi antenna to avoid pattern distortion and detuning.
- Wi-Fi/LoRa coexistence: the two bands don't overlap, but a strong nearby Wi-Fi TX burst can raise the LoRa front end's noise floor and desensitize RX — recommend physical separation between the two modules, with shielding/extra spacing if range proves marginal.
- Route the ESP32↔RAK3172 UART bridge short and away from the antenna feed line to avoid coupling RF noise into the digital signal.
- If housed in a metal enclosure, the whip antenna must protrude outside it (or the enclosure needs an RF-transparent window) — a fully metal box around a whip antenna substantially attenuates the LoRa link.

Power budget estimate

Unlike the collar, this schematic shows no battery/charging section — the gateway is assumed to run from a continuous 5 V USB or DC supply feeding the 3.3 V rail shown, so the estimate below frames supply current headroom rather than battery runtime:

State	Dominant load	Approx. current
Idle / LoRa RX listen	ESP32 Wi-Fi connected & idle + RAK3172 continuous LoRa RX	~90–130 mA
Wi-Fi TX burst (MQTT publish)	ESP32 Wi-Fi radio driving the MQTT publish over WLAN	~150–260 mA (peaks during association/TX)
LoRa TX burst (ack/downlink, if used)	RAK3172 PA drive, 14 dBm typical up to +22 dBm boost	~20–40 mA (14 dBm) – ~100–120 mA (22 dBm)
Worst-case concurrent peak	Wi-Fi TX overlapping a LoRa TX burst	~300–400 mA combined — size supply/regulator with margin above this

Takeaway: unlike the battery-powered collar, this bridge is continuously mains/USB powered, so the real design lever is the current capacity and thermal margin of the (not-yet-shown) 3.3 V regulation stage and supply connector, sized to the ~300–400 mA worst-case peak — not battery runtime.

Changes for a 1,000-unit production run

- Replace the ESP32-DEVKIT-V1 dev board with a bare ESP32-WROOM-32(E) module soldered directly to the production PCB, removing the duplicated USB-UART bridge, regulator, and headers the DEVKIT carries.
- Add a defined power input & regulation stage: the current schematic only shows a bare 3.3 V rail — production needs an actual input path (USB-C or DC jack), reverse-polarity/ESD protection, and a buck regulator sized for the peak Wi-Fi + LoRa current above.
- Retain a programming/debug path via a small CH340E/CP2102-class bridge or a pogo-pin/UART test jig, mirroring the same trade-off made on the collar.
- Negotiate reel/tape RAK3172 pricing at 500–1,000+ units versus the single-unit price used in the current BOM.
- Reconsider the ANT-868-PW-RA screw-mount whip versus a lower-cost SMD/chip or pre-terminated pigtail antenna, depending on enclosure design and required range.
- Schedule ETSI (or applicable regional) certification for both the 868 MHz and 2.4 GHz radios early, since it can drive antenna and layout changes.
- Move to an injection-molded, IP-rated enclosure with an RF-transparent antenna window or pass-through; add status LEDs (power/Wi-Fi/LoRa activity) and Wi-Fi OTA update capability for field-deployed units.

Gateway bill of materials (summary)

Full BOM: BOM_LoRa_Bridge_Receiver.docx. Section totals:

Section	Items	Subtotal (₹)
Reset system	3	13
ESP32 host MCU	1	400
MCU / LoRa section (RAK3172 + antenna + connector)	4	1,339
PCB & mechanical	1	350
Grand total (per unit, prototype qty)	—	₹2,102

Note: this BOM covers only the LoRa receiver / MQTT bridge circuit shown in the supplied schematic — no power-supply/battery-charging section, per the production-changes item above.

4. Part 2 — Collar Firmware

Target: RAKwireless RAK3172, RUI3 APIs (`api.lora.*`, `api.system.*`), with hardware-abstraction functions (`hal_gps_*`, `hal_accel_*`, `hal_battery_*`, `hal_lora_*`) so the control logic can be re-targeted to bare STM32 HAL or run against a mocked GPS/LoRa layer for bench testing. Source: `collar_firmware.cpp`.

4.1 System Architecture




Fig. 3 — A single low-power MCU arbitrates three peripherals: accelerometer (motion wake), GNSS (position), and LoRa P2P (transmission); battery voltage is sampled internally.

4.2 Firmware Operating Sequence

- Low-power sleep — MCU remains in its lowest power state between events.
- Motion interrupt or periodic wake-up — the accelerometer's motion interrupt, or the 30-minute periodic timer, wakes the MCU.
- GPS acquisition — the GNSS receiver is queried for a position fix, bounded by a 60 s fix timeout.
- GPS validation — a fix is accepted only if fix quality is valid; failed fixes clear the payload's GPS-valid flag.
- Battery measurement — the MCU samples battery voltage for inclusion in the payload.
- Binary payload construction — device ID, position, timestamp, battery voltage, and a sequence number are packed into the fixed-length payload.
- LoRa P2P transmission — the payload is transmitted over the configured 868 MHz P2P link.
- Return to low-power sleep — radio and non-essential peripherals are left idle; the MCU resumes deep sleep.

4.3 State Machine

Two independent triggers feed the same acquire→transmit path: a debounced motion interrupt and a periodic timer that guarantees a transmission at least every 30 minutes even with zero motion. Both converge back on deep sleep — `loop()` never does anything but `api.system.sleep.all()`; all real work happens in interrupt/timer-dispatched handlers.




Fig. 4 — Collar firmware state machine: both wake-up paths converge on a common acquire → build → transmit → sleep sequence.

4.4 Binary Packet Specification

Each location report is an 18-byte, little-endian binary payload. Full reference encoder/decoder (C, and inverse logic used by the gateway): PAW_Binary_Packet_Specification.docx.

Byte	Field	Type	Description
0	Device ID	uint8	Unique collar identifier
1	Protocol version	uint8	Packet format version
2	Status flags	uint8	Bit 0: GPS valid · Bit 1: motion-triggered wake
3–6	Latitude	int32	Degrees × 1,000,000
7–10	Longitude	int32	Degrees × 1,000,000
11–14	Timestamp	uint32	Seconds since boot (see Section 7 — not wall-clock UTC)
15–16	Battery	uint16	Battery voltage, millivolts
17	Sequence	uint8	Packet sequence number, wraps at 256

Worked example — device_id=1, protocol_version=1, flags=3 (GPS valid + motion wake), lat=22.864000, lon=88.401000, timestamp=123456, battery_mv=3785, sequence=42 encodes to:

01 01 03 80 E0 5C 01 68 E4 44 05 40 E2 01 00 C9 0E 2A

4.5 LoRa Radio Configuration & Rationale

All values below are set explicitly in hal_lora_init() via the RUI3 api.lora.* interface, except bandwidth — see the open item in Section 7. Full rationale and ETSI compliance workings:

PAW_LoRa_Radio_Configuration.docx.

Parameter	Value	Rationale
Frequency	868 MHz (EU868)	License-free ISM band for Europe; no cellular subscription needed, matching the collar's SIM-free design goal.
Spreading factor	SF9	Mid-range balance point: higher SF extends range/sensitivity at the cost of airtime and energy; lower SF shortens airtime but reduces link margin.
Coding rate	4/5	Least redundant LoRa FEC rate — minimum overhead for basic error correction on a short, private P2P link.
Preamble	8 symbols	LoRa standard default — long enough for reliable sync without unnecessary fixed overhead.
TX power	14 dBm	Deliberate mid-range setting that also happens to align exactly with the ETSI ERP limit for the primary EU868 sub-band (g1) — compliant by design, not throttled from a higher default.
Bandwidth	Not explicitly set in collar firmware — RUI3 default assumed (125 kHz)	Open item — see Section 7.
Payload size	18 bytes, fixed	Airtime scales directly with payload size for a given SF/CR/BW — a small, fixed packet keeps every transmission's on-air cost identical and predictable.

4.6 Airtime & ETSI EU868 Duty-Cycle Compliance

The collar's configured frequency (868 MHz) and TX power (14 dBm) place it in ETSI sub-band g1 (868.0–868.6 MHz), which permits 1% duty cycle (36 s/hour) at up to 25 mW ERP (14 dBm) — exactly the power configured.

Assumption	Explicit header + CRC	Implicit header + CRC
Bandwidth = 125 kHz (RUI3 default)	≈ 185.3 ms	≈ 164.9 ms
Bandwidth = 250 kHz	≈ 92.7 ms	≈ 82.4 ms

At ~185 ms airtime, the collar could transmit roughly 190 times/hour before approaching the 1% duty-cycle ceiling; even at the ~70 ms figure used elsewhere in this project's documents, that rises to ~500/hour. The modeled worst-case event rate (348 events/day ≈ 14.5/hour) sits well inside this margin either way — duty-cycle compliance is not at risk under currently modeled usage, though the margin narrows if SF or payload size increase later. See Section 7 for the airtime-figure reconciliation this table motivates.

4.7 Power Optimization Strategy

Seven design decisions keep the MCU and peripherals idle by default and active only for the minimum time a task requires:

- Event-driven architecture — no polling loop. `loop()` is a single call to `api.system.sleep.all()`; all work is dispatched from a hardware interrupt (accelerometer) or a software timer (periodic fix).
- Accelerometer interrupt instead of continuous MCU polling — the LIS2DW12 evaluates its own motion threshold on-chip and only interrupts the MCU after motion has already been detected.
- GPS activated only when a fix is actually required — never speculatively — and bounded by a 60 s timeout so a bad fix can't hold the radio on indefinitely.
- LoRa radio enabled only during transmission — a single bounded send per event, not a maintained radio session; the fixed 18-byte payload keeps on-air time minimal.

- MCU returns to low-power mode after every transmission — `lpm.set(1)` / `lpm.lvl.set(2)` (deepest supported level) are configured once in `setup()`, not re-entered manually per event.
- Motion transmission cooldown (2-minute debounce) — prevents a continuously active animal from triggering dozens of full GPS+LoRa cycles per minute; this is the single biggest lever this firmware has over real-world battery drain.
- Guaranteed maximum 30-minute periodic update — a fixed, predictable floor on reporting frequency so the collar is never silent for hours, independent of motion.

Implementation note carried over from the source documents: the firmware does not send an explicit power-down command to the GPS module between fixes, and UART inactivity alone does not guarantee a GNSS chip drops to a low-power state on all modules — this should be verified against the MAX-M10S's power-management interface before production, since it directly affects any sleep-current figure used in battery-life math.

4.8 Battery Life Estimates

Battery capacity is confirmed at 1,000 mAh and 2,000 mAh Li-Ion for these scenario tables; measured current draw and real-world duty cycle are not yet measured on physical hardware, so every current figure below is a labeled datasheet-typical assumption, not a measurement (sleep 3 μ A, GPS acquisition 25 mA, LoRa TX 120 mA @ ~70 ms — see Section 7 for why this last figure should be revisited).

1,000 mAh Li-Ion

Scenario	mAh/day	Est. days	Est. months
Warm-start GPS, periodic only (48/day)	0.851	1176	~38.7
Warm-start GPS, moderate motion (98/day)	1.662	602	~19.8
Warm-start GPS, high motion (348/day)	5.717	175	~5.8
Cold-start GPS, periodic only (48/day)	10.184	98	~3.2
Cold-start GPS, moderate motion (98/day)	20.717	48	~1.6

2,000 mAh Li-Ion (alternative capacity)

Scenario	mAh/day	Est. days	Est. months
Warm-start GPS, periodic only (48/day)	0.851	2351	~77.3
Warm-start GPS, moderate motion (98/day)	1.662	1204	~39.6
Warm-start GPS, high motion (348/day)	5.717	350	~11.5
Cold-start GPS, periodic only (48/day)	10.184	196	~6.5
Cold-start GPS, moderate motion (98/day)	20.717	97	~3.2

Takeaway: the ~20 $\times$ spread between best and worst case is driven almost entirely by whether GPS performs a warm or cold start on each fix — sleep current and LoRa airtime barely move the result by comparison. Measuring

warm- vs. cold-start GPS behavior across the 30-minute interval is the single highest-value hardware measurement for narrowing this range. Doubling capacity from 1,000 to 2,000 mAh roughly doubles every runtime figure, as expected, but does not change which variable dominates. Section 7 explains why these figures should be treated as provisional pending two open items (regulator choice and airtime).

5. Part 3 — MQTT Bridge

5.1 Bridge Firmware Architecture

gateway_bridge.ino runs on the ESP32 and does three jobs: keep Wi-Fi and MQTT connected (with non-overlapping, timer-driven reconnect logic for each), parse RAK3172 UART event lines, and decode/publish valid packets.

- Wi-Fi/MQTT reconnect is guarded against overlapping attempts via wifiConnectInFlight / mqttConnectInFlight flags plus one-shot FreeRTOS timers, rather than retrying inside a blocking loop.
- A retained MQTT Last Will (paw/collar/gateway/status = "offline", replaced with "online" on connect) lets the app detect a crashed or disconnected gateway automatically, without polling.
- RAK3172 UART lines are parsed for the pattern +EVT:RXP2P:<RSSI>:<SNR>:<HEX_PAYLOAD>; the code's own comments flag that some RUI3 firmware builds insert an extra length field before the hex payload — see Section 7.
- decodeAndPublish() validates hex length and protocol version, decodes lat/lon/timestamp/battery/sequence per the packet spec, skips publishing when the GPS-valid flag is clear (nothing meaningful to show on the map), and checks mqttClient.connected() before attempting a publish so drops are reported distinctly from decode errors.
- The RAK3172 is configured over AT commands on boot (AT+NWM=0 for P2P mode, AT+P2P=<freq:sf:bw:cr:preamble:power>, AT+PRECV=65534 for continuous receive) rather than assuming factory defaults.

5.2 MQTT Topic & Payload Schema

Topic	Purpose	Retained?
paw/collar/{device_id}/location	Latest location update from one collar	Yes
paw/collar/gateway/status	Gateway online/offline (Last Will)	Yes

{device_id} is the single-byte DEVICE_ID from the tracker firmware, published as a decimal string. The app subscribes to paw/collar+/location to track every collar on one connection, or a specific topic for one pet.

Field	Type	Description
lat	float	Latitude, decimal degrees
lon	float	Longitude, decimal degrees
ts	uint32	Seconds since collar boot — not wall-clock UTC (see Section 7)
battery_mv	uint16	Collar battery voltage, millivolts
source	string	Always "gateway" — reserved for future multi-gateway dedup
rsi	int	Signal strength of the received LoRa packet, dBm (schema-documented; see Section 7 for current publish status)

Field	Type	Description
snr	int	Signal-to-noise ratio of the received LoRa packet, dB (schema-documented; see Section 7)
gps_valid	bool	Whether the collar had a real fix when it sent this packet (schema-documented; see Section 7)
motion_wake	bool	true if triggered by the accelerometer, false if the periodic update (schema-documented; see Section 7)
seq	uint8	Rolling per-collar sequence number, 0–255 (schema-documented; see Section 7)

5.3 QoS Choice & Retained-Message Rationale

QoS	Guarantee	Chosen? Why / why not
0	At-most-once, fire-and-forget	Rejected — LoRa fixes are expensive to reacquire (GPS cold-start can take up to a minute, and each transmission costs battery); silently dropping an update on a flaky Wi-Fi hop isn't worth the marginal latency savings.
1	At-least-once	Chosen. Guarantees delivery across a brief gateway/broker disconnect (broker re-delivers until PUBACK). Possible duplicate deliveries are harmless — each message fully overwrites the previous location, so re-processing the same fix twice is a no-op.
2	Exactly-once	Rejected — the extra PUBREC/PUBREL/PUBCOMP handshake costs round-trips and broker-side state for a dedup benefit the app doesn't need, since duplicate location messages are idempotent by nature.

Retain = true: the tracker only transmits every 30 minutes (or on motion). Without retain, an app that opens or reconnects has to wait up to 30 minutes to see anything; with retain, the broker immediately replays the last known location the instant the app subscribes.

5.4 App-Side Subscriber

app_subscriber.dart is a minimal, working Flutter subscriber built on the mqtt_client package (pub.dev, ^10.0.0):

- Connects with a clean session (the app only cares about "now"), keep-alive 30 s, and auto-reconnect with re-subscription on reconnect.
- A single wildcard subscription (paw/collar+/location) at QoS 1 covers every collar on one connection, plus a separate subscription to the gateway's retained status topic.
- Incoming JSON is decoded into a CollarLocation and handed to an onLocationUpdate callback so a map widget can update markers without the service knowing anything about the UI.
- A per-device last-sequence map is intended to de-duplicate QoS-1 redeliveries — see Section 7 for a real gap in how this is currently wired end-to-end.

6. Assumptions & What's Simulated / Stubbed

Component	Status
Collar schematic	Real, complete circuit
Collar firmware — wake, sleep, packet build, LoRa TX	Real logic, targets real RUI3 APIs
Collar firmware — GPS acquisition	Mockable via HW_GPS MOCK build switch; real NMEA GGA parsing implemented and ready for hardware
Collar firmware — LoRa TX	Mockable via HW_LORA MOCK build switch; real <code>api.lora.psend()</code> by default
Gateway schematic	Real, complete circuit
Gateway bridge firmware	Real logic; not bench-tested against a live RAK3172 serial stream (Section 7 flags the one field-format assumption to confirm)
MQTT broker	Not hosted as part of this submission — firmware targets a public test broker by default; point at your own broker for anything beyond a bench test
App-side subscriber	Real, working Dart/Flutter subscription code; not wired into a full map UI
Battery-life figures	Engineering estimates from datasheet-typical values, not hardware measurements — no physical hardware was available

Also assumed: LoRa P2P (not full LoRaWAN) end-to-end — the gateway receives P2P packets directly rather than acting as a LoRaWAN network-server gateway, which is simpler to implement completely within the timebox while still satisfying "gets a location fix into a mobile app over MQTT." Component prices in both BOMs are indicative single-unit distributor prices in INR as of September 2026, excluding GST, assembly labour, and enclosure hardware.

7. Cross-Document Consistency Review

The hardware, firmware, and bridge documentation were produced as separate, focused documents. Reading them together surfaced several genuine inconsistencies, ranked by how much they matter:

7.1 [Critical] Battery-life model assumes a regulator that isn't in the current BOM

PAW_Power_Optimization_Strategy.docx models ~3 μ A sleep current — a low-IQ regulator. But the collar schematic and BOM currently specify an AMS1117 LDO, whose ~5 mA quiescent draw Collar_Design_Notes.docx itself calls "the single biggest lever on standby battery life." At 5 mA continuous, a 1,000 mAh cell depletes in roughly 8 days regardless of GPS/LoRa activity — nowhere near the 6–8 month headline figures in Section 4.8. The low-IQ swap is listed as a production-run TODO in the design notes; until it is made, the long-runtime figures describe the production revision, not the schematic as currently drawn. Recommendation: either re-run Section 4.8's scenarios against the AMS1117's real quiescent current, or pull the low-IQ regulator forward into the current BOM before quoting a runtime number to anyone.

7.2 [Medium] Battery capacity isn't pinned to a single source of truth

Collar_Design_Notes.docx's power-budget section assumes a 300 mAh cell; PAW_Power_Optimization_Strategy.docx models 1,000 mAh and 2,000 mAh scenarios; the BOM's battery line item (BT1) states no capacity at all. Recommendation: pin an exact cell part number and capacity in the BOM and have every downstream document reference that one number.

7.3 [Medium] LoRa bandwidth is assumed, not set, in the collar firmware

hal_lora_init() in collar_firmware.cpp never calls a bandwidth setter, so it relies on an unstated RUI3 P2P default (assumed 125 kHz). gateway_bridge.ino does set it explicitly (LORA_BW=125) for its own RAK3172 configuration. Because both ends of a LoRa P2P link must agree on bandwidth to demodulate at all, the gateway's explicit setting is indirect evidence the collar is effectively at 125 kHz too — but it should be set explicitly on the collar side as well, since an unstated default is one RUI3 library update away from silently breaking the link.

7.4 [Medium] Airtime figure needs reconciling against the confirmed bandwidth

README.md and PAW_Power_Optimization_Strategy.docx cite ~60–70 ms airtime for the 18-byte payload. The worked calculation in PAW_LoRa_Radio_Configuration.docx (Section 4.6 of this document) gives ~165–185 ms at 125 kHz — the bandwidth the gateway actually configures — and the ~70 ms figure only matches a 250 kHz / implicit-header case. Net effect on the battery-life numbers is small: GPS acquisition energy per event ($\sim 25 \text{ mA} \times 2\text{--}3 \text{ s} \approx 0.017\text{--}0.021 \text{ mAh}$) dominates LoRa TX energy at either airtime figure ($\sim 0.0023 \text{ mAh}$ at 70 ms vs. $\sim 0.0062 \text{ mAh}$ at 185 ms), so Section 4.8's scenario totals would shift by roughly a percent or two once corrected — not enough to change which variable dominates, but enough that the airtime constant should be corrected for a fully defensible spec.

7.5 [Low] TX power constant mismatch between collar and gateway firmware

collar_firmware.cpp sets LORA_TX_POWER=14 (dBm); gateway_bridge.ino sets LORA_POWER=15 for its own RAK3172's AT+P2P configuration. This doesn't break the link — a receiver's own TX power setting is irrelevant to how well it receives — but it's an unexplained inconsistency between the two firmware files' constants that should be reconciled or explicitly justified if the gateway is ever meant to transmit acks or downlinks.

7.6 [Low] Documented payload fields aren't actually published yet, and the app's de-dup logic references a field it never declares

MQTT_SCHEMA.md documents rssi, snr, gps_valid, motion_wake, and seq as payload fields, but gateway_bridge.ino currently leaves those five lines commented out in its JSON publish — only lat, lon, ts, battery_mv, and source go out today. Separately, app_subscriber.dart's _handleMessage compares location.seq for de-duplication, but the CollarLocation class as written declares no seq field and fromJson never parses one — so that de-dup path does not currently compile/run end-to-end, on top of the field not being sent yet by the gateway either. Recommendation: either uncomment the fields on the gateway and add seq to the Dart model, or drop seq-based de-dup entirely and rely on QoS-1's idempotent overwrite semantics, which MQTT_SCHEMA.md's own QoS rationale already argues is harmless.

7.7 [Low] +EVT:RXP2P field-format assumption is unverified

gateway_bridge.ino's own comments flag that some RUI3 firmware builds insert an extra length field before the hex payload in the +EVT:RXP2P: event line. The parser as written assumes a fixed three-field format (RSSI:SNR:HEX). This should be confirmed against the actual RUI3 firmware version's serial output before trusting the decoded fields on real hardware.

7.8 [Low] Timestamp is not wall-clock time

Already flagged clearly in MQTT_SCHEMA.md, restated here for visibility: ts is seconds since the collar last rebooted, not a UTC epoch. Any historical/timeline UI on the map needs either an RTC on the collar, real NMEA time-field parsing, or a gateway-side receipt timestamp (accepting sub-second LoRa transit delay) before ts can be treated as wall-clock time.

8. What I'd Do Differently With More Time

- Get real hardware on the bench to replace every datasheet-typical current figure in Section 4.8 with a measured one, and to confirm the actual +EVT:RXP2P field format the target RUI3 firmware version emits.
- Resolve the regulator/battery-life mismatch (Section 7.1) by re-running the battery scenarios against the AMS1117's real quiescent current, or by moving the low-IQ regulator into the current BOM instead of deferring it to the 1,000-unit revision.
- Wire up the payload fields MQTT_SCHEMA.md documents but the gateway currently leaves commented out, and fix app_subscriber.dart's CollarLocation model so its sequence-based de-dup actually compiles and runs (Section 7.6).
- Set LoRa bandwidth explicitly in the collar firmware instead of relying on an unstated default (Section 7.3), and reconcile the TX power constants between the two firmware files (Section 7.5).
- Give the collar an RTC, or have the gateway stamp ts on receipt, so the map can show wall-clock time instead of seconds-since-boot.
- Add battery discharge protection to the collar (TP4056 only manages charging) and a defined input/regulation stage to the gateway board (its schematic currently assumes a bare 3.3 V rail with no shown supply path) before either design is production-ready.
- Add a real battery-voltage divider/ADC path detail to the collar schematic rather than relying solely on RUI3's api.system.bat.get() abstraction, so the hardware and firmware documentation agree on exactly how that measurement is taken.

9. Evaluation Criteria Cross-Reference

Evaluation criterion	Where addressed
Correctness/clarity of RF & antenna reasoning	Sections 3.1, 3.2 (antenna placement), 4.5–4.6 (radio config, airtime, duty cycle)
Correctness/clarity of power-budget reasoning	Sections 3.1, 3.2 (hardware power budgets), 4.7–4.8 (firmware power strategy, battery life)
Code quality and readability (firmware + bridge)	part2-firmware/collar_firmware.cpp, part3-bridge/gateway_bridge.ino, part3-bridge/app_subscriber.dart
Sound low-power embedded design (sleep, wake sources, duty cycling)	Sections 4.2–4.3, 4.7
MQTT/protocol design judgment (topics, payload, QoS)	Section 5.2–5.3
Documentation clarity — can another engineer pick this up	This document in full, plus README.md's run instructions; Section 7's consistency review in particular is meant to show the reasoning another engineer would need, not just a clean final answer