

1. Use the page table below to answer this question. Each entry of table contains an hexadecimal value (starts with "0x"). Make sure to answer these question by preceding your answer with "0x". Top entry in the page table is for Page 0. Page 6 is stored in Frame _____.

0x1102
0x038A
0x8240
0xA2B3
0x2000
0x00C5
0x054E
0x23F4

0x054E

2. A CPU has a 32 bit address bus and page size = 8192 bytes. The CPU generates the address A = 0.27508103. For this system, the page number is _____ and the page offset is _____ in hexadecimal.

0x13A84

0x103

3. Use the page table below to answer this question. Each entry of table contains an hexadecimal value (starts with "0x"). Make sure to answer these question by preceding your answer with "0x". Top entry in the page table is for Page 0. Page 5 is stored in Frame _____.

0x1102
0x038A
0x8240
0xA2B3
0x2000
0x00C5
0x054E
0x23F4

0x00C5

4. A CPU has a 32 bit address bus and page size = 1024. For this system, the page offset has _____ bits and the page number has _____ bits.

10
22

5. Consider a CPU with a 32 bit address bus and a 4096 byte page size. Use the page table below to answer these questions. Each entry of table contains an hexadecimal value (starts with "0x"). Make sure to answer these questions with adding the prefix "0x" and omit leading zeros if any. Top entry in the page table is for Page 0.

The objective is to translate the logical address LA = 0x1F06. The page offset is _____. The page number is _____. The frame # is _____. Then the physical address is _____.

0x1102
0x038A
0x8240
0xA2B3
0x2000
0x00C5
0x054E
0x23F4

0xF06
0x1
0x38A
0x38AF06

6. Consider a CPU with a 32 bit address bus and a 512 byte page size. Use the page table below to answer these questions. Each entry of table contains an hexadecimal value (starts with "0x"). Make sure to answer these questions with adding the prefix "0x" and omit leading zeros if any. Top entry in the page table is for Page 0.

The objective is to translate the logical address LA = 0x54A. The page offset is _____. The page number is _____. The frame # is _____. Then the physical address is _____.

0x1102
0x038A
0x8240
0xA2B3
0x2000
0x00C5
0x054E
0x23F4

0x14A
0x2
0x8240
0x104814A

7. Consider a CPU with a 32 bit address bus and a 1024 byte page size. Use the page table below to answer these questions. Each entry of table contains an hexadecimal value (starts with "0x"). Make sure to answer these questions with adding the prefix "0x" and omit leading zeros if any. Top entry in the page table is for Page 0.

The objective is to translate the logical address LA =0x89F. The page offset is _____. The page number is _____. The frame # is _____. Then the physical address is _____.

0x1102
0x038A
0x8240
0xA2B3
0x2000
0x00C5
0x054E
0x23F4

0x9F
0x2
0x8240
0x209009F

8. Consider a CPU with a 32 bit address bus and a 4096 byte page size. Use the page table below to answer these questions. Each entry of table contains an hexadecimal value (starts with "0x"). Make sure to answer these questions with adding the prefix "0x" and omit leading zeros if any. Top entry in the page table is for Page 0.

The objective is to translate the logical address LA =0x7DE4. The page offset is _____. The page number is _____. The frame # is _____. Then the physical address is _____.

0x1102
0x038A
0x8240
0xA2B3
0x2000
0x00C5
0x054E
0x23F4

0xDE4
0x7
0x23F4
0x23F4DE4

9. Consider a CPU with a 32 bit address bus and a 8192 byte page size. Use the page table below to answer these questions. Each entry of table contains an hexadecimal value (starts with "0x"). Make sure to answer these questions with adding the prefix "0x" and omit leading zeros if any. Top entry in the page table is for Page 0.

The objective is to translate the logical address LA =0xB34A. The page offset is _____. The page number is _____. The frame # is _____. Then the physical address is _____.

0x1102
0x038A
0x8240
0xA2B3
0x2000
0x00C5
0x054E
0x23F4

0x134A
0x5
0xC5
0x18B34A