Project: Worked examples
Title: Load budget, PSU, transformer and battery
Status: DRAFT · Author: TempestOS (2026-10-23) · Checker: — (—) · Issued: —

1. Scope and method

The demand of a set of loads per supply (three-phase AC, single-phase AC, DC) and the minimum DC power supply, transformer and battery for it, each with a margin; the heat the loads dissipate for the enclosure calculation.

WHAT IT CALCULATES	RELATION
Demand per load	$P_i \cdot d_i \cdot k_i$; apparent power $P_i \cdot d_i \cdot k_i / \cos\varphi_i$ (arithmetic sum, conservative); this duty-weighted demand sizes the transformer and the enclosure heat
Running load of each load while it is on	$P_i \cdot k_i$, apparent $P_i \cdot k_i / \cos\varphi_i$ (the duty d is the share of time on, so it is left out: a cable, a bus and a power supply carry the load while it is on)
Bus currents	$I_{3\varphi} = S_{3\varphi,run}/(\sqrt{3} \cdot U)$, $I_{1\varphi} = S_{1\varphi,run}/U$, $I_{DC} = P_{DC,run}/U_{DC}$, from the running loads; when a bus is chosen for the DC power supply its input $P_{DC,run}/\eta_{PSU}$ (power factor 1) is added to that bus
Heat dissipated inside the enclosure	$\Phi = \Sigma\, h_i \cdot P_i \cdot d_i \cdot k_i + P_{DC} \cdot (1/\eta_{PSU} - 1)$, h_i = the share of the input power released inside (blank: the loss $1 - \eta_i$; electronics 1; a machine outside the enclosure 0); the second term is the power supply's own loss, present when an AC bus is chosen for it
Power supply sizing	$P_{PSU} \geq \text{margin} \cdot P_{DC,run}/f_{derate}$ (the running DC load, duty not applied; f_{derate} from the manufacturer's curve at θ and altitude)
Transformer sizing	$S_T \geq \text{margin} \cdot S$ for the running load; starting peak $S_{peak} = S + \max(m_i \cdot P_i/\cos\varphi_i - S_i) \leq k_T \cdot S_T$ (the starting load undiversified), so $S_T \geq S_{peak}/k_T$ for the start; the rating to buy is the larger of the two
Battery sizing	$C = I_b \cdot t/(\text{DoD} \cdot \eta_b \cdot k_{temp} \cdot k_{age})$, $I_b = \Sigma$ backed $P_i \cdot d_i \cdot k_i/(U_b \cdot \eta_{conv})$; Peukert: $I_b \cdot H \cdot (t/H)^{(1/k_p)}$ in place of $I_b \cdot t$, never below $I_b \cdot t$ (the exponent is not valid beyond the rated hour rate H)

Basis: Battery sizing and the Peukert relation[1](5th ed., Ch. 3–4); Electrical supply (supply voltage tolerance; cited by number only)[2](cl. 4.3).

2. Inputs

SYMBOL	DESCRIPTION	VALUE	UNIT	SOURCE	VALID RANGE
loads	Loads	6 row(s)		drawing: E-SCH-010 rev A	any
P_{add}	Additional three-phase load (linked from E1's RMS power)	0	kW	default	0 … 200 kW

SYMBOL	DESCRIPTION	VALUE	UNIT	SOURCE	VALID RANGE
$cosphi_{add}$	Power factor of the additional load	0.85		default	0.5 … 1
η_{add}	Efficiency of the additional load	0.9		default	0.5 … 1
$inrush_{add}$	Starting multiple of the additional load	1		default	1 … 20
$heat_{add}$	Share of the additional load's input power released inside the enclosure (a linked machine is outside it: 0)	0		default	0 … 1
U_{3ph}	Three-phase line voltage	400	V	spec: Site supply	12 … 1000 V
U_{1ph}	Single-phase voltage	230	V	spec: Site supply	12 … 1000 V
U_{DC}	DC bus voltage	24	V	drawing: E-SCH-010 rev A	12 … 1000 V
psu_{bus}	AC bus that feeds the DC power supply (its input P_{DC}/η_{PSU} is added to that bus)	AC single-phase		drawing: E-SCH-010 rev A	any
η_{psu}	DC power supply efficiency (power factor taken as 1)	0.9		assumption: 24 V supply efficiency 90 %, power factor taken as 1.	0.5 … 1
margin	Sizing margin	1.25		assumption: 25 % growth margin.	1 … 1.5
θ	Ambient temperature	45	°C	spec: Plant room design maximum	-20 … 70 °C
f_{derate}	PSU derating factor at the ambient and altitude	1		assumption: PSU rated to 60 °C without derating (datasheet).	0.1 … 1
P_{PSU}	Selected PSU rating	240	W	drawing: E-SCH-010 rev A	1 … 100000 W
S_T	Selected transformer rating	25	kVA	spec: Existing site transformer allocation	0.01 … 10000 kVA
k_T	Transformer short-time overload allowed for inrush	3		assumption: Short-time overload allowed by the supply authority.	1 … 20
t_{auto}	Battery autonomy	2	h	spec: Telemetry to stay up for 2 h on mains loss	0 … 72 h

SYMBOL	DESCRIPTION	VALUE	UNIT	SOURCE	VALID RANGE
U_b	Battery nominal voltage	24	V	drawing: E-SCH-010 rev A	2 … 1000 V
η_{conv}	Conversion efficiency battery → loads	1		assumption: DC UPS module, loads on the battery bus.	0.5 … 1
DoD	Allowed depth of discharge	0.8		assumption: VRLA, 80 % depth of discharge.	0.1 … 1
η_b	Battery discharge efficiency	0.95		assumption: Discharge efficiency.	0.5 … 1
k_{temp}	Temperature capacity factor	1		assumption: Battery kept at 20 °C.	0.3 … 1.2
k_{age}	Ageing (end-of-life) factor	0.8		assumption: End-of-life capacity 80 %.	0.5 … 1
C_{batt}	Selected battery capacity	17	A·h	drawing: E-SCH-010 rev A	0.1 … 100000 A·h

TABLE ROW	VALUES
loads[1]	name = Duty pump; supply = AC three-phase; P = 11 kW; cosphi = 0.86; eta = 0.91; d = 1; k = 1; inrush = 6.5; backed = no
loads[2]	name = Standby pump; supply = AC three-phase; P = 11 kW; cosphi = 0.86; eta = 0.91; d = 1; k = 0; inrush = 6.5; backed = no
loads[3]	name = Panel fan; supply = AC single-phase; P = 0.06 kW; cosphi = 0.9; eta = 0.7; d = 1; k = 1; inrush = 1; backed = no
loads[4]	name = Panel light; supply = AC single-phase; P = 0.02 kW; cosphi = 0.95; eta = 1; d = 0.1; k = 1; inrush = 1; backed = no
loads[5]	name = PLC and I/O; supply = DC; P = 0.096 kW; cosphi = 1; eta = 0.9; d = 1; k = 1; inrush = 1; backed = yes
loads[6]	name = Router; supply = DC; P = 0.024 kW; cosphi = 1; eta = 0.9; d = 1; k = 1; inrush = 1; backed = yes

3. Assumptions

A1. Each load's P is its electrical input; DC loads count at power factor 1 in the transformer demand; with a PSU bus chosen they count at P/η_{PSU}, which already includes the supply's own loss. The sheet adds that loss to Φ itself, as $P_{DC}\cdot(1/\eta_{PSU} - 1)$, whenever psu_{bus} and η_{PSU} are set: do not add the power supply as a load row, which would count its loss twice. (Load budget convention.)
A2. The heat released inside the enclosure is h·P·d·k per load; the default h = 1 − η is the loss of a drive or supply, electronics release all their input (h = 1) and a machine outside the panel releases none (h = 0). (Stated convention for the heat a load releases inside the panel; change h for a load that differs.)
A3. Apparent powers are added arithmetically, which is conservative when power factors differ. (Upper bound on S.)
A4. PSU derating, transformer overload and battery factors are the manufacturer's values, entered as records. (Entered as reference records, which carry their source, edition and licence.)
A5. η_{psu} (DC power supply efficiency (power factor taken as 1)) is taken as 0.9. (24 V supply efficiency

90 %, power factor taken as 1.)
A6. margin (Sizing margin) is taken as 1.25. (25 % growth margin.)
A7. f_{derate} (PSU derating factor at the ambient and altitude) is taken as 1. (PSU rated to 60 °C without derating (datasheet).)
A8. k_T (Transformer short-time overload allowed for inrush) is taken as 3. (Short-time overload allowed by the supply authority.)
A9. η_{conv} (Conversion efficiency battery → loads) is taken as 1. (DC UPS module, loads on the battery bus.)
A10. DoD (Allowed depth of discharge) is taken as 0.8. (VRLA, 80 % depth of discharge.)
A11. η_b (Battery discharge efficiency) is taken as 0.95. (Discharge efficiency.)
A12. k_{temp} (Temperature capacity factor) is taken as 1. (Battery kept at 20 °C.)
A13. k_{age} (Ageing (end-of-life) factor) is taken as 0.8. (End-of-life capacity 80 %.)

4. Working

[22] L1 = P·d·k; P·d·k/cosφ
= 11 × 1 × 1 = 11 kW; 12.791 kVA
= 11 kW
Duty pump (AC three-phase)

[23] L2 = P·d·k; P·d·k/cosφ
= 11 × 1 × 0 = 0 kW; 0 kVA
= 0 kW
Standby pump (AC three-phase)

[24] L3 = P·d·k; P·d·k/cosφ
= 0.06 × 1 × 1 = 0.06 kW; 0.066667 kVA
= 0.06 kW
Panel fan (AC single-phase)

[25] L4 = P·d·k; P·d·k/cosφ
= 0.02 × 0.1 × 1 = 0.002 kW; 0.0021053 kVA
= 0.002 kW
Panel light (AC single-phase)

[26] L5 = P·d·k; P·d·k/cosφ
= 0.096 × 1 × 1 = 0.096 kW; 0.10667 kVA
= 0.096 kW
PLC and I/O (DC)

[27] L6 = P·d·k; P·d·k/cosφ
= 0.024 × 1 × 1 = 0.024 kW; 0.026667 kVA
= 0.024 kW
Router (DC)

[28] $P_{conn} = \Sigma\ P_i$
= 11 + 11 + 0.06 + 0.02 + 0.096 + 0.024
= 22.2 kW
Connected load

[29] $P_{dem} = \Sigma\ P_i \cdot d_i \cdot k_i$
= 11 + 0 + 0.06 + 0.002 + 0.096 + 0.024
= 11.182 kW
Demand active power

[30] $S_{dem} = \Sigma\ P_i \cdot d_i \cdot k_i / \cos\varphi_i$
= 12.791 + 0 + 0.066667 + 0.0021053 + 0.10667 + 0.026667
= 12.993 kVA
Demand apparent power (arithmetic)

[31] $I_{3ph} = S_{3\varphi,run}/(\sqrt{3}\cdot U_{3ph})$, $S_{run} = \Sigma\ P_i \cdot k_i / \cos\varphi_i$
= 12791 / (√3 × 400)
= 18.462 A
Three-phase bus current, loads while on (duty not applied)

[32] $I_{1ph} = S_{1\varphi,run}/U_{1ph}$, $S_{run} = \Sigma\ P_i \cdot k_i/\cos\varphi_i$
= 221.05 / 230
= 0.9611 A
Single-phase bus current, loads while on (duty not applied)
[33] $I_{DC} = P_{DC,run}/U_{DC}$, $P_{DC,run} = \Sigma$ DC $P_i \cdot k_i$
= 120 / 24
= 5 A
DC bus current, loads while on (duty not applied)
[34] $\Phi = \Sigma\ h_i \cdot P_i \cdot d_i \cdot k_i + P_{DC} \cdot (1/\eta_{PSU} - 1)$
= 0.09×11 + 0.09×0 + 0.3×0.06 + 0×0.002 + 0.1×0.096 + 0.1×0.024 + PSU loss 0.013333
= 1.0333 kW
Heat dissipated inside the enclosure (→ E2)
[35] $P_{DC} = \Sigma$ DC $P_i \cdot d_i \cdot k_i$
= 120 W
= 120 W
DC demand (duty-weighted)
[36] $P_{DC,run} = \Sigma$ DC $P_i \cdot k_i$
= 120 W
= 120 W
DC load while on (duty not applied)
[37] $P_{PSU,req}$ = margin * $P_{DC,run}$ / f_{derate}
= 1.25 × 120 W / 1
= 150 W
Minimum PSU rating (the supply carries the load while it is on)
[38] $S_{T,req}$ = margin * S_{dem}
= 1.25 × 12.993 kVA
= 16.241 kVA
Minimum transformer rating for the running load
[39] $S_{peak} = S_{dem} + \max(m_i \cdot P_i/\cos\varphi_i - S_i)$
= 12.993 + 70.349 (Duty pump starting)
= 83.342 kVA
Peak apparent power while the largest load starts
[40] $S_{T,req,start} = S_{peak} / k_T$
= 83.342 kVA / 3
= 27.781 kVA
Minimum transformer rating for the starting peak
[41] $S_{T,min} = \max(S_{T,req}, S_{T,req,start})$
= max(16.241 kVA, 27.781 kVA)
= 27.781 kVA
Minimum transformer rating (running load and starting peak)
[42] $I_b = \Sigma$ backed $P_i \cdot d_i \cdot k_i/(U_b \cdot \eta_{conv})$
= 120 / (24 × 1)
= 5 A
Battery discharge current
[43] Ah = I_b * t_{auto}
= 5 A × 2 h
= 10 A·h
Discharge capacity
[44] C_{req} = Ah / (DoD * η_b * k_{temp} * k_{age})
= 10 A·h / (0.8 × 0.95 × 1 × 0.8)
= 16.447 A·h
Minimum battery capacity

[45] $U_L = U_{3ph}$
= 400 V
= 400 V
Three-phase line voltage of the bus
[46] pf_{link} = cosφ of the linked machine
= 0.85
= 0.85
Power factor of the linked machine
[48] $u_{PSU} = P_{PSU,req} / P_{PSU}$
= 150 W / 240 W
= 0.625
PSU utilisation
[50] $u_T = S_{T,req} / S_T$
= 16.241 kVA / 25 kVA
= 0.64964
Transformer utilisation
[51] $u_{inrush} = S_{peak} / (k_T * S_T)$
= 83.342 kVA / (3 × 25 kVA)
= 1.1112
Inrush utilisation
[53] $u_{batt} = C_{req} / C_{batt}$
= 16.447 A·h / 17 A·h
= 0.96749
Battery utilisation

5. Results

SYMBOL	VALUE	DESCRIPTION
P_{conn}	22.2 kW	Connected load
P_{dem}	11.182 kW	Demand active power
S_{dem}	12.993 kVA	Demand apparent power
I_{3ph}	18.462 A	Three-phase bus current
I_{1ph}	0.9611 A	Single-phase bus current
I_{DC}	5 A	DC bus current
Φ	1.0333 kW	Heat dissipated inside the enclosure
$P_{PSU,req}$	150 W	Minimum PSU rating
$S_{T,req}$	16.241 kVA	Minimum transformer rating, running load
S_{peak}	83.342 kVA	Peak apparent power at start
$S_{T,req,start}$	27.781 kVA	Minimum transformer rating, starting peak
$S_{T,min}$	27.781 kVA	Minimum transformer rating, running and starting
I_b	5 A	Battery discharge current
Ah	10 A·h	Discharge capacity
C_{req}	16.447 A·h	Minimum battery capacity
U_L	400 V	Three-phase line voltage
pf_{link}	0.85	Power factor of the linked machine
u_{PSU}	0.625	PSU utilisation

SYMBOL	VALUE	DESCRIPTION
u_T	0.64964	Transformer utilisation
u_{inrush}	1.1112	Inrush utilisation
u_{batt}	0.96749	Battery utilisation

6. Checks (governing first)

RESULT	CHECK	DEMAND	CAPACITY	UTILISATION	REF
FAIL	Starting peak against transformer overload	$u_{inrush} = 1.1112$	$u_{inrush} \le 1$	1.11	
PASS	Battery capacity against required	$u_{batt} = 0.96749$	$u_{batt} \le 1$	0.967	
PASS	Transformer rating against required	$u_T = 0.64964$	$u_T \le 1$	0.65	
PASS	PSU rating against required	$u_{PSU} = 0.625$	$u_{PSU} \le 1$	0.625	

7. Applicability

WARNING — record: Tabulated values not taken from a reference record: f_{derate} (PSU derating); DoD, η_b, k_{temp}, k_{age} (Battery factors). Enter each as one so its source, edition and licence travel with it.
WARNING — input.P_add: P_{add} (Additional three-phase load (linked from E1's RMS power)) was not entered; the template default 0 kW is used.
WARNING — input.cosphi_add: $cosphi_{add}$ (Power factor of the additional load) was not entered; the template default 0.85 is used.
WARNING — input.eta_add: η_{add} (Efficiency of the additional load) was not entered; the template default 0.9 is used.
WARNING — input.inrush_add: $inrush_{add}$ (Starting multiple of the additional load) was not entered; the template default 1 is used.
WARNING — input.heat_add: $heat_{add}$ (Share of the additional load's input power released inside the enclosure (a linked machine is outside it: 0)) was not entered; the template default 0 is used.
WARNING — derate: f_{derate}: the ambient is above 40 °C but no PSU derating is entered; read the factor from the manufacturer's curve.
WARNING — battery-charge: t_{auto}: the power supply rating covers the DC loads only. A battery-backed load needs the battery's charging power on top (a 0.1C charge at the battery voltage is a common allowance); check that the supply can charge the battery as well as carry the load.

8. Verification

```
Template elec.load-budget@1.4.1 Content hash 6cbfa0011c9a446f Engine calc-engine/1.0.0
Known-answer cases passed 4/4 Test run 2026-10-23 12:00 UTC TempestOS 0.26.0
```

9. References

1. Linden's Handbook of Batteries.
2. BS EN 60204-1:2018.