RAJALAKSHMI ENGINEERING COLLEGE

V R Krithika Sree 250701371-2025-CSE V2

Started on	Wednesday, 16 September 2026, 9:19 AM
State	Finished
Completed on	Wednesday, 16 September 2026, 9:27 AM
Time taken	8 mins 57 secs
Marks	1.00/1.00
Grade	**10.00** out of 10.00 (**100**%)

Question 1 | Correct Mark 1.00 out of 1.00

Convert the following algorithm into a program and find its time

complexity using counter method.

```
void function(int n)
{
    int c= 0;
    for(int i=n/2; i<n; i++)
        for(int j=1; j<n; j = 2 * j)
            for(int k=1; k<n; k = k * 2)
                c++;
}
```

Note: No need of counter increment for declarations and scanf() and count variable printf() statements.

Input:

A positive Integer n

Output:

Print the value of the counter variable

Answer:

```
#include<stdio.h>

int count =0;

void function(int n){
    int c=0;
    count++;
    for(int i=n/2;i<n;i++){
        count++;
        for(int j=1;j<n;j=2*j){
            count++;
            for(int k=1;k<n;k=k*2){
                count++;
                c++;
                count++;
            }
            count++;
        }
        count++;
    }
    count++;
    printf("%d",count);

}
int main(){
    int n;
    scanf("%d",&n);
    function(n);
    return 0;
}
```

	Input	Expected	Got	
✔	4	30	30	✔
✔	10	212	212	✔

Passed all tests! ✔

Correct

Marks for this submission: 1.00/1.00.

Back to Course