

Arduino and ATmega328 Pin MappingBJ Furman

01SEP2011

Arduino					
Arduino	Symbolic Name				
Pin No.	(using me106.h)	Header			
0	PIN_D0				
1	PIN_D1				
2	PIN_D2				
3	PIN_D3		J1		
4	PIN_D4		JI		
5	PIN_D5				
6	PIN_D6				
7	PIN_D7				
8	PIN_D8				
9	PIN_D9				
10	PIN_D10		J3		
11	PIN_D11		JJ		
12	PIN_D12				
13	PIN_D13				
14	PIN_D14	PIN_A0			
15	PIN_D15	PIN_A1			
16	PIN_D16	PIN_A2	J2		
17	PIN_D17	PIN_A3	J2		
18	PIN_D18	PIN_A4			
19	PIN_D19	PIN_A5			

ATmega328 (see the data sheet)						
ATmega		Symbolic Name	Some			
Pin No.	PORT	<u>Pin</u>	Alt. Fun.			
2	D	PD0	RXD			
3	D	PD1	TXD			
4	D	PD2	INT0			
5	D	PD3	INT1			
6	D	PD4	XCK			
11	D	PD5	OC0B			
12	D	PD6	OC0A/AIN0			
13	D	PD7	AIN1			
14	В	PB0	CLKO/ICP1			
15	В	PB1	OC1A			
16	В	PB2	OC1B			
17	В	PB3	MOSI			
18	В	PB4	MISO			
19	В	PB5	SCK			
23	С	PC0	ADC0			
24	С	PC1	ADC1			
25	С	PC2	ADC2			
26	С	PC3	ADC3			
27	С	PC4	ADC4/SDA			
28	С	PC5	ADC5/SCL			





ATmega328 data sheet, p. 2

http://www.atmel.com/dyn/resources/prod_documents/8

